CITY OF COOS BAY, OREGON

WASTEWATER TREATMENT PLANT 1 PHASE 1A IMPROVEMENTS

SEPTEMBER 2025

SECTION 26 05 04

BASIC ELECTRICAL MATERIALS AND METHODS

Table of Contents	
CONTROL STATIONS	
 CONTROL STATION, C35CS3101 Manufacturer's Certificate of Proper Installation Maintenance Summary Form Bill of Materials Drawings Manuals & Cut Sheets 	
• CONTROL STATION, C35CS3111	
 Manufacturer's Certificate of Proper Installation Maintenance Summary Form Bill of Materials Drawings Manuals & Cut Sheets 	
• CONTROL STATION, C35CS3112	
 Manufacturer's Certificate of Proper Installation Maintenance Summary Form Bill of Materials Drawings Manuals & Cut Sheets 	
• CONTROL STATION, C35CS3121	1
 Manufacturer's Certificate of Proper Installation Maintenance Summary Form Bill of Materials Drawings Manuals & Cut Sheets 	•
• CONTROL STATION, C35CS3122	3
 Manufacturer's Certificate of Proper Installation Maintenance Summary Form Bill of Materials Drawings Manuals & Cut Sheets 	
• CONTROL STATION, C35CS3201	1
 Manufacturer's Certificate of Proper Installation Maintenance Summary Form Bill of Materials Drawings Manuals & Cut Sheets 	
OPTIMAL CONTROL SYSTEMS, INC.	



2324 Three Lakes Road SE Albany, OR 97322 Phone: (541) 967-9323 Fax: (541) 967-9485 Project No. 0723-08MSI

CITY OF COOS BAY, OREGON

WASTEWATER TREATMENT PLANT 1 PHASE 1A IMPROVEMENTS

SEPTEMBER 2025

SECTION 26 05 04

BASIC ELECTRICAL MATERIALS AND METHODS

•	\mathbf{C}	ONTROL STATION, C35CS3211A	283
	0	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION	
	0	MAINTENANCE SUMMARY FORM	
	0	BILL OF MATERIALS	
	0	Drawings	
	0	Manuals & Cut Sheets	
•	\mathbf{C}	ONTROL STATION, C35CS3212A	335
	0	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION	
	0	MAINTENANCE SUMMARY FORM	
	0	BILL OF MATERIALS	
	0	Drawings	
	0	Manuals & Cut Sheets	
•	\mathbf{C}	ONTROL STATION, C35CS3221A	387
	0	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION	
	0	MAINTENANCE SUMMARY FORM	
	0	BILL OF MATERIALS	
	0	Drawings	
	0	Manuals & Cut Sheets	
•	Cc	ONTROL STATION, C35CS3222A	439
	0	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION	
	0	MAINTENANCE SUMMARY FORM	
	0	BILL OF MATERIALS	
	0	Drawings	
	0	Manuals & Cut Sheets	
•	\mathbf{C}	ONTROL STATION, C40CS0201A	491
	0	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION	
	0	MAINTENANCE SUMMARY FORM	
	0	BILL OF MATERIALS	
	0	Drawings	
	0	Manuals & Cut Sheets	
•	\mathbf{C}	ONTROL STATION, C40CS0401A	529
	0	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION	
	0	MAINTENANCE SUMMARY FORM	
	0	BILL OF MATERIALS	
	0	Drawings	
	0	Manuals & Cut Sheets	



OPTIMAL CONTROL SYSTEMS, INC.

2324 Three Lakes Road SE Albany, OR 97322 Phone: (541) 967-9323 Fax: (541) 967-9485 Project No. 0723-08MSI

CITY OF COOS BAY, OREGON

WASTEWATER TREATMENT PLANT 1 PHASE 1A IMPROVEMENTS

SEPTEMBER 2025

SECTION 26 05 04

BASIC ELECTRICAL MATERIALS AND METHODS

•	Co	NTROL STATION, C40CS1001
	Э	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION
	Э	Maintenance Summary Form
	Э	BILL OF MATERIALS
•	0	Drawings
•	0	MANUALS & CUT SHEETS
•	Со	NTROL STATION, C40CS1002619
	0	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION
	Э	MAINTENANCE SUMMARY FORM
	0	BILL OF MATERIALS
	0	Drawings
	С	Manuals & Cut Sheets
		SWITCHES
•	Do	oor Intrusion Limit Switch, C92ZS9401
	Э	MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION
	Э	MAINTENANCE SUMMARY FORM
	0	BILL OF MATERIALS
	С	Manuals & Cut Sheets
SPA	RI	E PARTS691



OPTIMAL CONTROL SYSTEMS, INC.

2324 Three Lakes Road SE Albany, OR 97322 Phone: (541) 967-9323 Fax: (541) 967-9485 Project No. 0723-08MSI THIS PAGE LEFT BLANK



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No.
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivale specific use r			by each manu	facturer for the

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost
Note: Identify parts p	provided by this Contr	act with two asterisks.		

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025





Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3101	PB Enclosure, SS Type 316/316L, NEMA 4X 10.25" H x 3.25" W x 2.75" D	Saginaw Control & Engineering	SCE-4PBSS6	Section 26 05 04	09-I-001, 90-E-304
002	1	C35CS3101	Selector Switch, 2-Position, Black Lever, 1NC/1NO	Eaton	E34VFBL1-1X	Section 26 05 04	09-I-001, 90-E-304
003	2	C35CS3101	Indicating Light, PresTest, LED, Full Voltage, Amber	Eaton	E34FPB297LAP2A	Section 26 05 04	09-I-001, 90-E-304
004	1	C35CS3101	Pushbutton, Flush, Black, 1NO	Eaton	E34PB1-53	Section 26 05 04	09-I-001, 90-E-304
005	1	C35CS3101	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-304
006	4	C35CS3101	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-304
007							
008							
009							
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
030							
030							
032							
033							
034							
035							
036							
037							
038							
039							
040					<u> </u>		

THIS PAGE LEFT BLANK










Н				JOPTIMAL (CONTROL S	SYSTEMS	هد ا
G				2324 THREE			
F				ALBANY, OR			
Ε				PHONE (541) 967-9	9323 FAX (5	41) 967-9485	
D				CLURE 8	& SONS		රා්රා
С				TITLE COOS BAY	WASTE WATER	R TREATMENT F	PLANT
В	2024.02.27.	CORRECTED	KCED		SECONDARY C	LARIFIER 2 ME	CHANISM
A	2023.10.25.	Original Draft	KCD	KCD		JOB NO. 0723-08MS	SI SI
REV	DATE	DESCRIPTION	IINI I	I ME I	2023.10.25	DWG NO. 0723-08MS	I-SC1M-3101
		REVISIONS	Ť	APPROVED HAD			OF 1

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-4PBSS6



Product Specifications:

Part Number: SCE-4PBSS6
Description: S.S. PB Enclosure Height: 10.25" Width: 3.25" Depth: 2.75" Price Code: S1 List Price: \$298.75 Catalog Page: 252 Est. Ship Weight: 4.00 lbs

Construction

- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Captivated cover screws thread into sealed wells.
- 4-way standard pushbutton holes accept all brands of oil-tight pushbuttons, switches and pilot lights. Hole diameter is 1.20 In. (30.5mm).
- Immediate removal of cover is permitted.
- Pour in place oil & water resistant gasket
- Welded mounting provision top and bottom of back.

Application

Designed to house standard pushbuttons, switches and pilot lights in wet and hosed down areas and in corrosive atmospheres.

Finish

#4 brushed finish on all exterior surfaces.

Industry Standards - (IS5)

- NEMA Type 4, 4X, 12 and Type 13UL Listed Type 4, 4X and 12
- CSA Type 4, 4X and 12
- **□** IEC 60529
- IP 66

Similar Part Numbers

SCE-12PBSS6S.S. PB Enclosure SCE-1PBSS6S.S. PB Enclosure SCE-1PBXSS6S.S. PBX Enclosure SCE-2PBSS6S.S. PBX Enclosure SCE-2PBSS6S.S. PBX Enclosure SCE-3PBSS6S.S. PBX Enclosure SCE-3PBSS6S.S. PBX Enclosure SCE-4PBXSS6S.S. PBX Enclosure SCE-4SPBSS6S.S. PB Enclosure SCE-6PBSS6S.S. PB Enclosure

Installation Information

Pushbutton Enclosures

THIS PAGE LEFT BLANK

PUSHBUTTON ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal



Product Identification


30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Non-Illuminated Pushbuttons




Note

 $^{\scriptsize \textcircled{1}}$ Add $\boldsymbol{\textbf{X}}$ at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Non-Illuminated Momentary Pushbutton Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Flush Button

Pushbutton Units





Extended Button



Mushroom Button



Jumbo Mushroom



Contact Flush Button **Extended Button Mushroom Button** Jumbo Mushroom 1 Type **Button Color Catalog Number Catalog Number Catalog Number Catalog Number** 1N0 E34JB1-53X Black E34PB1-53X E34EB1-53X E34LB1-53X Red E34PB2-53X E34EB2-53X E34LB2-53X E34JB2-53X Green E34PB3-53X E34EB3-53X E34LB3-53X E34JB3-53X Red-Engraved EMERG. STOP E34JB2N8-53X 1NC Black E34PB1-51X E34EB1-51X E34LB1-51X E34JB1-51X Red E34PB2-51X E34EB2-51X E34LB2-51X E34JB2-51X E34PB3-51X E34EB3-51X E34LB3-51X E34JB3-51X Green Red-Engraved EMERG. STOP E34JB2N8-51X 1NO-1NC Black E34PB1-1X E34EB1-1X E34LB1-1X E34JB1-1X Red E34PB2-1X E34EB2-1X E34LB2-1X E34JB2-1X Green E34PB3-1X E34EB3-1X E34LB3-1X E34JB3-1X Red-Engraved EMERG. STOP E34JB2N8-1X

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light



Indicating Light Units

Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① Anodized aluminum head—may not be suitable for some corrosive environments.

Pushbuttons

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Momentary Pushbutton Operators, Non-Illuminated

	Button	Color	Catalog Number	
E34PB_	Flush button	Black	E34PB1	
		Red	E34PB2	
		Green	E34PB3	_
		Yellow	E34PB4	
		White	E34PB5	_
		Blue	E34PB6	_
		Gray	E34PB7	_
		Orange	E34PB8	_
E34EB_	Extended button	Black	E34EB1	_
		Red	E34EB2	_
		Green	E34EB3	_
16311		Yellow	E34EB4	_
WELL		White	E34EB5	_
		Blue	E34EB6	_
		Gray	E34EB7	
		Orange	E34EB8	_
E34EHB_	Half shrouded button		Vertical	Horizontal
D		Black	E34EVB1	E34EHB1
Alle .		Red	E34EVB2	E34EHB2
		Green	E34EVB3	E34EHB3
		Yellow	E34EVB4	E34EHB4
		White	E34EVB5	E34EHB5
		Blue	E34EVB6	E34EHB6
		Gray	E34EVB7	E34EHB7
		Orange	E34EVB8	E34EHB8
E34LB_	Mushroom button	Black	E34LB1	
		Red	E34LB2	_
		Green	E34LB3	_
W - (4/6)		Yellow	E34LB4	_
		Blue	E34LB6	
E34JB_	Anodized aluminum jumbo	Black	E34JB1	_
-	mushroom button ①	Red	E34JB2	<u> </u>
		Red (Engraved EMERG. STOP)	E34JB2N8	_
		Green	E34JB3	_
ALC: N		Yellow	E34JB4	

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V 5 E34P 5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



	Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
(Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
,	X	0	M /M	1NC	ملہ	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
	0	X	IVI VIVI	1N0	-					

Three-Position Maint.

Three-Position Selector Switch



Operator Position ①								Non-Illuminated		Illuminated—120V Transformer		
			Operator Action ^②	Contact Type	Mounting A	Location B	Cam Code	Black Knob	Black Lever Catalog Number [®]	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③	
X 0	0	0 X	M	1N0	 		3	E34VHBK <u>1</u> -2X	E34VHBL <u>1</u> -2X	E34VHB120TER-2X	E34VHB120TFR-2X	
			_	1N0		 						
Χ	0	0		1N0			3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X	
0	Χ	0			○							
0	0	Χ		2NC (Series)	-مىه	—aro						
				1N0		 						

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Opera	ator Po	osition	1					Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number [®]	Black Lever Catalog Number [®]	Red Knob	Red Lever Catalog Number ^③
Ì	Χ	0	0	0	M M	1NC	ملہ	7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0	Χ	0	0	_\/_							
,	0	0	Χ	0	M	1NO	1					
	0	0	0	Χ			0 0					
						1N0	0 0					
						1NC	ملہ					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter
Black	1	White	5
Red	2	Blue	6
Green	3	Gray	7
Yellow	4	Orange	8

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0	" Patterr	1	Top A	Bottom B	Top A	Bottom B
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Х	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

① Wired in series.

Three-Position Switch—Cam and Contact Block Selection

				Contact Blocks Required to Accomplish Circuit Function (Jumpers must be installed where indicated)				
	Desired Circuit and Operator Position			Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location		
No.				Top Bottom Plunger Plunger A B	r	Bottom Plunger B		
1	Х	0	0		→ — — — N0			
2	Х	Х	0	−O_L_C NC	-	NC		
3	X	0	X	 NO	TO 0-	NO NO		
4	0	0	Х	 _O C NO	<u>-</u>	 		
5	0	Х	Х	NC NO	NC NC			
6	0	X	0	— <u>О. І. О</u> — NC	NC	NC NC		

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Χ	0	0	0	–o⊥o– NC		10	Χ	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0		
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	X	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	To -o-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	Х		NC NC	13	Х	0	Х	X		010
8	Χ	Х	0	0	TO LO	NO NO	_					NO NC	NC
9	0	X	0	X		NO NC	14	X	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountir	
Positions	Action ①	Cam Code ③	Catalog Number ④
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M .	2	E34VJB <u>K1</u>
	s M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M 👡	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>
	MM		

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ³		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A 4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	_	10250T71E ^③	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 ^③	_	10250T47E ^③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3®	_	10250T57E ^③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	_	10250T45E ^③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ^③	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	-		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification			
Climate Conditions				
Operating temperature	1° to 150°F (-17° to 66°C)			
Storage temperature	-40° to 176°F (−40° to 80°C)			
Altitude	6,562 ft (2,000m)			
Humidity	Max. 95% RH at 60°C			
Terminals				
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).			
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors			
Torque	7 lb-in (0.8 Nm)			
Degree of protection against direct electrical contact	IP2X with fingerproof shroud			
Light Units				
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1			
Bulbs—average life:				
Transformer type	20,000 hrs.			
Resistor/direct voltage type	2500 hrs. minimum at rated V			
LED	60,000 to 100,000 hrs.			

Electrical Ratings

Description	Specification			
Insulation	U _i = 660 Vac or Vdc			
Thermal	$I_{th} = 10A$			
Short Circuit Coordination to IEC/EN 609	47-5-1			
Rated conditional short circuit current	1 kA			
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1			
UL rating	A600, P600			
AC load life duty cycle 1200 operations/hour				
10A	110V pf 0.4—1 x 10 ⁶ operations			
5A	250V pf 0.4—1 x 10 ⁶ operations			
2A	600V pf 0.4—1 x 10 ⁶ operations			
Switching capacity				
AC 15 rated make/break (11 x I _e at 1.1 x U _e)				
6A	120V pf 0.3			
4A	240V pf 0.3			
2A	660V pf 0.3			
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)				
1.0A	125V L/R ≥0.95 at 300 ms			
0.55A	250V L/R ≥0.95 at 300 ms			
0.1A	660V L/R ≥0.95 at 300 ms			
10A	110V pure resistive			
Maximum ratings for logic level and hostile atmosphere application				
Maximum amperes	0.5A			
Maximum volts	120 Vac/Vdc			
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.			
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.			

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600,	A300 and B300 f	or AC and	P600 for DC	;			
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)					
Plate	A	В	C	D		
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)		
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)		
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)		

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LAP2A

Catalog Number: E34FPB297LAP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Amber, Plastic, 120 V





Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LAP2A

UPC Product Length/Depth

782114718971 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications
FDA 3-A CSA Certified
CE Marked UL Listed

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4X

NEMA 13

NEMA 3R

NEMA 12

NEMA 3

NEMA 4

Lens material

Plastic

Lens color

Amber

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LAP2A

Cam selection for pushbutton selectors


Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.





Eaton E34PB1-53

Catalog Number: E34PB1-53

E34, 30.5 mm, Corrosion Resistant, NEMA 3, 3R, 4, 4X, 12, 13, Non-illuminated, Momentary, Black actuator, Flush, 1NO, Black bezel, Plastic actuator

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34PB1-53

UPC Product Length/Depth 782114958018 3 in

Product Height Product Width

2 in 2 in

Product Weight Warranty
0.25 lb 1 year

Compliances Certifications
CE Marked CSA Certified
FDA 3-A UL Listed



Product specifications

Contact configuration

1 NO

Series

E34

Type

Pushbutton

Actuator color

Black

Operating mode

Momentary

Actuator material

Plastic

Rating

NEMA 4X

NEMA 13

NEMA 3R

NEMA 12

NEMA 3

NEMA 4

Illumination

Non-illuminated

Mounting method

Flush

Bezel

Black

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34PB1-53

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.






Eaton E34VFBL1-1X

Catalog Number: E34VFBL1-1X

Eaton E34 pushbutton, Assembled Selector Switch, E34, 30.5 mm, Corrosion Resistant, Cam 1, 60° throw, NEMA 3, 3R, 4, 4X, 12, 13, Non-illuminated, Two-position, Knob, Black actuator, 1NO-1NC.





Product Name

Eaton E34 pushbutton

UPC

782113891637

Product Height

1 in

Product Weight

1 lb

Compliances

CE Marked FDA 3-A

Catalog Notes

Assembled at Factory

Catalog Number

E34VFBL1-1X

Product Length/Depth

1 in

Product Width

1 in

Warranty

1 year

Certifications

CSA Certified

UL Listed



Product specifications

Contact configuration

1 NO-1 NC

Throw type

60°

Series

E34

Number of positions

Type

30.5 mm, Corrosion Resistant

Actuator color

Black

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Illumination

Non-illuminated

Cam code

Cam 1

Actuator

Knob

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34VFBL1-1X

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:		
EQPT TAG NO:	EQPT/SYSTEM:		
PROJECT NO:	SPEC. SECTION:		
I hereby certify that the above-referenced ed	quipment/system has been:		
(Check Applicable)			
☐ Installed in accordance with Manufa	acturer's recommendations.		
☐ Inspected, checked, and adjusted.			
Serviced with proper initial lubrican	ts.		
☐ Electrical and mechanical connection	ns meet quality and safety standards.		
☐ All applicable safety equipment has	been properly installed.		
☐ Functional tests.			
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)		
Note: Attach any performance test docu	mentation from manufacturer.		
Comments:			
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all		
Date:	, 20		
Manufacturer:			
By Manufacturer's Authorized Representati			
	(Authorized Signature)		



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:						
1. EQUIPME	NT ITEM							
2. MANUFA	2. MANUFACTURER							
3. EQUIPMENT/TAG NUMBER(S)								
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)						
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _							
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE						
a.	Name_	Telephone No.						
	Address	-						

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal	
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.					

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost	
Note: Identify parts provided by this Contract with two asterisks.					

Bill of Materials


Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025



Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3111	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-002, 90-E-306
002	1	C35CS3111	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-002, 90-E-306
003	1	C35CS3111	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-002, 90-E-306
004	1	C35CS3111	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-002, 90-E-306
005	1	C35CS3111	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-002, 90-E-306
006	1	C35CS3111	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-002, 90-E-306
007	1	C35CS3111	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-002, 90-E-306
008	1	C35CS3111	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
009	3	C35CS3111	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
010			,	,			
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040					l	<u> </u>	







Н				OPTIMAL CONTROL SYSTEMS A
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
Ε				PHONE (541) 967-9323 FAX (541) 967-9485
D				CLIENT MCCLURE & SONS
С	2024.3.11	TERMINAL BLOCKS	HAD	COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCEI	
A	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	INII	MENT ME 2022 10 25 PM M 7222 10MST 20101 2111
		REVISIONS		APPROVED SCALE NUME SHEET 1 OF 1





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS





Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.


Industry Standards - (IS17) NEMA Not Applicable

- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)


Keps Nut (x2)

- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL







Your Enclosure Source ®



SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs

Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

30.5 mm Corrosion Resistant Watertight/Oiltight—E34



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac 50/60 Hz	Red	#755	E34TB120H2X
		Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass () Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V5 E34P5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal One-Hole Mounting ³

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number
uminum Dial Plate 🐠
E34PDB1F1
E34PDB1F2
E34PDB1F5
E34PDB1F10
E34PDB1F25
E34PDB1F50
E34PDB1A0
E34LP99

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote ® below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator Position ①						Non-Illuminated		Illuminated—120V Transformer		
		Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ³	Red Lever Catalog Number ^③	
X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X	
U	Х	IVI VIVI	1N0							

Three-Position Maint.

Three-Position Selector Switch



Opera	Derator Position ①							Non-Illuminated		Illuminated—120V Transformer		
			Operator Action ^②	Contact Type	Mounting A	J Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③	
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X	
			_	1N0		→ •						
Χ	0	0		1N0			3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X	
0	Χ	0			0 0							
0	0	X		2NC (Series)	-مىن	صىه						
				1N0		→						

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Oper:	ator P	osition	11						Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ②	Contact Type	Mounting A	Location B	Calli		Black Lever Catalog Number ®	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
Ì	X	0	-	0	м м	1NC	<u>م ا ه</u>		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0 0 0	X 0 0		0 0 X	M	1N0	→						
						1N0		~ ~					
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter	
Black	1	White	5	
Red	2	Blue	6	
Green	3	Gray	7	
Yellow	4	Orange	8	

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0" Pattern		Top A	Bottom B	Top A	Bottom B	
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Χ	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function					
No.	D		Top Plunger A	Bottom Plunger B				
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC				
2	0	Х	or NO	 				

Note

① Wired in series.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Three-Position Switch—Cam and Contact Block Selection

				Contact Blocks Requi (Jumpers must be ins	Function	
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Χ	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Х	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0	TO 0	
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	X	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X	N0	NC NC	13	X	0	Х	X	To o	010
8	Χ	X	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	X	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountin	
Positions	Action ①	Cam Code ③	Catalog Number [®]
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M _	2	E34VJB <u>K1</u>
	s M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M 👡	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>
	MM		

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ^③		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification			
Insulation	U _i = 660 Vac or Vdc			
Thermal	$I_{th} = 10A$			
Short Circuit Coordination to IEC/EN 609	47-5-1			
Rated conditional short circuit current	1 kA			
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1			
UL rating	A600, P600			
AC load life duty cycle 1200 operations/hour				
10A	110V pf 0.4—1 x 10 ⁶ operations			
5A	250V pf 0.4—1 x 10 ⁶ operations			
2A	600V pf 0.4—1 x 10 ⁶ operations			
Switching capacity				
AC 15 rated make/break (11 x I _e at 1.1 x U _e)				
6A	120V pf 0.3			
4A	240V pf 0.3			
2A	660V pf 0.3			
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)				
1.0A	125V L/R ≥0.95 at 300 ms			
0.55A	250V L/R ≥0.95 at 300 ms			
0.1A	660V L/R ≥0.95 at 300 ms			
10A	110V pure resistive			
Maximum ratings for logic level and hostile atmosphere application				
Maximum amperes	0.5A			
Maximum volts	120 Vac/Vdc			
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.			
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.			

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600,	A300 and B300 f	or AC and	P600 for DC	;			
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)					
Plate	Α	В	C	D		
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)		
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)		
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)		

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications FDA 3-A **UL** Listed CE Marked **CSA** Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty 0.3 lb 1 year

Compliances
CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats. THIS PAGE LEFT BLANK

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications						
	CU10	-200°C to 260°C	-328°F to 500°F			
Input Ranges	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current	CU10, PT100 500 μA ±50 μA PT1000 80 μA ±20 μA					
Common Mode Range		0 - 3.5 VD	С			
Output Range		4-20 mA (linea	rized)			
Maximum Inaccuracy	0.35% FSO / CU10 0.2% FSO @ 25°C / PT100 & PT1000 0.26% FSO @ 60°C / PT100 & PT1000					
Maximum Loop Supply		30VDC				
Load Impedance	0Ω minimum					
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V					
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000					
Output Slew Rate	1% @ 20 mS					
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz					
Stability		0.05% FSO ma	ximum			
Operating Temperature		0 to 60°C (32 to	140°F)			
Storage Temperature		-20 to 70°C (-4 to	158°F)			
Relative Humidity	5 to 90% (non-condensing)					
Environmental Air	No corrosive gases permitted					
Vibration		ML STD 810C	514.2			
Shock		ML STD 810C	516.2			
Noise Immunity		NEMA ICS3-	304			

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

	FC Series Terminal Blocks					
FC Series Model	Terminal Block Replacement Part Number	Package Includes				
FC-11						
FC-33	EO EMM	(2) 2-pole blocks				
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks				
FC-T1		()				
FC-ISO-C						
FC-ISO-D		(6) 2-pole blocks				
FC-B34		(2) 3-pole blocks				
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks				
FC-P3		(1) 6-pole blocks				
FC-3RLY2		(2) 8-pole blocks				
FC-3RLY4						

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners						
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price		
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00		
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00		

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Input Ranges	Switch Position							
input rianges	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges			
	CU10	-200°C to 260°C	-328°F to 500°F	
	PT100	-200°C to 850°C	-328°F to 1562°F	
	PT1000	-200°C to 595°C	-328°F to 1103°F	
RTD Excitation Current	CU10 & PT100	500μA :	± 50μA	
TITO EXCITATION GUITGIN	PT1000	80μA ±	: 20μΑ	
Common Mode Range	0-3.5 VDC			
Maximum Inggayyayı	CU10	0.35%	FS0	
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C		
(moradoo onoot, opan, Emourty)	PT100 & PT1000 0.26% FS0			
Maximum Loop Supply	30VDC			
Load Impedance	0Ω Minimum			
Maximum Load	12V Power Supply	203Ω		
maximum Luau	24V Power Supply	745Ω		
Linearity Error	CU10	0.35% FS0		
Lilicality Lilui	PT100 & PT1000	0.2%FS0 Maximum		
Output Slew Rate	1% @ 20mS			
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz			
Stability	0.05% FSO Maximum			

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No.
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.				

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost
Note: Identify parts p	provided by this Contr	act with two asterisks.		

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025



Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3112	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-002, 90-E-306
002	1	C35CS3112	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-002, 90-E-306
003	1	C35CS3112	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-002, 90-E-306
004	1	C35CS3112	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-002, 90-E-306
005	1	C35CS3112	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-002, 90-E-306
006	1	C35CS3112	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-002, 90-E-306
007	1	C35CS3112	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-002, 90-E-306
008	1	C35CS3112	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
009	3	C35CS3112	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
010	Ŭ	00000112	Eogona i ideo	Systems, me.		25 de 44	30 L 000
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
037							
039							
040							

THIS PAGE LEFT BLANK





H G F				OPTIMAL CONTROL SYSTEMS 2324 THREE LAKES RD / PO BOX 462 ALBANY, OR 97321
E				PHONE (541) 967-9323 FAX (541) 967-9485
D				CUENT MCCLURE & SONS
С	2024.3.11	TERMINAL BLOCKS	HAD	COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCEI	C35CS3112 SECONDARY CLARIFIER 1 RAS PUMP 2
Α	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	IINII	DATE 2023.10.25 DWG NO. 0723-08MSI-SC1R2-3112
		REVISIONS		MPPROVED

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

THIS PAGE LEFT BLANK

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK



Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.

Industry Standards - (IS17) NEMA Not Applicable


- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

THIS PAGE LEFT BLANK

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)

Keps Nut (x2)


- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL



THIS PAGE LEFT BLANK





SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs



Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

THIS PAGE LEFT BLANK



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E3	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass ① Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34V2	E34P2	
Green	E34V3	E34P3	
Yellow	E34V4	E34P4	
White	E34V5	E34P5	
Blue	E34V6	E34P6	
Ambler	E34V9	E34P9	
Clear	E34V0	E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number 0hms 2 Watt (60V Max.) Single Potentiometer with Standard Aluminum Dial Plate 40 E34PDB1F1 2500 E34PDB1F2 5000 E34PDB1F5 10000 E34PDB1F10 25000 E34PDB1F25 50000 E34PDB1F50 E34PDB1A0 Operator only 6 Alternative—black plastic large legend with standard markings E34LP99 Dimensions, see Page V7-T1-322.

. .

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote
 below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

Standard LED Lamp

24V

LED Selection

Blue

White

E22LED048BN

E22LED048WN

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED060ON
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN	 ;	Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED0480N			
	Yellow	E22LED048YN			
	Green	E22LED048GN			

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
		Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ³	Red Lever Catalog Number ^③
X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
U	Х	IVI VIVI	1N0						

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)		Non-Illuminated		Illuminated—120V Transformer				
			Operator Action ^②	Contact Type	Mounting A	J Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		→ •					
Χ	0	0		1N0	\bot		3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			0 0						
0	0	X		2NC (Series)	-مىن	صىه					
				1N0		→					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Opera	ator Po	osition	(1)						Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ^②	Contact Type	Mounting A	Location B	Gaill	Black Knob Catalog Number ^③	Black Lever Catalog Number [®]	Red Knob Catalog Number ^③	Red Lever Catalog Number [®]
Ì	X O	0 X	0	0	мм	1NC	مله		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
,	0 0		Χ	0 X	M M	1N0	~ ~						
						1N0							
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter
Black	1	White	5
Red	2	Blue	6
Green	3	Gray	7
Yellow	4	Orange	8

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Code #3		
No.	"X-0" Pattern		1	Top A	Bottom B	Top A	Bottom B	
1	Х	0	0	- -	D 0.10-	-0 -0-	_	
				NO	NC	NO		
4	0	0	Х	_	-0 -0-	_	-0 0-	
					NO		NO	

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

Wired in series.

Three-Position Switch—Cam and Contact Block Selection

					ocks Required to Acc nust be installed whe		Function
	Desired C	Circuit and		Operator w	ith Cam Code #2	Operator w	ith Cam Code #3
	Operator	Position		Mounting I	Location	Mounting I	Location
No.				Top Plunger A	Bottom Plunger B	Top Plunger A	Bottom Plunger B
1	Х	0	0		OL_O NC	_ 	
2	Х	Х	0		NC		—O_LO— NC
3	X	0	X	 NO		TO 0-	NO NO
4	0	0	Х		 NO		 NO
5	0	Х	Х	TO LO	NO NO	NC	
6	0	Х	0	— <u>0_1_0</u> NC		NC	NC

Four-Position Switch—Contact Block Selection

		ed Circuit tor Positi		<i>(</i> ?h)	Contact B Required t Accomplis Function Mounting Top Plunger	co sh Circuit Location Bottom Plunger			ed Circui tor Posit		<i>(</i> ?h)	Contact B Required t Accomplis Function Mounting Top Plunger	to sh Circuit Location Bottom Plunger
No.	All	- All			A	В	No.	A)	A)			A	В
1	Х	0	0	0	− <u>o </u>		10	Χ	0	Χ	0		
2	0	Х	0	0		 N0						NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0		-0 -0
4	0	0	0	Χ		—Q⊥O— NC	_					NC NO	NO
5	Х	0	0	Х	TO LO	NC NC	12	0	Х	Х	Х	70-0-	<u> </u>
6	0	Х	Х	0	TO O	NO NO	_					NO	NC NO
7	0	0	Х	Х	 NO	NC NC	13	Х	0	Х	Х	To -0	010
8	X	Х	0	0	TO LO	NO NO	_					NO NC	NC
9	0	X	0	X		To old	14	Х	Х	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountir	
Positions	Action ①	Cam Code ^③	Catalog Number ®
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M .	2	E34VJB <u>K1</u>
	S M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ^③		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A 4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	К8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
Δ Ι Ω Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Func	tion Blocl	ks ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	_	10250T71E ^③	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3®	_	10250T47E ^③	_
7 0 0 0	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 ³⁴	_	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	_	10250T45E ③	_
<u>a L o</u>	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ^③	_
Special Purpo	se Block	S ⁽⁵⁾				
0 0 0 0	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®			

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- @ Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

	Description	Req.	Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification					
Insulation	U _i = 660 Vac or Vdc					
Thermal	$I_{th} = 10A$					
Short Circuit Coordination to IEC/EN 609	47-5-1					
Rated conditional short circuit current	1 kA					
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1					
UL rating	A600, P600					
AC load life duty cycle 1200 operations/hour						
10A	110V pf 0.4—1 x 10 ⁶ operations					
5A	250V pf 0.4—1 x 10 ⁶ operations					
2A	600V pf 0.4—1 x 10 ⁶ operations					
Switching capacity						
AC 15 rated make/break (11 x I _e at 1.1 x U _e)						
6A	120V pf 0.3					
4A	240V pf 0.3					
2A	660V pf 0.3					
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)						
1.0A	125V L/R ≥0.95 at 300 ms					
0.55A	250V L/R ≥0.95 at 300 ms					
0.1A	660V L/R ≥0.95 at 300 ms					
10A	110V pure resistive					
Maximum ratings for logic level and hostile atmosphere application						
Maximum amperes	0.5A					
Maximum volts	120 Vac/Vdc					
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.					
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.					

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc				
Description	120	240	480	600	24/28	125	250		
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC									
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55		
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55		
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0		
Voltamperes:									
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138		
Normal load break	720	720	720	720	138	138	138		

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)						
Plate	A	В	C	D			
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)			
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)			
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)			

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications

FDA 3-A UL Listed

CE Marked CSA Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors


Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty
0.3 lb 1 year

Compliances

CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats.

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications						
	CU10	CU10 -200°C to 260°C -328°F to 500°				
Input Ranges	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current		CU10, PT100 500 μ PT1000 80 μΑ:				
Common Mode Range		0 - 3.5 VD	С			
Output Range		4-20 mA (linea	rized)			
Maximum Inaccuracy		0.35% FSO / 0 0.2% FSO @ 25°C / PT 0.26% FSO @ 60°C / PT	100 & PT1000			
Maximum Loop Supply		30VDC				
Load Impedance		0Ω minimu	m			
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V					
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000					
Output Slew Rate	1% @ 20 mS					
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz					
Stability		0.05% FSO ma	ximum			
Operating Temperature		0 to 60°C (32 to	140°F)			
Storage Temperature		-20 to 70°C (-4 to	158°F)			
Relative Humidity	5 to 90% (non-condensing)					
Environmental Air	No corrosive gases permitted					
Vibration		ML STD 810C	514.2			
Shock	ML STD 810C 516.2					
Noise Immunity		NEMA ICS3-	304			

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

FC Series Terminal Blocks					
FC Series Model	Terminal Block Replacement Part Number	Package Includes			
FC-11					
FC-33	EO EMM	(2) 2-pole blocks			
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks			
FC-T1		(1) 1 polo blooks			
FC-ISO-C					
FC-ISO-D		(6) 2-pole blocks			
FC-B34		(2) 3-pole blocks			
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks			
FC-P3		(1) 6-pole blocks			
FC-3RLY2		(2) 8-pole blocks			
FC-3RLY4					

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners					
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price	
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00	
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00	

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Innut Ranges				Switch I	Position	ı		
Input Ranges	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges				
	CU10	-200°C to 260°C	-328°F to 500°F		
	PT100	-200°C to 850°C	-328°F to 1562°F		
	PT1000	-200°C to 595°C	-328°F to 1103°F		
RTD Excitation Current	CU10 & PT100	500μA ± 50μA			
TITO EXCITATION GUITGIN	PT1000	80μA ±	: 20μΑ		
Common Mode Range	0-3.5 VDC				
Maximum Inggayyayı	CU10	0.35% FSO			
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C			
(monutes onset, span, Linearity)	PT100 & PT1000 0.26% FS0				
Maximum Loop Supply	30VDC				
Load Impedance	0Ω Minimum				
Maximum Load	12V Power Supply	203Ω			
maximum Luau	24V Power Supply	745Ω			
Linearity Error	CU10	0.35% FS0			
Lilicality Lilui	PT100 & PT1000	0.2%FSO Maximum			
Output Slew Rate	1% @ 20mS				
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz				
Stability	0.05% FSO Maximum				

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufacture inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and according to the contained to the	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No.
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivale specific use r			by each manu	facturer for the

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost
Note: Identify parts p	provided by this Contr	act with two asterisks.		

Bill of Materials


Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025



Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3121	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-002, 90-E-306
002	1	C35CS3121	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-002, 90-E-306
003	1	C35CS3121	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-002, 90-E-306
004	1	C35CS3121	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-002, 90-E-306
005	1	C35CS3121	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-002, 90-E-306
006	1	C35CS3121	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-002, 90-E-306
007	1	C35CS3121	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-002, 90-E-306
008	1	C35CS3121	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
009	3	C35CS3121	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							







H				IOPTIMAL CONTROL SYSTEMS ו
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
Е				PHONE (541) 967-9323 FAX (541) 967-9485
D				CLURE & SONS
c	2024.3.11	TERMINAL BLOCKS	HAD	TITLE COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCED	
A	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	INII	MEMENT ME 2022 10 25 PM MO722 - 10MST - SC11/P1 - 2121
		REVISIONS		APPROVED SCALE NONE SHEET 1 OF 1





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS





Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.


Industry Standards - (IS17) NEMA Not Applicable

- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)


Keps Nut (x2)

- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL







Your Enclosure Source ®



SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs

Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

30.5 mm Corrosion Resistant Watertight/Oiltight—E34



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V5 E34P5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal One-Hole Mounting ³

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number				
2 Watt (60V Max.) Single Potentiometer with Standard Aluminum Dial Plate 👀				
E34PDB1F1				
E34PDB1F2				
E34PDB1F5				
E34PDB1F10				
E34PDB1F25				
E34PDB1F50				
E34PDB1A0				
E34LP99				

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote
 below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator Position ①							Non-Illuminated		Illuminated—120V Transformer	
			Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
	X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
	U	Х	IVI VIVI	1N0						

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)					Non-Illuminated		Illuminated—120V Transformer	
			Operator Action ^②	Contact Type	Mounting A	Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		 					
Χ	0	0		1N0	\bot		3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			○						
0	0	X		2NC (Series)	-مىن	—aro					
				1N0		00					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Operator Position ①								Non-Illuminated		Illuminated—120V Transformer		
					Operator Action ②	Contact Type	Mounting A	Location B	Cam Code	Black Knob Catalog Number ®	Black Lever Catalog Number ®	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
Ì	X	0	-	0	м м	1NC	<u>م ا ه</u>		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0 0 0	X 0 0		0 0 X	M	1N0	→						
						1N0		~ ~					
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter	
Black	1	White	5	
Red	2	Blue	6	
Green	3	Gray	7	
Yellow	4	Orange	8	

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0	" Patterr	1	Top A	Bottom B	Top A	Bottom B
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Χ	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

① Wired in series.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Three-Position Switch—Cam and Contact Block Selection

					red to Accomplish Circuit talled where indicated)	Function
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Х	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Х	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	Х	Х	Х	0	TO 0	
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	X	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X	N0	NC NC	13	X	0	Х	X	To o	010
8	Χ	Х	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	X	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Selector Switch— Vertical Mounting ②			
Positions	Action ①	Cam Code ③	Catalog Number [®]		
Two-position—60° throw	M M	1	E34VFB <u>K1</u>		
	M	1	E34VEB <u>K1</u>		
Three-position—60° throw	M	2	E34VGB <u>K1</u>		
	$M \longrightarrow M$	3	E34VHB <u>K1</u>		
	M _	2	E34VJB <u>K1</u>		
	S M	3	E34VKB <u>K1</u>		
	y M ⋅	2	E34VLB <u>K1</u>		
	SS	3	E34VMB <u>K1</u>		
	M 👡	2	E34VNB <u>K1</u>		
	MS	3	E34VPB <u>K1</u>		
Four-position—40° throw	M M	7	E34VTB <u>K1</u>		
	MM				

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ³		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Technical Data and Specifications

Mechanical Ratings

Description	Specification		
Frequency of Operation			
All pushbuttons	6000 operations/hr.		
Key and lever selector switches	3000 operations/hr.		
Auto-latch devices	1200 operations/hr.		
Life			
Pushbuttons	10 x 10 ⁶ operations		
Contact blocks	10 x 10 ⁶ operations		
PresTest units	10 x 10 ⁶ operations		
Lever and key selector switches	0.25 x 10 ⁶ operations		
Twist to release pushbuttons	0.3 x 10 ⁶ operations		
Shock Resistance			
Duration	210 ms ≥5g		

General Specifications

Description	Specification				
Climate Conditions					
Operating temperature	1° to 150°F (-17° to 66°C)				
Storage temperature	-40° to 176°F (−40° to 80°C)				
Altitude	6,562 ft (2,000m)				
Humidity	Max. 95% RH at 60°C				
Terminals					
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).				
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors				
Torque	7 lb-in (0.8 Nm)				
Degree of protection against direct electrical contact	IP2X with fingerproof shroud				
Light Units					
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1				
Bulbs—average life:					
Transformer type	20,000 hrs.				
Resistor/direct voltage type	2500 hrs. minimum at rated V				
LED	60,000 to 100,000 hrs.				

Electrical Ratings

Description	Specification				
Insulation	U _i = 660 Vac or Vdc				
Thermal	$I_{th} = 10A$				
Short Circuit Coordination to IEC/EN 609	47-5-1				
Rated conditional short circuit current	1 kA				
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1				
UL rating	A600, P600				
AC load life duty cycle 1200 operations/hour					
10A	110V pf 0.4—1 x 10 ⁶ operations				
5A	250V pf 0.4—1 x 10 ⁶ operations				
2A	600V pf 0.4—1 x 10 ⁶ operations				
Switching capacity					
AC 15 rated make/break (11 x I _e at 1.1 x U _e)					
6A	120V pf 0.3				
4A	240V pf 0.3				
2A	660V pf 0.3				
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)					
1.0A	125V L/R ≥0.95 at 300 ms				
0.55A	250V L/R ≥0.95 at 300 ms				
0.1A	660V L/R ≥0.95 at 300 ms				
10A	110V pure resistive				
Maximum ratings for logic level and hostile atmosphere application					
Maximum amperes	0.5A				
Maximum volts	120 Vac/Vdc				
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.				
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.				

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600,	A300 and B300 f	or AC and	P600 for DC	;			
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)							
Plate	A	В	C	D				
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)				
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)				
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)				

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications
FDA 3-A UL Listed
CE Marked CSA Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty 0.3 lb 1 year

Compliances
CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats. THIS PAGE LEFT BLANK

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications							
	CU10	-200°C to 260°C	-328°F to 500°F				
Input Ranges	PT100	-328°F to 1562°F					
	PT1000	-200°C to 595°C	-328°F to 1103°F				
RTD Excitation Current	CU10, РТ100 500 µA ±50 µA РТ1000 80 µA ±20 µA						
Common Mode Range		0 - 3.5 VD	С				
Output Range		4-20 mA (linea	rized)				
Maximum Inaccuracy	0.35% FSO / CU10 0.2% FSO @ 25°C / PT100 & PT1000 0.26% FSO @ 60°C / PT100 & PT1000						
Maximum Loop Supply	30VDC						
Load Impedance	0Ω minimum						
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V						
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000						
Output Slew Rate	1% @ 20 mS						
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz						
Stability		0.05% FSO ma	ximum				
Operating Temperature		0 to 60°C (32 to	140°F)				
Storage Temperature		-20 to 70°C (-4 to	158°F)				
Relative Humidity	5 to 90% (non-condensing)						
Environmental Air	No corrosive gases permitted						
Vibration		ML STD 810C	514.2				
Shock	ML STD 810C 516.2						
Noise Immunity		NEMA ICS3-	304				

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

	FC Series Terminal Blocks							
FC Series Model	Terminal Block Replacement Part Number	Package Includes						
FC-11								
FC-33	EO EMM	(2) 2-pole blocks						
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks						
FC-T1		(1) 1 polo blooks						
FC-ISO-C								
FC-ISO-D		(6) 2-pole blocks						
FC-B34		(2) 3-pole blocks						
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks						
FC-P3		(1) 6-pole blocks						
FC-3RLY2		(2) 8-pole blocks						
FC-3RLY4								

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners									
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price					
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00					
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00					

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Input Ranges		Switch Position						
IIIµut naliyes	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges					
	CU10	-200°C to 260°C	-328°F to 500°F			
	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current	CU10 & PT100	500μA :	± 50μA			
TITO EXCITATION GUITGIN	PT1000	80μA ± 20μA				
Common Mode Range	0-3.5 VDC					
Maximum Inggayyayı	CU10	0.35% FS0				
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C				
(moradoo onoot, opan, Emourty)	PT100 & PT1000 0.26% FS0					
Maximum Loop Supply	30VDC					
Load Impedance	0Ω Minimum					
Maximum Load	12V Power Supply	203Ω				
maximum Luau	24V Power Supply	745Ω				
Linearity Error	CU10	0.35% FSO				
Lilicality Lilui	PT100 & PT1000	0.2%FSO Maximum				
Output Slew Rate	1% @ 20mS					
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz					
Stability	0.05% FSO Maximum					

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	I, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to ent and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:		
1. EQUIPME	NT ITEM			
2. MANUFA	CTURER			
3. EQUIPME	NT/TAG NUMBER(S)			
4. WEIGHT OF INDIVIDUAL COMPONENTS (OVER 100 POUNDS)				
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _			
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE		
a.	Name_	Telephone No		
	Address	-		

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal	
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.					

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost		
Note: Identify parts provided by this Contract with two asterisks.						

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025




Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3122	PB Enclosure, SS Type 316/316L, NEMA 4X 5.75" H x 3.25" W x 2.75" D	Saginaw Control & Engineering	SCE-2PBSS6	Section 26 05 04	09-I-001, 90-E-304
002	1	C35CS3122	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-001, 90-E-304
003	1	C35CS3122	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-001, 90-E-304
004	1	C35CS3122	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-304
005	2	C35CS3122	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-304
006			Ĭ i	,			
007							
008							
009							
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
000							

THIS PAGE LEFT BLANK








Н				OPTIMAL CONTROL SYSTEMS
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
E			Ì	PHONE (541) 967-9323 FAX (541) 967-9485
D				CLIENT MCCLURE & SONS
С				TITLE COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCEI	
A	2023.10 <i>2</i> 5.	Original Draft	KCD	
REV	DATE	DESCRIPTION	IINII	ME 2022 10 25 100 100 100 100 100 100 100 100 100 10
		REVISIONS		APPROVED SCALE NIDNE SHEET 1 OF 1

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-2PBSS6



Product Specifications:

Part Number: SCE-2PBSS6 Description: S.S. PB Enclosure Height: 5.75" Width: 3.25" Depth: 2.75" Price Code: S1 List Price: \$242.12 Catalog Page: 252 Est. Ship Weight: 2.92 lbs

Construction

- 0.063 In. stainless steel Type 316/316L.
 Seams continuously welded and ground smooth.
- Captivated cover screws thread into sealed wells.
- 4-way standard pushbutton holes accept all brands of oil-tight pushbuttons, switches and pilot lights. Hole diameter is 1.20 In. (30.5mm).
- Immediate removal of cover is permitted.
- Pour in place oil & water resistant gasket
- Welded mounting provision top and bottom of back.

Application

Designed to house standard pushbuttons, switches and pilot lights in wet and hosed down areas and in corrosive atmospheres.

Finish

#4 brushed finish on all exterior surfaces.

Industry Standards - (IS5)

- NEMA Type 4, 4X, 12 and Type 13UL Listed Type 4, 4X and 12
- CSA Type 4, 4X and 12
- **□** IEC 60529
- IP 66

Optional Accessories

SCE-ASPB-SS Plug, Hole

Similar Part Numbers

SCE-12PBSS6S.S. PB Enclosure SCE-1PBSS6S.S. PB Enclosure SCE-1PBXSS6S.S. PBX Enclosure SCE-2PBXSS6S.S. PBX Enclosure SCE-3PBSS6S.S. PB Enclosure SCE-3PBXSS6S.S. PBX Enclosure SCE-4PBSS6S.S. PB Enclosure SCE-4PBXSS6S.S. PBX Enclosure SCE-4SPBSS6S.S. PB Enclosure SCE-6PBSS6S.S. PB Enclosure

Installation Information

Pushbutton Enclosures

THIS PAGE LEFT BLANK

PUSHBUTTON ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK

30.5 mm Corrosion Resistant Watertight/Oiltight—E34



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V5 E34P5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
		Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ³	Red Lever Catalog Number ^③
X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
U	Х	IVI VIVI	1N0						

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)					Non-Illuminated		Illuminated—120V T	ransformer
			Operator Action ^②	Contact Type	Mounting A	J Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		→ •					
Χ	0	0		1N0	\bot		3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			0 0						
0	0	X		2NC (Series)	-مىن	صىه					
				1N0		→					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Oper:	ator P	osition	11						Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ②	Contact Type	Mounting A	Location B	Calli		Black Lever Catalog Number ®	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
Ì	X	0	-	0	м м	1NC	<u>م ا ه</u>		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0 0 0	X 0 0		0 0 X	M	1N0	→						
						1N0		~ ~					
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter	
Black	1	White	5	
Red	2	Blue	6	
Green	3	Gray	7	
Yellow	4	Orange	8	

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0	" Patterr	1	Top A	Bottom B	Top A	Bottom B
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Х	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function		
No.	D		Top Plunger A	Bottom Plunger B	
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC	
2	0	Х	or NO	 	

Note

① Wired in series.

Three-Position Switch—Cam and Contact Block Selection

					red to Accomplish Circuit talled where indicated)	Function
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Х	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Χ	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	Х	Х	Х	0		
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	Χ	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X	N0	NC NC	13	X	0	Х	X	TO 0	010
8	Χ	Х	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	X	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountin	
Positions	Action ①	Cam Code ③	Catalog Number [®]
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M _	2	E34VJB <u>K1</u>
	s M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M 👡	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>
	MM		

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection [®]	
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number
Black	K1	E34K1	L1	E34L1	A 1	E34A1
Red	K2	E34K2	L2	E34L2	A2	E34A2
Green	К3	E34K3	L3	E34L3	А3	E34A3
Yellow	K4	E34K4	L4	E34L4	A4	E34A4
White	K5	E34K5	L5	E34L5	A5	E34A5
Blue	К6	E34K6	L6	E34L6	A6	E34A6
Gray	К7	E34K7	L7	E34L7	A7	E34A7
Orange	K8	E34K8	L8	E34L8	A8	E34A8

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5		53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification
Insulation	U _i = 660 Vac or Vdc
Thermal	$I_{th} = 10A$
Short Circuit Coordination to IEC/EN 609	47-5-1
Rated conditional short circuit current	1 kA
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1
UL rating	A600, P600
AC load life duty cycle 1200 operations/hour	
10A	110V pf 0.4—1 x 10 ⁶ operations
5A	250V pf 0.4—1 x 10 ⁶ operations
2A	600V pf 0.4—1 x 10 ⁶ operations
Switching capacity	
AC 15 rated make/break (11 x I _e at 1.1 x U _e)	
6A	120V pf 0.3
4A	240V pf 0.3
2A	660V pf 0.3
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)	
1.0A	125V L/R ≥0.95 at 300 ms
0.55A	250V L/R ≥0.95 at 300 ms
0.1A	660V L/R ≥0.95 at 300 ms
10A	110V pure resistive
Maximum ratings for logic level and hostile atmosphere application	
Maximum amperes	0.5A
Maximum volts	120 Vac/Vdc
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC							
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)		10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)						
Plate	A	В	C	D			
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)			
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)			
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)			

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



THIS PAGE LEFT BLANK

Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications FDA 3-A **UL** Listed **CE Marked CSA** Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty 0.3 lb 1 year

Compliances
CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	EQPT SERIAL NO:		
EQPT TAG NO:	EQPT/SYSTEM:		
PROJECT NO:	SPEC. SECTION:		
I hereby certify that the above-referenced ed	quipment/system has been:		
(Check Applicable)			
☐ Installed in accordance with Manufa	acturer's recommendations.		
☐ Inspected, checked, and adjusted.			
Serviced with proper initial lubrican	ts.		
☐ Electrical and mechanical connection	ns meet quality and safety standards.		
☐ All applicable safety equipment has	been properly installed.		
☐ Functional tests.			
System has been performance tested requirements. (When complete system of	I, and meets or exceeds specified performance of one manufacturer)		
Note: Attach any performance test docu	mentation from manufacturer.		
Comments:			
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to ent and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all		
Date:	, 20		
Manufacturer:			
By Manufacturer's Authorized Representati			
	(Authorized Signature)		

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivale specific use r			by each manu	facturer for the

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost			
Note: Identify parts p	Note: Identify parts provided by this Contract with two asterisks.						

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025





Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3201	PB Enclosure, SS Type 316/316L, NEMA 4X 10.25" H x 3.25" W x 2.75" D	Saginaw Control & Engineering	SCE-4PBSS6	Section 26 05 04	09-I-003, 90-E-304
002	1	C35CS3201	Selector Switch, 2-Position, Black Lever, 1NC/1NO	Eaton	E34VFBL1-1X	Section 26 05 04	09-I-003, 90-E-304
003	2	C35CS3201	Indicating Light, PresTest, LED, Full Voltage, Amber	Eaton	E34FPB297LAP2A	Section 26 05 04	09-I-003, 90-E-304
004	1	C35CS3201	Pushbutton, Flush, Black, 1NO	Eaton	E34PB1-53	Section 26 05 04	09-I-003, 90-E-304
005	1	C35CS3201	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-304
006	4	C35CS3201	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-304
007							
008							
009							
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							

THIS PAGE LEFT BLANK










Н				OPTIMAL CONTROL SYSTEMS	
G				2324 THREE LAKES RD / PO BOX 462	A
F				ALBANY, OR 97321	
E				PHONE (541) 967-9323 FAX (541) 967-9485	עצ
D				CUENT MCCLURE & SONS)
С				COOS BAY WASTE WATER TREATMENT PLANT	
В	2024.2.27.	CORRECTED	KCEI		
A	2023.10.25.	Original Draft		DRAWN KCD ISSUED JOB NO. 0723-08MSI	
REV	DATE	DESCRIPTION	IINII	MECKE ME 2022 10 25 MM 1722 _ 10MCI _ CC2M_ 2	201
		REVISIONS		APPROVED SCALE NUMBER SHEET 1 OF 1	

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-4PBSS6



Product Specifications:

Part Number: SCE-4PBSS6
Description: S.S. PB Enclosure Height: 10.25" Width: 3.25" Depth: 2.75" Price Code: S1 List Price: \$298.75 Catalog Page: 252 Est. Ship Weight: 4.00 lbs

Construction

- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Captivated cover screws thread into sealed wells.
- 4-way standard pushbutton holes accept all brands of oil-tight pushbuttons, switches and pilot lights. Hole diameter is 1.20 In. (30.5mm).
- Immediate removal of cover is permitted.
- Pour in place oil & water resistant gasket
- Welded mounting provision top and bottom of back.

Application

Designed to house standard pushbuttons, switches and pilot lights in wet and hosed down areas and in corrosive atmospheres.

Finish

#4 brushed finish on all exterior surfaces.

Industry Standards - (IS5)

- NEMA Type 4, 4X, 12 and Type 13UL Listed Type 4, 4X and 12
- CSA Type 4, 4X and 12
- **□** IEC 60529
- IP 66

Similar Part Numbers

SCE-12PBSS6S.S. PB Enclosure SCE-1PBSS6S.S. PB Enclosure SCE-1PBXSS6S.S. PBX Enclosure SCE-2PBSS6S.S. PBX Enclosure SCE-2PBSS6S.S. PBX Enclosure SCE-3PBSS6S.S. PBX Enclosure SCE-3PBSS6S.S. PBX Enclosure SCE-4PBXSS6S.S. PBX Enclosure SCE-4SPBSS6S.S. PB Enclosure SCE-6PBSS6S.S. PB Enclosure

Installation Information

Pushbutton Enclosures

THIS PAGE LEFT BLANK

PUSHBUTTON ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E3	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal



Product Identification


30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Non-Illuminated Pushbuttons




Note

 $^{\scriptsize \textcircled{1}}$ Add $\boldsymbol{\textbf{X}}$ at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Non-Illuminated Momentary Pushbutton Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Flush Button

Pushbutton Units



Extended Button



Mushroom Button



Jumbo Mushroom



Pusnbui	tton Units				
Contact Type	Button Color	Flush Button Catalog Number	Extended Button Catalog Number	Mushroom Button Catalog Number	Jumbo Mushroom ^① Catalog Number
1N0	Black	E34PB1-53X	E34EB1-53X	E34LB1-53X	E34JB1-53X
	Red	E34PB2-53X	E34EB2-53X	E34LB2-53X	E34JB2-53X
	Green	E34PB3-53X	E34EB3-53X	E34LB3-53X	E34JB3-53X
	Red—Engraved EMERG. STOP	_	_	_	E34JB2N8-53X
1NC	Black	E34PB1-51X	E34EB1-51X	E34LB1-51X	E34JB1-51X
	Red	E34PB2-51X	E34EB2-51X	E34LB2-51X	E34JB2-51X
	Green	E34PB3-51X	E34EB3-51X	E34LB3-51X	E34JB3-51X
	Red—Engraved EMERG. STOP	_	_	_	E34JB2N8-51X
1NO-1NC	Black	E34PB1-1X	E34EB1-1X	E34LB1-1X	E34JB1-1X
	Red	E34PB2-1X	E34EB2-1X	E34LB2-1X	E34JB2-1X
	Green	E34PB3-1X	E34EB3-1X	E34LB3-1X	E34JB3-1X
	Red—Engraved EMERG. STOP	_	_	_	E34JB2N8-1X

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light



Indicating Light Units

Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see ${f Pages}$ ${f V7-T1-213}$ to ${f V7-T1-283}$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Pushbuttons

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Momentary Pushbutton Operators, Non-Illuminated

	Button	Color	Catalog Number	
E34PB_	Flush button	Black	E34PB1	
		Red	E34PB2	
		Green	E34PB3	_
		Yellow	E34PB4	
		White	E34PB5	_
		Blue	E34PB6	_
		Gray	E34PB7	_
		Orange	E34PB8	_
E34EB_	Extended button	Black	E34EB1	_
		Red	E34EB2	_
		Green	E34EB3	_
15.11		Yellow	E34EB4	_
WELL		White	E34EB5	_
		Blue	E34EB6	_
		Gray	E34EB7	
		Orange	E34EB8	_
E34EHB_	Half shrouded button		Vertical	Horizontal
D		Black	E34EVB1	E34EHB1
Alle .		Red	E34EVB2	E34EHB2
		Green	E34EVB3	E34EHB3
		Yellow	E34EVB4	E34EHB4
		White	E34EVB5	E34EHB5
		Blue	E34EVB6	E34EHB6
		Gray	E34EVB7	E34EHB7
		Orange	E34EVB8	E34EHB8
E34LB_	Mushroom button	Black	E34LB1	
		Red	E34LB2	_
		Green	E34LB3	_
W 446		Yellow	E34LB4	_
		Blue	E34LB6	
E34JB_	Anodized aluminum jumbo	Black	E34JB1	_
-	mushroom button ①	Red	E34JB2	<u> </u>
		Red (Engraved EMERG. STOP)	E34JB2N8	_
		Green	E34JB3	_
		Yellow	E34JB4	

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass ① Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34V2	E34P2	
Green	E34V3	E34P3	
Yellow	E34V4	E34P4	
White	E34V5	E34P5	
Blue	E34V6	E34P6	
Ambler	E34V9	E34P9	
Clear	E34V0	E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Standard LED Lamp

24V

LED Selection

Blue

White

E22LED048BN

E22LED048WN

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED060ON
ransformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN	 ;	Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED0480N			
	Yellow	E22LED048YN			
	Green	E22LED048GN			

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



	Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
(Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
,	X	0	M /M	1NC	ملہ	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
	0	X	IVI VIVI	1N0	-					

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	ition 1)			Non-Illuminated			Illuminated—120V Transformer		
			Operator Action ^②	Contact Type	Mounting A	Location B	Cam Code	Black Knob	Black Lever Catalog Number [®]	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0	0 X	M	1N0	 		3	E34VHBK <u>1</u> -2X	E34VHBL <u>1</u> -2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		 					
Χ	0	0		1N0			3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			○						
0	0	Χ		2NC (Series)	-مىه	—aro					
				1N0		 					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



Operator Position ^①									Non-Illuminated		Illuminated—120V Transformer		
					Operator Action ②	Contact Type	Mounting Location A B	Calli	Black Knob Catalog Number ®	Black Lever Catalog Number ®	Red Knob	Red Lever Catalog Number ®	
ĺ	Χ	0	0	0	M M	1NC	<u>م ا ه</u>	7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X	
١	0 0	X 0	0 X	0	M	4110							
	0	0	Ô	X	101	1N0							
						1N0	 • •						
						1NC	ملہ						

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter
Black	1	White	5
Red	2	Blue	6
Green	3	Gray	7
Yellow	4	Orange	8

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Code #3		
No.	"X-0" Pattern		1	Top A	Bottom B	Top A	Bottom B	
1	Х	0	0	- -	D 0.10-	-0 -0-	_	
				NO	NC	NO		
4	0	0	Х	_	-0 -0-	_	-0 0-	
					NO		NO	

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

			Contact Blocks Required to Accomplish Circuit Function			
No.	A)		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

Wired in series.

Three-Position Switch—Cam and Contact Block Selection

				Contact Blocks Required to Accomplish Circuit Function (Jumpers must be installed where indicated)				
	Desired C	Circuit and		Operator w	ith Cam Code #2	Operator with Cam Code #3		
	Operator	Position		Mounting I	Location	Mounting I	Location	
No.				Top Plunger A	Bottom Plunger B	Top Plunger A	Bottom Plunger B	
1	Х	0	0		OL_O NC	_ 		
2	Х	Х	0		NC		—O_LO— NC	
3	X	0	X	 NO		TO 0-	NO NO	
4	0	0	Х		 NO		 NO	
5	0	Х	Х	TO LO	NO NO	NC		
6	0	Х	0	— <u>0_1_0</u> NC		NC	NC	

Four-Position Switch—Contact Block Selection

Desired Circuit and Operator Position			Required t Accomplis Function	Mounting Location Top Bottom		Desired Circuit and Operator Position			<i>(</i> ?h)	locks to sh Circuit Location Bottom Plunger			
No.	All	- All			A	В	No.	A)	A)			A	В
1	Х	0	0	0	− <u>o </u>		10	Χ	0	Χ	0		
2	0	Х	0	0		 N0						NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0		-0 -0
4	0	0	0	Χ		—Q⊥O— NC	_					NC NO	NO
5	Х	0	0	Х	TO LO	NC NC	12	0	Х	Х	Х	70-0-	<u> </u>
6	0	Х	Х	0	TO O	NO NO	_					NO	NC NO
7	0	0	Х	Х	 NO	NC NC	13	Х	0	Х	Х	To -0	010
8	X	Х	0	0	TO LO	NO NO	_					NO NC	NC
9	0	X	0	X		To old	14	Х	Х	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Selector Switch— Vertical Mounting ②		
Positions	Action ①	Cam Code ^③	Catalog Number ®	
Two-position—60° throw	M M	1	E34VFB <u>K1</u>	
	M	1	E34VEB <u>K1</u>	
Three-position—60° throw	M	2	E34VGB <u>K1</u>	
	$M \longrightarrow M$	3	E34VHB <u>K1</u>	
	M .	2	E34VJB <u>K1</u>	
	S M	3	E34VKB <u>K1</u>	
	y M ⋅	2	E34VLB <u>K1</u>	
	SS	3	E34VMB <u>K1</u>	
	M	2	E34VNB <u>K1</u>	
	MS	3	E34VPB <u>K1</u>	
Four-position—40° throw	M M	7	E34VTB <u>K1</u>	

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever			esigned for ngress Protection ^③
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number
Black	K1	E34K1	L1	E34L1	A1	E34A1
Red	K2	E34K2	L2	E34L2	A2	E34A2
Green	К3	E34K3	L3	E34L3	А3	E34A3
Yellow	K4	E34K4	L4	E34L4	A 4	E34A4
White	K5	E34K5	L5	E34L5	A5	E34A5
Blue	К6	E34K6	L6	E34L6	A6	E34A6
Gray	К7	E34K7	L7	E34L7	A7	E34A7
Orange	К8	E34K8	L8	E34L8	A8	E34A8

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
Δ Ι Ω Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Func	tion Blocl	ks ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	_	10250T71E ^③	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3®	_	10250T47E ^③	_
7 0 0 0	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 ³⁴	_	10250T57E ^③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	_	10250T45E ③	_
<u>a L o</u>	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ^③	_
Special Purpo	se Block	S ⁽⁵⁾				
0 0 0 0	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®			

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- @ Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

	Description	Req.	Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification			
Insulation	U _i = 660 Vac or Vdc			
Thermal	$I_{th} = 10A$			
Short Circuit Coordination to IEC/EN 609	47-5-1			
Rated conditional short circuit current	1 kA			
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1			
UL rating	A600, P600			
AC load life duty cycle 1200 operations/hour				
10A	110V pf 0.4—1 x 10 ⁶ operations			
5A	250V pf 0.4—1 x 10 ⁶ operations			
2A	600V pf 0.4—1 x 10 ⁶ operations			
Switching capacity				
AC 15 rated make/break (11 x I _e at 1.1 x U _e)				
6A	120V pf 0.3			
4A	240V pf 0.3			
2A	660V pf 0.3			
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)				
1.0A	125V L/R ≥0.95 at 300 ms			
0.55A	250V L/R ≥0.95 at 300 ms			
0.1A	660V L/R ≥0.95 at 300 ms			
10A	110V pure resistive			
Maximum ratings for logic level and hostile atmosphere application				
Maximum amperes	0.5A			
Maximum volts	120 Vac/Vdc			
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.			
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.			

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC							
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inc	hes (mm)		
Plate	A	В	C	D
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



THIS PAGE LEFT BLANK

Eaton E34FPB297LAP2A

Catalog Number: E34FPB297LAP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Amber, Plastic, 120 V

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LAP2A

UPC Product Length/Depth

782114718971 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications
FDA 3-A CSA Certified
CE Marked UL Listed

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4X

NEMA 13

NEMA 3R

NEMA 12

NEMA 3

NEMA 4

Lens material

Plastic

Lens color

Amber

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LAP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PB1-53

Catalog Number: E34PB1-53

E34, 30.5 mm, Corrosion Resistant, NEMA 3, 3R, 4, 4X, 12, 13, Non-illuminated, Momentary, Black actuator, Flush, 1NO, Black bezel, Plastic actuator

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34PB1-53

UPC Product Length/Depth 782114958018 3 in

Product Height Product Width

2 in 2 in

Product Weight Warranty
0.25 lb 1 year

Compliances Certifications
CE Marked CSA Certified
FDA 3-A UL Listed



Product specifications

Contact configuration

1 NO

Series

E34

Type

Pushbutton

Actuator color

Black

Operating mode

Momentary

Actuator material

Plastic

Rating

NEMA 4X

NEMA 13

NEMA 3R

NEMA 12

NEMA 3

NEMA 4

Illumination

Non-illuminated

Mounting method

Flush

Bezel

Black

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34PB1-53

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34VFBL1-1X

Catalog Number: E34VFBL1-1X

Eaton E34 pushbutton, Assembled Selector Switch, E34, 30.5 mm, Corrosion Resistant, Cam 1, 60° throw, NEMA 3, 3R, 4, 4X, 12, 13, Non-illuminated, Two-position, Knob, Black actuator, 1NO-1NC.

General specifications



Product Name

Eaton E34 pushbutton

UPC

782113891637

Product Height

1 in

Product Weight

1 lb

Compliances

CE Marked FDA 3-A

Catalog Notes

Assembled at Factory

Catalog Number

E34VFBL1-1X

Product Length/Depth

1 in

Product Width

1 in

Warranty

1 year

Certifications

CSA Certified UL Listed





Product specifications

Contact configuration

1 NO-1 NC

Throw type

60°

Series

E34

Number of positions

Type

30.5 mm, Corrosion Resistant

Actuator color

Black

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Illumination

Non-illuminated

Cam code

Cam 1

Actuator

Knob

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34VFBL1-1X

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced equ	nipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufac	eturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubricants	3.
☐ Electrical and mechanical connection	s meet quality and safety standards.
☐ All applicable safety equipment has b	een properly installed.
☐ Functional tests.	
System has been performance tested, requirements. (When complete system of	and meets or exceeds specified performance one manufacturer)
Note: Attach any performance test docum	nentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Representative of the manufacturer inspect, approve, and operate their equipment recommendations required to ensure equipment and operational, except as may be otherwise information contained herein is true and accurate.	r, (ii) empowered by the manufacturer to t and (iii) authorized to make ent furnished by the manufacturer is complete indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representative	
	(Authorized Signature)

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:_		CONTRACT NO.:	
1. EQUIPMI	ENT ITEM		
2. MANUFA	ACTURER		
3. EQUIPMI	ENT/TAG NUMBER(S)		
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)	
5. NAMEPL	ATE DATA (hp, voltage, speed, etc.) _		
6. MANUFA	ACTURER'S LOCAL REPRESENTAT	IVE	
a.	Name	Telephone No.	
	Address		

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.				

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost	
Note: Identify parts provided by this Contract with two asterisks.					

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025




Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3211A	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-004, 90-E-306
002	1	C35CS3211A	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-004, 90-E-306
003	1	C35CS3211A	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-004, 90-E-306
004	1	C35CS3211A	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-004, 90-E-306
005	1	C35CS3211A	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-004, 90-E-306
006	1	C35CS3211A	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-004, 90-E-306
007	1	C35CS3211A	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-004, 90-E-306
008	1	C35CS3211A	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
009	3	C35CS3211A	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							

THIS PAGE LEFT BLANK







Н				OPTIMAL CONTROL SYSTEMS
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
Ε				PHONE (541) 967-9323 FAX (541) 967-9485
D				CLIENT MCCLURE & SONS
С	2024.3.11	TERMINAL BLOCKS	HAD	COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCED	C35CS3211A SECONDARY CLARIFIER 2 RAS PUMP 1
Α	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION		DATE DWG NO. 0723-08MSI-S2RP1-3211A
·		REVISIONS		APPROVED SCALE NONE SHEET 1 OF 1

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

THIS PAGE LEFT BLANK

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK



Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.

Industry Standards - (IS17) NEMA Not Applicable


- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

THIS PAGE LEFT BLANK

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)

Keps Nut (x2)


- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL



THIS PAGE LEFT BLANK





SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs



Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

THIS PAGE LEFT BLANK



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass () Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V5 E34P5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal One-Hole Mounting ³

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number								
2 Watt (60V Max.) Single Potentiometer with Standard Aluminum Dial Plate 46								
E34PDB1F1								
E34PDB1F2								
E34PDB1F5								
E34PDB1F10								
E34PDB1F25								
E34PDB1F50								
E34PDB1A0								
E34LP99								

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote
 below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator F	Position ①					Non-Illuminated		Illuminated—120V Transformer		
		Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ³	Red Lever Catalog Number ^③	
X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X	
U	Х	IVI VIVI	1N0							

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)					Non-Illuminated		Illuminated—120V Transformer	
			Operator Action ^②	Contact Type	Mounting A	J Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		→ •					
Χ	0	0		1N0	\bot		3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			0 0						
0	0	X		2NC (Series)	-مىن	صىه					
				1N0		→					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Oper:	ator P	osition	11						Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ②	Contact Type	Mounting A	Location B	Calli		Black Lever Catalog Number ®	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
Ì	X	0	-	0	м м	1NC	<u>م ا ه</u>		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0 0 0	X 0 0		0 0 X	M	1N0	→						
						1N0		~ ~					
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter	
Black	1	White	5	
Red	2	Blue	6	
Green	3	Gray	7	
Yellow	4	Orange	8	

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0" Pattern		1	Top A	Bottom B	Top A	Bottom B
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Χ	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

① Wired in series.

Three-Position Switch—Cam and Contact Block Selection

				Contact Blocks Required to Accomplish Circuit Function (Jumpers must be installed where indicated)			
	Desired Circuit and Operator Position			Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location	
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B	
1	Х	0	0		 		
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC	
3	X	0	X	 NO		NO NO	
4	0	0	Х	 O NO		 	
5	0	Х	Х	TO O O			
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC	

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Χ	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Х	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	Х	Х	Х	0	TO 0	
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	X	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X		NC NC	13	X	0	Х	X	To o	010
8	Χ	Х	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	Х	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountin	
Positions	Action ①	Cam Code ③	Catalog Number [®]
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M _	2	E34VJB <u>K1</u>
	s M	3	E34VKB <u>K1</u>
	→ M →	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M 👡	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>
	MM		

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ^③		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification				
Climate Conditions					
Operating temperature	1° to 150°F (-17° to 66°C)				
Storage temperature	-40° to 176°F (−40° to 80°C)				
Altitude	6,562 ft (2,000m)				
Humidity	Max. 95% RH at 60°C				
Terminals					
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).				
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors				
Torque	7 lb-in (0.8 Nm)				
Degree of protection against direct electrical contact	IP2X with fingerproof shroud				
Light Units					
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1				
Bulbs—average life:					
Transformer type	20,000 hrs.				
Resistor/direct voltage type	2500 hrs. minimum at rated V				
LED	60,000 to 100,000 hrs.				

Electrical Ratings

Description	Specification					
Insulation	U _i = 660 Vac or Vdc					
Thermal	$I_{th} = 10A$					
Short Circuit Coordination to IEC/EN 609	47-5-1					
Rated conditional short circuit current	1 kA					
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1					
UL rating	A600, P600					
AC load life duty cycle 1200 operations/hour						
10A	110V pf 0.4—1 x 10 ⁶ operations					
5A	250V pf 0.4—1 x 10 ⁶ operations					
2A	600V pf 0.4—1 x 10 ⁶ operations					
Switching capacity						
AC 15 rated make/break (11 x I _e at 1.1 x U _e)						
6A	120V pf 0.3					
4A	240V pf 0.3					
2A	660V pf 0.3					
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)						
1.0A	125V L/R ≥0.95 at 300 ms					
0.55A	250V L/R ≥0.95 at 300 ms					
0.1A	660V L/R ≥0.95 at 300 ms					
10A	110V pure resistive					
Maximum ratings for logic level and hostile atmosphere application						
Maximum amperes	0.5A					
Maximum volts	120 Vac/Vdc					
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.					
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.					

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc			
Description	120	240	480	600	24/28	125	250	
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC								
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55	
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55	
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0	
Voltamperes:								
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138	
Normal load break	720	720	720	720	138	138	138	

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)						
Plate	A	В	C	D			
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)			
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)			
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)			

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications FDA 3-A **UL** Listed **CE Marked CSA** Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.





Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

© 2023 Eaton. All Rights property of their respective Reserved. owners.

Eaton is a registered trademark.

All other trademarks are





Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty 0.3 lb 1 year

Compliances
CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats.

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications						
	CU10	CU10 -200°C to 260°C -328°F to 500°				
Input Ranges	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current		CU10, PT100 500 μ PT1000 80 μΑ:				
Common Mode Range		0 - 3.5 VD	С			
Output Range		4-20 mA (linea	rized)			
Maximum Inaccuracy		0.35% FSO / 0 0.2% FSO @ 25°C / PT 0.26% FSO @ 60°C / PT	100 & PT1000			
Maximum Loop Supply		30VDC				
Load Impedance		0Ω minimu	m			
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V					
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000					
Output Slew Rate	1% @ 20 mS					
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz					
Stability		0.05% FSO ma	ximum			
Operating Temperature		0 to 60°C (32 to	140°F)			
Storage Temperature		-20 to 70°C (-4 to	158°F)			
Relative Humidity	5 to 90% (non-condensing)					
Environmental Air	No corrosive gases permitted					
Vibration		ML STD 810C	514.2			
Shock	ML STD 810C 516.2					
Noise Immunity		NEMA ICS3-	304			

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

FC Series Terminal Blocks					
FC Series Model	Terminal Block Replacement Part Number	Package Includes			
FC-11					
FC-33	EO EMM	(2) 2-pole blocks			
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks			
FC-T1		(1) 1 polo blooks			
FC-ISO-C					
FC-ISO-D		(6) 2-pole blocks			
FC-B34		(2) 3-pole blocks			
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks			
FC-P3		(1) 6-pole blocks			
FC-3RLY2		(2) 8-pole blocks			
FC-3RLY4					

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners					
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price	
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00	
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00	

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Innut Ranges				Switch I	Position	ı		
Input Ranges	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges				
	CU10	-200°C to 260°C	-328°F to 500°F		
	PT100	-200°C to 850°C	-328°F to 1562°F		
	PT1000	-200°C to 595°C	-328°F to 1103°F		
RTD Excitation Current	CU10 & PT100	500μA ± 50μA			
TITO EXCITATION GUITGIN	PT1000	80μA ±	: 20μΑ		
Common Mode Range	0-3.5 VDC				
Maximum Inggayyayı	CU10	0.35% FSO			
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C			
(monutes onset, span, Linearity)	PT100 & PT1000 0.26% FS0				
Maximum Loop Supply	30VDC				
Load Impedance	0Ω Minimum				
Maximum Load	12V Power Supply	203Ω			
maximum Luau	24V Power Supply	745Ω			
Linearity Error	CU10	0.35% FS0			
Lilicality Lilui	PT100 & PT1000	0.2%FSO Maximum			
Output Slew Rate	1% @ 20mS				
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz				
Stability	0.05% FSO Maximum				

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No.
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.				

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost	
Note: Identify parts provided by this Contract with two asterisks.					

Bill of Materials


Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods

Date: September 2025



Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3212A	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-004, 90-E-306
002	1	C35CS3212A	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-004, 90-E-306
003	1	C35CS3212A	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-004, 90-E-306
004	1	C35CS3212A	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-004, 90-E-306
005	1	C35CS3212A	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-004, 90-E-306
006	1	C35CS3212A	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-004, 90-E-306
007	1	C35CS3212A	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-004, 90-E-306
008	1	C35CS3212A	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
009	3	C35CS3212A	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							





Н				OPTIMAL CONTROL SYSTEMS 🚜
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
Ε				PHONE (541) 967-9323 FAX (541) 967-9485
D				CUENT MCCLURE & SONS
С	2024.3.11	TERMINAL BLOCKS	HAD	COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCED	
Α	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	INII	WIELDER DAIL 2022 10 25 PHIL NO. 722 COMET SORDI 22124
		REVISIONS		APPROVED SCALE NUME SHEET 1 OF 1





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS





Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.


Industry Standards - (IS17) NEMA Not Applicable

- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)


Keps Nut (x2)

- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL







Your Enclosure Source ®



SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs

Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

30.5 mm Corrosion Resistant Watertight/Oiltight—E34



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

 $\label{thm:light_see} \textbf{PsemA 4X 10250T operators where exposed to ultraviolet light, see} \textbf{Pages V7-T1-213} \ to \textbf{V7-T1-283}.$

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass ① Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34V2	E34P2	
Green	E34V3	E34P3	
Yellow	E34V4	E34P4	
White	E34V5	E34P5	
Blue	E34V6	E34P6	
Ambler	E34V9	E34P9	
Clear	E34V0	E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal One-Hole Mounting ³

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number
uminum Dial Plate 🐠
E34PDB1F1
E34PDB1F2
E34PDB1F5
E34PDB1F10
E34PDB1F25
E34PDB1F50
E34PDB1A0
E34LP99

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote ® below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator Position ①						Non-Illuminated		Illuminated—120V Transformer		
		Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ³	Red Lever Catalog Number ^③	
X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X	
U	Х	IVI VIVI	1N0							

Three-Position Maint.

Three-Position Selector Switch



Opera	Derator Position ①							Non-Illuminated		Illuminated—120V Transformer		
			Operator Action ^②	Contact Type	Mounting A	J Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③	
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X	
			_	1N0		→ •						
Χ	0	0		1N0	\bot		3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X	
0	Χ	0			0 0							
0	0	X		2NC (Series)	-مىن	صىه						
				1N0		→						

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Oper:	ator P	osition	11						Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ②	Contact Type	Mounting A	Location B	Calli		Black Lever Catalog Number ®	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
Ì	X	0	-	0	м м	1NC	<u>م ا ه</u>		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0 0 0	X 0 0		0 0 X	M	1N0	→						
						1N0		~ ~					
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter	
Black	1	White	5	
Red	2	Blue	6	
Green	3	Gray	7	
Yellow	4	Orange	8	

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0" Pattern		Top A	Bottom B	Top A	Bottom B	
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Х	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function					
No.	D		Top Plunger A	Bottom Plunger B				
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC				
2	0	Х	or NO	 				

Note

① Wired in series.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Three-Position Switch—Cam and Contact Block Selection

				Contact Blocks Requi (Jumpers must be ins	Function	
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Χ	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Χ	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	Х	Х	Х	0	TO 0	
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	X	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	Х	N0	NC NC	13	X	0	Х	X	TO 0	010
8	Χ	X	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	X	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountin	
Positions	Action ①	Cam Code ③	Catalog Number [®]
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M _	2	E34VJB <u>K1</u>
	s M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M 👡	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>
	MM		

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ^③		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification			
Insulation	U _i = 660 Vac or Vdc			
Thermal	$I_{th} = 10A$			
Short Circuit Coordination to IEC/EN 609	47-5-1			
Rated conditional short circuit current	1 kA			
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1			
UL rating	A600, P600			
AC load life duty cycle 1200 operations/hour				
10A	110V pf 0.4—1 x 10 ⁶ operations			
5A	250V pf 0.4—1 x 10 ⁶ operations			
2A	600V pf 0.4—1 x 10 ⁶ operations			
Switching capacity				
AC 15 rated make/break (11 x I _e at 1.1 x U _e)				
6A	120V pf 0.3			
4A	240V pf 0.3			
2A	660V pf 0.3			
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)				
1.0A	125V L/R ≥0.95 at 300 ms			
0.55A	250V L/R ≥0.95 at 300 ms			
0.1A	660V L/R ≥0.95 at 300 ms			
10A	110V pure resistive			
Maximum ratings for logic level and hostile atmosphere application				
Maximum amperes	0.5A			
Maximum volts	120 Vac/Vdc			
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.			
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.			

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600,	A300 and B300 f	or AC and	P600 for DC	;			
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)					
Plate	A	В	C	D		
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)		
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)		
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)		

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications FDA 3-A **UL** Listed CE Marked **CSA Certified**

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty 0.3 lb 1 year

Compliances
CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats. THIS PAGE LEFT BLANK

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications						
	CU10	-200°C to 260°C	-328°F to 500°F			
Input Ranges	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current	CU10, PT100 500 μA ±50 μA PT1000 80 μA ±20 μA					
Common Mode Range		0 - 3.5 VD	С			
Output Range		4-20 mA (linea	rized)			
Maximum Inaccuracy	0.35% FSO / CU10 0.2% FSO @ 25°C / PT100 & PT1000 0.26% FSO @ 60°C / PT100 & PT1000					
Maximum Loop Supply		30VDC				
Load Impedance	0Ω minimum					
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V					
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000					
Output Slew Rate	1% @ 20 mS					
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz					
Stability		0.05% FSO ma	ximum			
Operating Temperature		0 to 60°C (32 to	140°F)			
Storage Temperature		-20 to 70°C (-4 to	158°F)			
Relative Humidity	5 to 90% (non-condensing)					
Environmental Air	No corrosive gases permitted					
Vibration		ML STD 810C	514.2			
Shock		ML STD 810C	516.2			
Noise Immunity		NEMA ICS3-	304			

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

	FC Series Terminal Blocks					
FC Series Model	Terminal Block Replacement Part Number	Package Includes				
FC-11						
FC-33	EO EMM	(2) 2-pole blocks				
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks				
FC-T1		()				
FC-ISO-C						
FC-ISO-D		(6) 2-pole blocks				
FC-B34		(2) 3-pole blocks				
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks				
FC-P3		(1) 6-pole blocks				
FC-3RLY2		(2) 8-pole blocks				
FC-3RLY4						

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners						
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price		
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00		
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00		

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Input Ranges	Switch Position							
input rianges	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges			
	CU10	-200°C to 260°C	-328°F to 500°F	
	PT100	-200°C to 850°C	-328°F to 1562°F	
	PT1000	-200°C to 595°C	-328°F to 1103°F	
RTD Excitation Current	CU10 & PT100	500μA :	± 50μA	
TITO EXCITATION GUITGIN	PT1000	80μA ±	: 20μΑ	
Common Mode Range	0-3.5 VDC			
Maximum Inggayyayı	CU10	0.35%	FS0	
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C		
(moradoo onoot, opan, Emourty)	PT100 & PT1000 0.26% FS0			
Maximum Loop Supply	30VDC			
Load Impedance	0Ω Minimum			
Maximum Load	12V Power Supply	203Ω		
maximum Luau	24V Power Supply	745Ω		
Linearity Error	CU10	0.35% FS0		
Lilicality Lilui	PT100 & PT1000	0.2%FS0 Maximum		
Output Slew Rate	1% @ 20mS			
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz			
Stability	0.05% FSO Maximum			

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No.
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.				

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost
Note: Identify parts p	provided by this Contr	act with two asterisks.		

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025




Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3221A	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-004, 90-E-306
002	1	C35CS3221A	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-004, 90-E-306
003	1	C35CS3221A	Subpanel	Saginaw Control & SCE-12P10		Section 26 05 04	09-I-004, 90-E-306
004	1	C35CS3221A	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-004, 90-E-306
005	1	C35CS3221A	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-004, 90-E-306
006	1	C35CS3221A	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-004, 90-E-306
007	1	C35CS3221A	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-004, 90-E-306
008	1	C35CS3221A	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
009	3	C35CS3221A	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							

THIS PAGE LEFT BLANK







Н				JOPTIMAL CONTROL SYSTEMS 🗚
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
Ε				PHONE (541) 967-9323 FAX (541) 967-9485
D				CLIENT MCCLURE & SIINS (MA)
С	2024.3.11	TERMINAL BLOCKS	HAD	COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCEI	
Α	2023.10.25.	Original Draft		DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	INII	CHECKED DATE DWG NO. 0723-08MSI-S2WP1-322
		REVISIONS		APPROVED SCALE SCALE SCALE SHEET 1 OF 1

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

THIS PAGE LEFT BLANK

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK



Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.

Industry Standards - (IS17) NEMA Not Applicable


- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

THIS PAGE LEFT BLANK

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)

Keps Nut (x2)


- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL



THIS PAGE LEFT BLANK





SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs



Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

THIS PAGE LEFT BLANK



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E3	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass ① Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34V2	E34P2	
Green	E34V3	E34P3	
Yellow	E34V4	E34P4	
White	E34V5	E34P5	
Blue	E34V6	E34P6	
Ambler	E34V9	E34P9	
Clear	E34V0	E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number 0hms 2 Watt (60V Max.) Single Potentiometer with Standard Aluminum Dial Plate 40 E34PDB1F1 2500 E34PDB1F2 5000 E34PDB1F5 10000 E34PDB1F10 25000 E34PDB1F25 50000 E34PDB1F50 E34PDB1A0 Operator only 6 Alternative—black plastic large legend with standard markings E34LP99 Dimensions, see Page V7-T1-322.

. .

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote
 below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

Standard LED Lamp

24V

LED Selection

Blue

White

E22LED048BN

E22LED048WN

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED060ON
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN	 ;	Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED0480N			
	Yellow	E22LED048YN			
	Green	E22LED048GN			

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
		Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ³	Red Lever Catalog Number ^③
X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
U	Х	IVI VIVI	1N0						

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)		Non-Illuminated		Illuminated—120V Transformer				
			Operator Action ^②	Contact Type	Mounting A	J Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		→ •					
Χ	0	0		1N0	\bot		3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			0 0						
0	0	X		2NC (Series)	-مىن	صىه					
				1N0		→					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Opera	ator Po	osition	(1)						Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ^②	Contact Type	Mounting A	Location B	Gaill	Black Knob Catalog Number ^③	Black Lever Catalog Number [®]	Red Knob Catalog Number ^③	Red Lever Catalog Number [®]
Ì	X O	0 X	0	0	мм	1NC	مله		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
,	0 0		Χ	0 X	M M	1N0	~ ~						
						1N0							
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter
Black	1	White	5
Red	2	Blue	6
Green	3	Gray	7
Yellow	4	Orange	8

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Code #3		
No.	"X-0" Pattern		1	Top A	Bottom B	Top A	Bottom B	
1	Х	0	0	- -	D 0.10-	-0 -0-	_	
				NO	NC	NO		
4	0	0	Х	_	-0 -0-	_	-0 0-	
					NO		NO	

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

Wired in series.

Three-Position Switch—Cam and Contact Block Selection

					ocks Required to Acc nust be installed whe		Function
	Desired C	Circuit and		Operator w	ith Cam Code #2	Operator w	ith Cam Code #3
	Operator	Position		Mounting I	Location	Mounting I	Location
No.				Top Plunger A	Bottom Plunger B	Top Plunger A	Bottom Plunger B
1	Х	0	0		OL_O NC	_ 	
2	Х	Х	0		NC		—O_LO— NC
3	X	0	X	 NO		TO 0-	NO NO
4	0	0	Х		 NO		 NO
5	0	Х	Х	TO LO	NO NO	NC	
6	0	Х	0	— <u>0_1_0</u> NC		NC	NC

Four-Position Switch—Contact Block Selection

		ed Circuit tor Positi		<i>(</i> ?h)	Contact B Required t Accomplis Function Mounting Top Plunger	co sh Circuit Location Bottom Plunger			ed Circui tor Posit		<i>(</i> ?h)	Contact B Required t Accomplis Function Mounting Top Plunger	to sh Circuit Location Bottom Plunger
No.	All	- All			A	В	No.	A)	A)			A	В
1	Х	0	0	0	− <u>o </u>		10	Χ	0	Χ	0		
2	0	Х	0	0		 N0						NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0		-0 -0
4	0	0	0	Χ		—Q⊥O— NC	_					NC NO	NO
5	Х	0	0	Х	TO LO	NC NC	12	0	Х	Х	Х	70-0-	<u> </u>
6	0	Х	Х	0	TO O	NO NO	_					NO	NC NO
7	0	0	Х	Х	 NO	NC NC	13	Х	0	Х	Х	To -0	010
8	X	Х	0	0	TO LO	NO NO	_					NO NC	NC
9	0	X	0	X		To old	14	Х	Х	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountir	
Positions	Action ①	Cam Code ^③	Catalog Number ®
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M .	2	E34VJB <u>K1</u>
	S M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ^③		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A 4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	К8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
Δ Ι Ω Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Func	tion Blocl	ks ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	_	10250T71E ^③	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3®	_	10250T47E ^③	_
7 0 0 0	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 ³⁴	_	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	_	10250T45E ③	_
<u>a L o</u>	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ^③	_
Special Purpo	se Block	S ⁽⁵⁾				
0 0 0 0	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®			

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- @ Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

	Description	Req.	Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification					
Insulation	U _i = 660 Vac or Vdc					
Thermal	$I_{th} = 10A$					
Short Circuit Coordination to IEC/EN 609	47-5-1					
Rated conditional short circuit current	1 kA					
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1					
UL rating	A600, P600					
AC load life duty cycle 1200 operations/hour						
10A	110V pf 0.4—1 x 10 ⁶ operations					
5A	250V pf 0.4—1 x 10 ⁶ operations					
2A	600V pf 0.4—1 x 10 ⁶ operations					
Switching capacity						
AC 15 rated make/break (11 x I _e at 1.1 x U _e)						
6A	120V pf 0.3					
4A	240V pf 0.3					
2A	660V pf 0.3					
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)						
1.0A	125V L/R ≥0.95 at 300 ms					
0.55A	250V L/R ≥0.95 at 300 ms					
0.1A	660V L/R ≥0.95 at 300 ms					
10A	110V pure resistive					
Maximum ratings for logic level and hostile atmosphere application						
Maximum amperes	0.5A					
Maximum volts	120 Vac/Vdc					
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.					
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.					

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc				
Description	120	240	480	600	24/28	125	250		
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC									
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55		
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55		
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0		
Voltamperes:									
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138		
Normal load break	720	720	720	720	138	138	138		

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)						
Plate	A	В	C	D			
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)			
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)			
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)			

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications

FDA 3-A UL Listed

CE Marked CSA Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors


Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty
0.3 lb 1 year

Compliances

CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats.

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications						
	CU10	CU10 -200°C to 260°C -328°F to 500°				
Input Ranges	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current		CU10, PT100 500 μ PT1000 80 μΑ:				
Common Mode Range		0 - 3.5 VD	С			
Output Range		4-20 mA (linea	rized)			
Maximum Inaccuracy		0.35% FSO / 0 0.2% FSO @ 25°C / PT 0.26% FSO @ 60°C / PT	100 & PT1000			
Maximum Loop Supply		30VDC				
Load Impedance		0Ω minimu	m			
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V					
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000					
Output Slew Rate	1% @ 20 mS					
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz					
Stability		0.05% FSO ma	ximum			
Operating Temperature		0 to 60°C (32 to	140°F)			
Storage Temperature		-20 to 70°C (-4 to	158°F)			
Relative Humidity	5 to 90% (non-condensing)					
Environmental Air	No corrosive gases permitted					
Vibration		ML STD 810C	514.2			
Shock	ML STD 810C 516.2					
Noise Immunity		NEMA ICS3-	304			

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

FC Series Terminal Blocks					
FC Series Model	Terminal Block Replacement Part Number	Package Includes			
FC-11					
FC-33	EO EMM	(2) 2-pole blocks			
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks			
FC-T1		(1) 1 polo blooko			
FC-ISO-C					
FC-ISO-D		(6) 2-pole blocks			
FC-B34		(2) 3-pole blocks			
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks			
FC-P3		(1) 6-pole blocks			
FC-3RLY2		(2) 8-pole blocks			
FC-3RLY4					

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners					
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price	
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00	
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00	

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Innut Ranges				Switch I	Position	ı		
Input Ranges	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges				
	CU10	-200°C to 260°C	-328°F to 500°F		
	PT100	-200°C to 850°C	-328°F to 1562°F		
	PT1000	-200°C to 595°C	-328°F to 1103°F		
RTD Excitation Current	CU10 & PT100	500μA ± 50μA			
TITO EXCITATION GUITGIN	PT1000	80μA ±	: 20μΑ		
Common Mode Range	0-3.5 VDC				
Maximum Inggayyayı	CU10	0.35% FSO			
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C			
(monutes onset, span, Linearity)	PT100 & PT1000 0.26% FS0				
Maximum Loop Supply	30VDC				
Load Impedance	0Ω Minimum				
Maximum Load	12V Power Supply	203Ω			
maximum Luau	24V Power Supply	745Ω			
Linearity Error	CU10	0.35% FS0			
Lilicality Lilui	PT100 & PT1000	0.2%FSO Maximum			
Output Slew Rate	1% @ 20mS				
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz				
Stability	0.05% FSO Maximum				

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No.
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal		
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.						

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost
Note: Identify parts p	provided by this Contr	act with two asterisks.		

Bill of Materials


Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025




Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C35CS3222A	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-004, 90-E-306
002	1	C35CS3222A	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-004, 90-E-306
003	1	C35CS3222A	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-004, 90-E-306
004	1	C35CS3222A	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-004, 90-E-306
005	1	C35CS3222A	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-004, 90-E-306
006	1	C35CS3222A	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-004, 90-E-306
007	1	C35CS3222A	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-004, 90-E-306
008	1	C35CS3222A	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
009	3	C35CS3222A	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-306
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							









Н				OPTIMAL CONTROL SYSTEMS
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
Ε				PHONE (541) 967-9323 FAX (541) 967-9485
D				CLIENT MCCLURE & SONS
С	2024.3.11	TERMINAL BLOCKS	HAD	TITLE COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCEI	
A	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	INIT	ME 2022 10 25 MO 1722_00MST_52\/D222222
,		REVISIONS	•	APPROVED SCALE NUME SHEET 1 OF 1





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS





Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.


Industry Standards - (IS17) NEMA Not Applicable

- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)


Keps Nut (x2)

- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL







Your Enclosure Source ®



SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs

Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

30.5 mm Corrosion Resistant Watertight/Oiltight—E34



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V 5 E34P 5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal One-Hole Mounting ³

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number				
2 Watt (60V Max.) Single Potentiometer with Standard Aluminum Dial Plate 👀				
E34PDB1F1				
E34PDB1F2				
E34PDB1F5				
E34PDB1F10				
E34PDB1F25				
E34PDB1F50				
E34PDB1A0				
E34LP99				

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote
 below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator Position ①							Non-Illuminated		Illuminated—120V Transformer	
			Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ³	Black Lever Catalog Number ³	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
	X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
	U	Х	IVI VIVI	1N0						

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)					Non-Illuminated		Illuminated—120V Transformer	
			Operator Action ^②	Contact Type	Mounting A	Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		0 0					
Χ	0	0		1N0			3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			0 0						
0	0	X		2NC (Series)	-مىن	—aro					
				1N0		00					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Operator Position ①								Non-Illuminated		Illuminated—120V Transformer		
					Operator Action ②	Contact Type	Mounting A	Location B	Cam Code	Black Knob Catalog Number ®	Black Lever Catalog Number ®	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
Ì	X	0	-	0	м м	1NC	<u>م ا ه</u>		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0 0 0	X 0 0		0 0 X	M	1N0	→						
						1N0		~ ~					
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter	
Black	1	White	5	
Red	2	Blue	6	
Green	3	Gray	7	
Yellow	4	Orange	8	

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0	" Patterr	1	Top A	Bottom B	Top A	Bottom B
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Х	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

① Wired in series.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Three-Position Switch—Cam and Contact Block Selection

					red to Accomplish Circuit talled where indicated)	Function
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Х	0	0	0	–o⊥o– NC		10	Χ	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0	TO 0	
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	Χ	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X	N0	NC NC	13	X	0	Х	X	To o	010
8	Χ	Х	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	X	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Selector Switch— Vertical Mounting ②			
Positions	Action ①	Cam Code ③	Catalog Number [®]		
Two-position—60° throw	M M	1	E34VFB <u>K1</u>		
	M	1	E34VEB <u>K1</u>		
Three-position—60° throw	M	2	E34VGB <u>K1</u>		
	$M \longrightarrow M$	3	E34VHB <u>K1</u>		
	M _	2	E34VJB <u>K1</u>		
	S M	3	E34VKB <u>K1</u>		
	y M ⋅	2	E34VLB <u>K1</u>		
	SS	3	E34VMB <u>K1</u>		
	M 👡	2	E34VNB <u>K1</u>		
	MS	3	E34VPB <u>K1</u>		
Four-position—40° throw	M M	7	E34VTB <u>K1</u>		
	MM				

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ³		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Technical Data and Specifications

Mechanical Ratings

Description	Specification		
Frequency of Operation			
All pushbuttons	6000 operations/hr.		
Key and lever selector switches	3000 operations/hr.		
Auto-latch devices	1200 operations/hr.		
Life			
Pushbuttons	10 x 10 ⁶ operations		
Contact blocks	10 x 10 ⁶ operations		
PresTest units	10 x 10 ⁶ operations		
Lever and key selector switches	0.25 x 10 ⁶ operations		
Twist to release pushbuttons	0.3 x 10 ⁶ operations		
Shock Resistance			
Duration	210 ms ≥5g		

General Specifications

Description	Specification				
Climate Conditions					
Operating temperature	1° to 150°F (-17° to 66°C)				
Storage temperature	-40° to 176°F (−40° to 80°C)				
Altitude	6,562 ft (2,000m)				
Humidity	Max. 95% RH at 60°C				
Terminals					
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).				
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors				
Torque	7 lb-in (0.8 Nm)				
Degree of protection against direct electrical contact	IP2X with fingerproof shroud				
Light Units					
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1				
Bulbs—average life:					
Transformer type	20,000 hrs.				
Resistor/direct voltage type	2500 hrs. minimum at rated V				
LED	60,000 to 100,000 hrs.				

Electrical Ratings

Description	Specification				
Insulation	U _i = 660 Vac or Vdc				
Thermal	$I_{th} = 10A$				
Short Circuit Coordination to IEC/EN 609	47-5-1				
Rated conditional short circuit current	1 kA				
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1				
UL rating	A600, P600				
AC load life duty cycle 1200 operations/hour					
10A	110V pf 0.4—1 x 10 ⁶ operations				
5A	250V pf 0.4—1 x 10 ⁶ operations				
2A	600V pf 0.4—1 x 10 ⁶ operations				
Switching capacity					
AC 15 rated make/break (11 x I _e at 1.1 x U _e)					
6A	120V pf 0.3				
4A	240V pf 0.3				
2A	660V pf 0.3				
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)					
1.0A	125V L/R ≥0.95 at 300 ms				
0.55A	250V L/R ≥0.95 at 300 ms				
0.1A	660V L/R ≥0.95 at 300 ms				
10A	110V pure resistive				
Maximum ratings for logic level and hostile atmosphere application					
Maximum amperes	0.5A				
Maximum volts	120 Vac/Vdc				
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.				
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.				

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600,	A300 and B300 f	or AC and	P600 for DC	;			
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)							
Plate	A	В	C	D				
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)				
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)				
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)				

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications
FDA 3-A UL Listed
CE Marked CSA Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty 0.3 lb 1 year

Compliances
CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats. THIS PAGE LEFT BLANK

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications							
	CU10	-200°C to 260°C	-328°F to 500°F				
Input Ranges	PT100	-328°F to 1562°F					
	PT1000	-200°C to 595°C	-328°F to 1103°F				
RTD Excitation Current	CU10, РТ100 500 µA ±50 µA РТ1000 80 µA ±20 µA						
Common Mode Range		0 - 3.5 VD	С				
Output Range		4-20 mA (linea	rized)				
Maximum Inaccuracy	0.35% FSO / CU10 0.2% FSO @ 25°C / PT100 & PT1000 0.26% FSO @ 60°C / PT100 & PT1000						
Maximum Loop Supply	30VDC						
Load Impedance	0Ω minimum						
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V						
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000						
Output Slew Rate	1% @ 20 mS						
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz						
Stability		0.05% FSO ma	ximum				
Operating Temperature		0 to 60°C (32 to	140°F)				
Storage Temperature		-20 to 70°C (-4 to	158°F)				
Relative Humidity	5 to 90% (non-condensing)						
Environmental Air	No corrosive gases permitted						
Vibration		ML STD 810C	514.2				
Shock	ML STD 810C 516.2						
Noise Immunity		NEMA ICS3-	304				

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

	FC Series Terminal Blocks							
FC Series Model	Terminal Block Replacement Part Number	Package Includes						
FC-11								
FC-33	EO EMM	(2) 2-pole blocks						
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks						
FC-T1		(1) 1 polo blooks						
FC-ISO-C								
FC-ISO-D		(6) 2-pole blocks						
FC-B34		(2) 3-pole blocks						
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks						
FC-P3		(1) 6-pole blocks						
FC-3RLY2		(2) 8-pole blocks						
FC-3RLY4								

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners									
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price					
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00					
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00					

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Input Ranges		Switch Position						
IIIµut naliyes	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges					
	CU10	-200°C to 260°C	-328°F to 500°F			
	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current	CU10 & PT100	500μA :	± 50μA			
TITO EXCITATION GUITGIN	PT1000	80μA ± 20μA				
Common Mode Range	0-3.5 VDC					
Maximum Inggayyayı	CU10	0.35% FS0				
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C				
(moradoo onoot, opan, Emourty)	PT100 & PT1000 0.26% FS0					
Maximum Loop Supply	30VDC					
Load Impedance	0Ω Minimum					
Maximum Load	12V Power Supply	203Ω				
maximum Luau	24V Power Supply	745Ω				
Linearity Error	CU10	0.35% FSO				
Lilicality Lilui	PT100 & PT1000	0.2%FSO Maximum				
Output Slew Rate	1% @ 20mS					
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz					
Stability	0.05% FSO Maximum					

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	EQPT SERIAL NO:				
EQPT TAG NO:	EQPT/SYSTEM:				
PROJECT NO:	SPEC. SECTION:				
I hereby certify that the above-referenced ed	quipment/system has been:				
(Check Applicable)					
☐ Installed in accordance with Manufa	acturer's recommendations.				
☐ Inspected, checked, and adjusted.					
Serviced with proper initial lubrican	ts.				
☐ Electrical and mechanical connection	ns meet quality and safety standards.				
☐ All applicable safety equipment has	been properly installed.				
☐ Functional tests.					
System has been performance tested requirements. (When complete system of	I, and meets or exceeds specified performance of one manufacturer)				
Note: Attach any performance test docu	mentation from manufacturer.				
Comments:					
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to ent and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all				
Date:	, 20				
Manufacturer:					
By Manufacturer's Authorized Representati					
	(Authorized Signature)				

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:		
1. EQUIPME	NT ITEM			
2. MANUFA	CTURER			
3. EQUIPME	NT/TAG NUMBER(S)			
4. WEIGHT OF INDIVIDUAL COMPONENTS (OVER 100 POUNDS)				
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _			
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE		
a.	Name_	Telephone No		
	Address	-		

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal	
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.					

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost			
Note: Identify parts provided by this Contract with two asterisks.							

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025




Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C40CS0201A	PB Enclosure, SS Type 316/316L, NEMA 4X 5.75" H x 3.25" W x 2.75" D	Saginaw Control & Engineering	SCE-2PBSS6	Section 26 05 04	09-I-005, 90-E-305
002	1	C40CS0201A	Selector Switch, 2-Position, Black Lever, 1NC/1NO	Eaton	E34VFBL1-1X	Section 26 05 04	09-I-005, 90-E-305
003	1	C40CS0201A	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-005, 90-E-305
004	1	C40CS0201A	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
005	2	C40CS0201A	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
006							
007							
008							
009							
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							

THIS PAGE LEFT BLANK








Н				OPTIMAL CONTROL SYSTEMS
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321 '
Ε				PHONE (541) 967-9323 FAX (541) 967-9485
D				CUENT MCCLURE & SONS
С				COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCEI	
Α	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	INIT	CHECKED DATE DWG NO. 0723-08MSI-SHM-0201A
_		REVISIONS		APPROVED HAD SCALE NONE SHEET 1 OF 1

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-2PBSS6



Product Specifications:

Part Number: SCE-2PBSS6 Description: S.S. PB Enclosure Height: 5.75" Width: 3.25" Depth: 2.75" Price Code: S1 List Price: \$242.12 Catalog Page: 252 Est. Ship Weight: 2.92 lbs

Construction

- 0.063 In. stainless steel Type 316/316L.
 Seams continuously welded and ground smooth.
- Captivated cover screws thread into sealed wells.
- 4-way standard pushbutton holes accept all brands of oil-tight pushbuttons, switches and pilot lights. Hole diameter is 1.20 In. (30.5mm).
- Immediate removal of cover is permitted.
- Pour in place oil & water resistant gasket
- Welded mounting provision top and bottom of back.

Application

Designed to house standard pushbuttons, switches and pilot lights in wet and hosed down areas and in corrosive atmospheres.

Finish

#4 brushed finish on all exterior surfaces.

Industry Standards - (IS5)

- NEMA Type 4, 4X, 12 and Type 13UL Listed Type 4, 4X and 12
- CSA Type 4, 4X and 12
- **□** IEC 60529
- IP 66

Optional Accessories

SCE-ASPB-SS Plug, Hole

Similar Part Numbers

SCE-12PBSS6S.S. PB Enclosure SCE-1PBSS6S.S. PB Enclosure SCE-1PBXSS6S.S. PBX Enclosure SCE-2PBXSS6S.S. PBX Enclosure SCE-3PBSS6S.S. PB Enclosure SCE-3PBXSS6S.S. PBX Enclosure SCE-4PBSS6S.S. PB Enclosure SCE-4PBXSS6S.S. PBX Enclosure SCE-4SPBSS6S.S. PB Enclosure SCE-6PBSS6S.S. PB Enclosure

Installation Information

Pushbutton Enclosures

THIS PAGE LEFT BLANK

PUSHBUTTON ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK

30.5 mm Corrosion Resistant Watertight/Oiltight—E34



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V5 E34P5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN	Yellow	Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



	Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
(Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
,	X	0	M /M	1NC	ملہ	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
	0	X	IVI VIVI	1N0	-					

Three-Position Maint.

Three-Position Selector Switch



Operator Position ①								Non-Illuminated		Illuminated—120V Transformer		
			Operator Action ^②	Contact Type	Mounting A	Location B	Cam Code	Black Knob	Black Lever Catalog Number [®]	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③	
X 0	0	0 X	M	1N0	 		3	E34VHBK <u>1</u> -2X	E34VHBL <u>1</u> -2X	E34VHB120TER-2X	E34VHB120TFR-2X	
			_	1N0		 						
Χ	0	0		1N0			3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X	
0	Χ	0			○							
0	0	Χ		2NC (Series)	-مىه	—aro						
				1N0		 						

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Opera	ator Po	osition	1					Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number [®]	Black Lever Catalog Number [®]	Red Knob	Red Lever Catalog Number ^③
Ì	Χ	0	0	0	M M	1NC	ملہ	7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0	Χ	0	0	_\/_							
,	0	0	Χ	0	M	1NO	1					
	0	0	0	Χ			0 0					
						1N0	0 0					
						1NC	ملہ					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter
Black	1	White	5
Red	2	Blue	6
Green	3	Gray	7
Yellow	4	Orange	8

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0	" Patterr	1	Top A	Bottom B	Top A	Bottom B
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Х	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function		
No.	D		Top Plunger A	Bottom Plunger B	
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC	
2	0	Х	or NO	 	

Note

① Wired in series.

Three-Position Switch—Cam and Contact Block Selection

					red to Accomplish Circuit talled where indicated)	Function
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact Bl Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Х	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Χ	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0	TO 0	
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	Χ	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X		NC NC	13	X	0	Х	X	TO 0	010
8	Χ	Х	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	Х	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountin	
Positions	Action ①	Cam Code ③	Catalog Number [®]
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M _	2	E34VJB <u>K1</u>
	s M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M 👡	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>
	MM		

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection [®]	
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number
Black	K1	E34K1	L1	E34L1	A 1	E34A1
Red	K2	E34K2	L2	E34L2	A2	E34A2
Green	К3	E34K3	L3	E34L3	А3	E34A3
Yellow	K4	E34K4	L4	E34L4	A4	E34A4
White	K5	E34K5	L5	E34L5	A5	E34A5
Blue	К6	E34K6	L6	E34L6	A6	E34A6
Gray	К7	E34K7	L7	E34L7	A7	E34A7
Orange	K8	E34K8	L8	E34L8	A8	E34A8

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5		53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification
Insulation	U _i = 660 Vac or Vdc
Thermal	$I_{th} = 10A$
Short Circuit Coordination to IEC/EN 609	47-5-1
Rated conditional short circuit current	1 kA
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1
UL rating	A600, P600
AC load life duty cycle 1200 operations/hour	
10A	110V pf 0.4—1 x 10 ⁶ operations
5A	250V pf 0.4—1 x 10 ⁶ operations
2A	600V pf 0.4—1 x 10 ⁶ operations
Switching capacity	
AC 15 rated make/break (11 x I _e at 1.1 x U _e)	
6A	120V pf 0.3
4A	240V pf 0.3
2A	660V pf 0.3
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)	
1.0A	125V L/R ≥0.95 at 300 ms
0.55A	250V L/R ≥0.95 at 300 ms
0.1A	660V L/R ≥0.95 at 300 ms
10A	110V pure resistive
Maximum ratings for logic level and hostile atmosphere application	
Maximum amperes	0.5A
Maximum volts	120 Vac/Vdc
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC							
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)					
Plate	Α	В	C	D		
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)		
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)		
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)		

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



THIS PAGE LEFT BLANK

Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications FDA 3-A **UL** Listed **CE Marked CSA Certified**

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.








Eaton E34VFBL1-1X

Catalog Number: E34VFBL1-1X

Eaton E34 pushbutton, Assembled Selector Switch, E34, 30.5 mm, Corrosion Resistant, Cam 1, 60° throw, NEMA 3, 3R, 4, 4X, 12, 13, Non-illuminated, Two-position, Knob, Black actuator, 1NO-1NC.





Product Name

Eaton E34 pushbutton

UPC

782113891637

Product Height

1 in

Product Weight

1 lb

Compliances

CE Marked FDA 3-A

Catalog Notes

Assembled at Factory

Catalog Number

E34VFBL1-1X

Product Length/Depth

1 in

Product Width

1 in

Warranty

1 year

Certifications

CSA Certified

UL Listed



Product specifications

Contact configuration

1 NO-1 NC

Throw type

60°

Series

E34

Number of positions

Type

30.5 mm, Corrosion Resistant

Actuator color

Black

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Illumination

Non-illuminated

Cam code

Cam 1

Actuator

Knob

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34VFBL1-1X

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	EQPT SERIAL NO:			
EQPT TAG NO:	EQPT/SYSTEM:			
PROJECT NO:	SPEC. SECTION:			
I hereby certify that the above-referenced ed	quipment/system has been:			
(Check Applicable)				
☐ Installed in accordance with Manufa	acturer's recommendations.			
☐ Inspected, checked, and adjusted.				
Serviced with proper initial lubrican	ts.			
☐ Electrical and mechanical connection	ns meet quality and safety standards.			
☐ All applicable safety equipment has	been properly installed.			
☐ Functional tests.				
System has been performance tested requirements. (When complete system of	I, and meets or exceeds specified performance of one manufacturer)			
Note: Attach any performance test docu	mentation from manufacturer.			
Comments:				
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to ent and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all			
Date:	, 20			
Manufacturer:				
By Manufacturer's Authorized Representati				
	(Authorized Signature)			

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivale specific use r			by each manu	facturer for the

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost
Note: Identify parts p	provided by this Contr	act with two asterisks.		

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025




Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C40CS0401A	PB Enclosure, SS Type 316/316L, NEMA 4X 5.75" H x 3.25" W x 2.75" D	Saginaw Control & Engineering	SCE-2PBSS6	Section 26 05 04	09-I-005, 90-E-305
002	1	C40CS0401A	Selector Switch, 2-Position, Black Lever, 1NC/1NO	Eaton	E34VFBL1-1X	Section 26 05 04	09-I-005, 90-E-305
003	1	C40CS0401A	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-005, 90-E-305
004	1	C40CS0401A	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
005	2	C40CS0401A	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
006							
007							
008							
009							
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							

THIS PAGE LEFT BLANK








Н				OPTIMAL CONTROL SYSTEMS
G				2324 THREE LAKES RD / PO BOX 462
F				ALBANY, OR 97321
Ε				PHONE (541) 967-9323 FAX (541) 967-9485
D				CLENT MCCLURE & SONS
С	2024.3.12	BISULFITE	HAD	COOS BAY WASTE WATER TREATMENT PLANT
В	2024.02.27.	CORRECTED	KCEI	C40M0401 SODIUM BISULFITE MIXER
A	2023.10.25.	Original Draft	KCD	DRAWN KCD ISSUED JOB NO. 0723-08MSI
REV	DATE	DESCRIPTION	INIT	CHECKED DATE DWG NO.
		REVISIONS		APPROVED SCALE NONE SHEET 1 OF 1

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-2PBSS6



Product Specifications:

Part Number: SCE-2PBSS6 Description: S.S. PB Enclosure Height: 5.75" Width: 3.25" Depth: 2.75" Price Code: S1 List Price: \$242.12 Catalog Page: 252 Est. Ship Weight: 2.92 lbs

Construction

- 0.063 In. stainless steel Type 316/316L.
 Seams continuously welded and ground smooth.
- Captivated cover screws thread into sealed wells.
- 4-way standard pushbutton holes accept all brands of oil-tight pushbuttons, switches and pilot lights. Hole diameter is 1.20 In. (30.5mm).
- Immediate removal of cover is permitted.
- Pour in place oil & water resistant gasket
- Welded mounting provision top and bottom of back.

Application

Designed to house standard pushbuttons, switches and pilot lights in wet and hosed down areas and in corrosive atmospheres.

Finish

#4 brushed finish on all exterior surfaces.

Industry Standards - (IS5)

- NEMA Type 4, 4X, 12 and Type 13UL Listed Type 4, 4X and 12
- CSA Type 4, 4X and 12
- **□** IEC 60529
- IP 66

Optional Accessories

SCE-ASPB-SS Plug, Hole

Similar Part Numbers

SCE-12PBSS6S.S. PB Enclosure SCE-1PBSS6S.S. PB Enclosure SCE-1PBXSS6S.S. PBX Enclosure SCE-2PBXSS6S.S. PBX Enclosure SCE-3PBSS6S.S. PB Enclosure SCE-3PBXSS6S.S. PBX Enclosure SCE-4PBSS6S.S. PB Enclosure SCE-4PBXSS6S.S. PBX Enclosure SCE-4SPBSS6S.S. PB Enclosure SCE-6PBSS6S.S. PB Enclosure

Installation Information

Pushbutton Enclosures

THIS PAGE LEFT BLANK

PUSHBUTTON ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V5 E34P5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



	Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
(Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
,	X	0	M /M	1NC	ملہ	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
	0	X	IVI VIVI	1N0	-					

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	ition 1)					Non-Illuminated		Illuminated—120V T	ransformer
			Operator Action ^②	Contact Type	Mounting A	Location B	Cam Code	Black Knob	Black Lever Catalog Number [®]	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0	0 X	M	1N0	 		3	E34VHBK <u>1</u> -2X	E34VHBL <u>1</u> -2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		 					
Χ	0	0		1N0			3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			○						
0	0	X		2NC (Series)	-مىه	—aro					
				1N0		 					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Opera	ator Po	osition	1					Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number [®]	Black Lever Catalog Number [®]	Red Knob	Red Lever Catalog Number ^③
Ì	Χ	0	0	0	M M	1NC	ملہ	7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0	Χ	0	0	_\/_							
,	0	0	Χ	0	M	1N0	1					
	0	0	0	Χ			0 0					
						1N0	0 0					
						1NC	ملہ					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter
Black	1	White	5
Red	2	Blue	6
Green	3	Gray	7
Yellow	4	Orange	8

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Code #3		
No.	"X-0" Pattern		1	Top A	Bottom B	Top A	Bottom B	
1	Х	0	0	- -	D 0.10-	-0 -0-	_	
				NO	NC	NO		
4	0	0	Х	_	-0 -0-	_	-0 0-	
					NO		NO	

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

① Wired in series.

Three-Position Switch—Cam and Contact Block Selection

					red to Accomplish Circuit talled where indicated)	Function
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact B Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Х	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Χ	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	Х	Х	Х	0		
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	Χ	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X	N0	NC NC	13	X	0	Х	X	TO 0	010
8	Χ	Х	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	Х	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountir	
Positions	Action ①	Cam Code ③	Catalog Number [®]
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M _	2	E34VJB <u>K1</u>
	s M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M 👡	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>
	MM		

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ³		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize \textcircled{\tiny 1}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- © Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number	
12	Mounting screw	2	11-1632	
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below	
	1,000 ohms	_	41-782-2	
	2,500 ohms	_	41-782-3	
	5,000 ohms	_	41-782-10	
	10,000 ohms	_	41-782-4	
	25,000 ohms	_	41-782-5	
	50,000 ohms	_	41-782-6	
14	Connector (includes screw and lug)	2	25-1851	
15	Indicating plate	1	As Req. Above	
	Standard size (without legend)	_	30-4460	
	Large size (specify legend)	_	10250TR30	
16	Retaining nut	1	15-1547-3	
17	Knob	1	53-1314	
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014	
18	Coupling	1	11-2014	
			29-3749-2	
19	Set screw (#6-32 x 0.188 in long)	1	11-1199	
20	Spacer	2	56-1066-18	
21	Connector (includes screw and lug)	1	25-1851-2	
22	Mounting nut	1	15-1938-2	

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification
Insulation	U _i = 660 Vac or Vdc
Thermal	$I_{th} = 10A$
Short Circuit Coordination to IEC/EN 609	47-5-1
Rated conditional short circuit current	1 kA
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1
UL rating	A600, P600
AC load life duty cycle 1200 operations/hour	
10A	110V pf 0.4—1 x 10 ⁶ operations
5A	250V pf 0.4—1 x 10 ⁶ operations
2A	600V pf 0.4—1 x 10 ⁶ operations
Switching capacity	
AC 15 rated make/break (11 x I _e at 1.1 x U _e)	
6A	120V pf 0.3
4A	240V pf 0.3
2A	660V pf 0.3
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)	
1.0A	125V L/R ≥0.95 at 300 ms
0.55A	250V L/R ≥0.95 at 300 ms
0.1A	660V L/R ≥0.95 at 300 ms
10A	110V pure resistive
Maximum ratings for logic level and hostile atmosphere application	
Maximum amperes	0.5A
Maximum volts	120 Vac/Vdc
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description		240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC							
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)					
Plate	A	В	C	D		
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)		
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)		
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)		

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



THIS PAGE LEFT BLANK

Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications FDA 3-A **UL** Listed CE Marked **CSA** Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.








Eaton E34VFBL1-1X

Catalog Number: E34VFBL1-1X

Eaton E34 pushbutton, Assembled Selector Switch, E34, 30.5 mm, Corrosion Resistant, Cam 1, 60° throw, NEMA 3, 3R, 4, 4X, 12, 13, Non-illuminated, Two-position, Knob, Black actuator, 1NO-1NC.





Product Name

Eaton E34 pushbutton

UPC

782113891637

Product Height

1 in

Product Weight

1 lb

Compliances

CE Marked FDA 3-A

Catalog Notes

Assembled at Factory

Catalog Number

E34VFBL1-1X

Product Length/Depth

1 in

Product Width

1 in

Warranty

1 year

Certifications

CSA Certified

UL Listed



Product specifications

Contact configuration

1 NO-1 NC

Throw type

60°

Series

E34

Number of positions

Type

30.5 mm, Corrosion Resistant

Actuator color

Black

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Illumination

Non-illuminated

Cam code

Cam 1

Actuator

Knob

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34VFBL1-1X

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	I, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to ent and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal	
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.					

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost	
Note: Identify parts provided by this Contract with two asterisks.					

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025




Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C40CS1001	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-006, 90-E-305
002	1	C40CS1001	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-006, 90-E-305
003	1	C40CS1001	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-006, 90-E-305
004	1	C40CS1001	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-006, 90-E-305
005	1	C40CS1001	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-006, 90-E-305
006	1	C40CS1001	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-006, 90-E-305
007	1	C40CS1001	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-006, 90-E-305
800	1	C40CS1001	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
009	3	C40CS1001	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							

THIS PAGE LEFT BLANK







REVISIONS

THIS PAGE LEFT BLANK





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Construction

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13"

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Product Specifications:

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

THIS PAGE LEFT BLANK

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS



THIS PAGE LEFT BLANK



Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.

Industry Standards - (IS17) NEMA Not Applicable


- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

THIS PAGE LEFT BLANK

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)

Keps Nut (x2)


- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL



THIS PAGE LEFT BLANK





SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs



Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

THIS PAGE LEFT BLANK



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E3	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass ① Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34V2	E34P2	
Green	E34V3	E34P3	
Yellow	E34V4	E34P4	
White	E34V5	E34P5	
Blue	E34V6	E34P6	
Ambler	E34V9	E34P9	
Clear	E34V0	E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number 0hms 2 Watt (60V Max.) Single Potentiometer with Standard Aluminum Dial Plate 40 E34PDB1F1 2500 E34PDB1F2 5000 E34PDB1F5 10000 E34PDB1F10 25000 E34PDB1F25 50000 E34PDB1F50 E34PDB1A0 Operator only 6 Alternative—black plastic large legend with standard markings E34LP99 Dimensions, see Page V7-T1-322.

. .

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote
 below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

Standard LED Lamp

24V

LED Selection

Blue

White

E22LED048BN

E22LED048WN

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED060ON
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN	 ;	Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED0480N			
	Yellow	E22LED048YN			
	Green	E22LED048GN			

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator F	Position ①					Non-Illuminated		Illuminated—120V	Transformer
		Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ³	Red Lever Catalog Number ^③
X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
U	Х	IVI VIVI	1N0						

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)		Non-Illuminated		Illuminated—120V Transformer				
			Operator Action ^②	Contact Type	Mounting A	J Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		→ •					
Χ	0	0		1N0	\bot		3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			0 0						
0	0	X		2NC (Series)	-مىن	صىه					
				1N0		→					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Opera	ator Po	osition	(1)						Non-Illuminated		Illuminated—120V To	ransformer
					Operator Action ^②	Contact Type	Mounting A	Location B	Gaill	Black Knob Catalog Number ^③	Black Lever Catalog Number [®]	Red Knob Catalog Number ^③	Red Lever Catalog Number [®]
Ì	X O	0 X	0	0	мм	1NC	مله		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
,	0 0		Χ	0 X	M M	1N0	~ ~						
						1N0							
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter
Black	1	White	5
Red	2	Blue	6
Green	3	Gray	7
Yellow	4	Orange	8

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Code #3		
No.	"X-0" Pattern		1	Top A	Bottom B	Top A	Bottom B	
1	Х	0	0	- -	D 0.10-	-0 -0-	_	
				NO	NC	NO		
4	0	0	Х	_	-0 -0-	_	-0 0-	
					NO		NO	

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

Wired in series.

Three-Position Switch—Cam and Contact Block Selection

					ocks Required to Acc nust be installed whe		Function
	Desired C	Circuit and		Operator w	ith Cam Code #2	Operator w	ith Cam Code #3
	Operator	Position		Mounting I	Location	Mounting I	Location
No.				Top Plunger A	Bottom Plunger B	Top Plunger A	Bottom Plunger B
1	Х	0	0		OL_O NC	_ 	
2	Х	Х	0		NC		—O_LO— NC
3	X	0	X	 NO		TO 0-	NO NO
4	0	0	Х		 NO		 NO
5	0	Х	Х	TO LO	NO NO	NC	
6	0	Х	0	— <u>0_1_0</u> NC		NC	NC

Four-Position Switch—Contact Block Selection

		ed Circuit tor Positi		<i>(</i> ?h)	Contact B Required t Accomplis Function Mounting Top Plunger	co sh Circuit Location Bottom Plunger			ed Circui tor Posit		<i>(</i> ?h)	Contact B Required t Accomplis Function Mounting Top Plunger	to sh Circuit Location Bottom Plunger
No.	All	- All			A	В	No.	A)	A)			A	В
1	Х	0	0	0	− <u>o </u>		10	Χ	0	Χ	0		
2	0	Х	0	0		 N0						NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0		-0 -0
4	0	0	0	Χ		—Q⊥O— NC	_					NC NO	NO
5	Х	0	0	Х	TO LO	NC NC	12	0	Х	Х	Х	70-0-	<u> </u>
6	0	Х	Х	0	TO O	NO NO	_					NO	NC NO
7	0	0	Х	Х	 NO	NC NC	13	Х	0	Х	Х	To -0	010
8	X	Х	0	0	TO LO	NO NO	_					NO NC	NC
9	0	X	0	X		To old	14	Х	Х	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Sele Vertical Mountir	
Positions	Action ①	Cam Code ^③	Catalog Number ®
Two-position—60° throw	M M	1	E34VFB <u>K1</u>
	M	1	E34VEB <u>K1</u>
Three-position—60° throw	M	2	E34VGB <u>K1</u>
	$M \longrightarrow M$	3	E34VHB <u>K1</u>
	M .	2	E34VJB <u>K1</u>
	S M	3	E34VKB <u>K1</u>
	y M ⋅	2	E34VLB <u>K1</u>
	SS	3	E34VMB <u>K1</u>
	M	2	E34VNB <u>K1</u>
	MS	3	E34VPB <u>K1</u>
Four-position—40° throw	M M	7	E34VTB <u>K1</u>

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ^③		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A 4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	К8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
Δ Ι Ω Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Func	tion Blocl	ks ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	_	10250T71E ^③	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3®	_	10250T47E ^③	_
7 0 0 0	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 ³⁴	_	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	_	10250T45E ③	_
<u>a L o</u>	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ^③	_
Special Purpo	se Block	S ⁽⁵⁾				
0 0 0 0	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®			

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- @ Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

	Description	Req.	Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

Technical Data and Specifications

Mechanical Ratings

Description	Specification
Frequency of Operation	
All pushbuttons	6000 operations/hr.
Key and lever selector switches	3000 operations/hr.
Auto-latch devices	1200 operations/hr.
Life	
Pushbuttons	10 x 10 ⁶ operations
Contact blocks	10 x 10 ⁶ operations
PresTest units	10 x 10 ⁶ operations
Lever and key selector switches	0.25 x 10 ⁶ operations
Twist to release pushbuttons	0.3 x 10 ⁶ operations
Shock Resistance	
Duration	210 ms ≥5g

General Specifications

Description	Specification
Climate Conditions	
Operating temperature	1° to 150°F (-17° to 66°C)
Storage temperature	-40° to 176°F (−40° to 80°C)
Altitude	6,562 ft (2,000m)
Humidity	Max. 95% RH at 60°C
Terminals	
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors
Torque	7 lb-in (0.8 Nm)
Degree of protection against direct electrical contact	IP2X with fingerproof shroud
Light Units	
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1
Bulbs—average life:	
Transformer type	20,000 hrs.
Resistor/direct voltage type	2500 hrs. minimum at rated V
LED	60,000 to 100,000 hrs.

Electrical Ratings

Description	Specification					
Insulation	U _i = 660 Vac or Vdc					
Thermal	$I_{th} = 10A$					
Short Circuit Coordination to IEC/EN 609	47-5-1					
Rated conditional short circuit current	1 kA					
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1					
UL rating	A600, P600					
AC load life duty cycle 1200 operations/hour						
10A	110V pf 0.4—1 x 10 ⁶ operations					
5A	250V pf 0.4—1 x 10 ⁶ operations					
2A	600V pf 0.4—1 x 10 ⁶ operations					
Switching capacity						
AC 15 rated make/break (11 x I _e at 1.1 x U _e)						
6A	120V pf 0.3					
4A	240V pf 0.3					
2A	660V pf 0.3					
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)						
1.0A	125V L/R ≥0.95 at 300 ms					
0.55A	250V L/R ≥0.95 at 300 ms					
0.1A	660V L/R ≥0.95 at 300 ms					
10A	110V pure resistive					
Maximum ratings for logic level and hostile atmosphere application						
Maximum amperes	0.5A					
Maximum volts	120 Vac/Vdc					
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.					
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.					

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc				
Description	120	240	480	600	24/28	125	250		
Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC									
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55		
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55		
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0		
Voltamperes:									
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138		
Normal load break	720	720	720	720	138	138	138		

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)						
Plate	A	В	C	D			
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)			
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)			
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)			

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications

FDA 3-A UL Listed

CE Marked CSA Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors


Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty
0.3 lb 1 year

Compliances

CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats.

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications						
	CU10	CU10 -200°C to 260°C -328°F to 500°				
Input Ranges	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current		CU10, PT100 500 μ PT1000 80 μΑ:				
Common Mode Range		0 - 3.5 VD	С			
Output Range		4-20 mA (linea	rized)			
Maximum Inaccuracy		0.35% FSO / 0 0.2% FSO @ 25°C / PT 0.26% FSO @ 60°C / PT	100 & PT1000			
Maximum Loop Supply		30VDC				
Load Impedance		0Ω minimu	m			
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V					
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000					
Output Slew Rate	1% @ 20 mS					
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz					
Stability		0.05% FSO ma	ximum			
Operating Temperature		0 to 60°C (32 to	140°F)			
Storage Temperature		-20 to 70°C (-4 to	158°F)			
Relative Humidity	5 to 90% (non-condensing)					
Environmental Air	No corrosive gases permitted					
Vibration		ML STD 810C	514.2			
Shock	ML STD 810C 516.2					
Noise Immunity		NEMA ICS3-	304			

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

FC Series Terminal Blocks					
FC Series Model	Terminal Block Replacement Part Number	Package Includes			
FC-11					
FC-33	EO EMM	(2) 2-pole blocks			
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks			
FC-T1		(1) 1 polo blooks			
FC-ISO-C					
FC-ISO-D		(6) 2-pole blocks			
FC-B34		(2) 3-pole blocks			
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks			
FC-P3		(1) 6-pole blocks			
FC-3RLY2		(2) 8-pole blocks			
FC-3RLY4					

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners					
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price	
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00	
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00	

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Innut Ranges				Switch I	Position	ı		
Input Ranges	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges				
	CU10	-200°C to 260°C	-328°F to 500°F		
	PT100	-200°C to 850°C	-328°F to 1562°F		
	PT1000	-200°C to 595°C	-328°F to 1103°F		
RTD Excitation Current	CU10 & PT100	500μA ± 50μA			
TITO EXCITATION GUITGIN	PT1000	80μA ±	: 20μΑ		
Common Mode Range	0-3.5 VDC				
Maximum Inggayyayı	CU10	0.35% FSO			
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C			
(monutes onset, span, Linearity)	PT100 & PT1000 0.26% FS0				
Maximum Loop Supply	30VDC				
Load Impedance	0Ω Minimum				
Maximum Load	12V Power Supply	203Ω			
maximum Luau	24V Power Supply	745Ω			
Linearity Error	CU10	0.35% FS0			
Lilicality Lilui	PT100 & PT1000	0.2%FSO Maximum			
Output Slew Rate	1% @ 20mS				
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz				
Stability	0.05% FSO Maximum				

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:
1. EQUIPME	NT ITEM	
2. MANUFA	CTURER	
3. EQUIPME	NT/TAG NUMBER(S)	
4. WEIGHT	OF INDIVIDUAL COMPONENTS (O	VER 100 POUNDS)
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _	
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE
a.	Name_	Telephone No.
	Address	-

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal
List symbols used in No. 7 above.	List equivale specific use r			by each manu	facturer for the

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost
Note: Identify parts p	provided by this Contr	act with two asterisks.		

Bill of Materials


Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements


Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods


Date: September 2025



Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C40CS1002	CHNF Enclosure, SS Type 316/316L, NEMA 4X 12.13" H x 10.00" W x 8.00" D	Saginaw Control & Engineering	SCE-12108CHNFSS6	Section 26 05 04	09-I-006, 90-E-305
002	1	C40CS1002	Padlock Kit	Saginaw Control & Engineering	SCE-PLKJIC	Section 26 05 04	09-I-006, 90-E-305
003	1	C40CS1002	Subpanel	Saginaw Control & Engineering	SCE-12P10	Section 26 05 04	09-I-006, 90-E-305
004	1	C40CS1002	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	Section 26 05 04	09-I-006, 90-E-305
005	1	C40CS1002	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	Section 26 05 04	09-I-006, 90-E-305
006	1	C40CS1002	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	Section 26 05 04	09-I-006, 90-E-305
007	1	C40CS1002	Potentiometer Transmitter, 4-20mA Output	AutomationDirect	FC-R1	_	09-I-006, 90-E-305
800	1	C40CS1002	Nameplate	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
009	3	C40CS1002	Legend Plates	Optimal Control Systems, Inc.	_	Section 26 05 04	90-E-305
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							







D CUENT MCCLURE & SONS COMMON	H G F E				OPTIMAL CONTROL SYSTEMS 2324 THREE LAKES RD / PO BOX 462 ALBANY, OR 97321 PHONE (541) 967-9323 FAX (541) 967-9485
B 2024.02.27. CDRRECTED KCED C40P1002 W3 PUMP 2 A 2023.10.25. Driginal Draft KCD PRAWN KCD SSUED 108 NO. 0723-08MSI REV DATE DESCRIPTION INIT CHECKED F DATE 2020.10.25 DWG NO. 7720-00MSI NO. 1000.1000.	D				MCCLURE & SINS (0)(0)
A 202310.25. Driginal Draft KCD PRAWN KCD SSUED NOB NO. 0723-08MSI REV DATE DESCRIPTION INIT CHECKED UP DATE 2023-10-25 PWG NO. 7220-00MSI PWG NO. 7220-00MSI PWG NO. 7220-00MSI NOB	С	2024.3.11	TERMINAL BLOCKS	HAD	TITLE COOS BAY WASTE WATER TREATMENT PLANT
REV DATE DESCRIPTION INIT CHECKED DATE DATE DOOD TO SEE DWG NO.	В	2024.02.27.	CORRECTED	KCEI	
REV DATE DESCRIPTION INIT MILLARD ME 2000 10 05 PM 1000 1000 1000 1000 1000	Α	2023.10.25.	Original Draft	KCD	DRAWN SSUED JOB NO. 0723-08MSI
REVISIONS APPROVED SCALE NONE SHEET 1 OF 1	REV	DATE	DESCRIPTION	I INIII	MILE OCCUPANTA OF PROPERTY AND ADDRESS AND
			REVISIONS		APPROVED SCALE NONE SHEET 1 OF 1





Your Enclosure Source ®

SCE-12108CHNFSS6

SCE-12108ELJSS6 - Cost Effective Alternative.



Product Specifications:

Part Number: SCE-12108CHNFSS6 Description: S.S. CHNF Enclosure Height: 12.13" Width: 10.00" Depth: 8.00" Price Code: S1 List Price: \$630.71 Catalog Page: 268 Est. Ship Weight: 16.00 lbs

Construction

- 0.063 In. stainless steel Type 316/316L.
- Seams continuously welded and ground smooth.
- Pour in place oil & water resistant gasket
- Ground stud on door.
- Stainless steel continuous hinge. ø
- Φ Standoffs provided for mounting optional panels.
- Welded mounting provision top and bottom of back.

Application

Designed for use as electrical junction boxes, terminal wiring boxes, instrument housings, and electrical control enclosures. For use in wet and hosed down areas and in corrosive atmospheres.

For Details about the Design, Performance Expectations, Applications and Design Suggestions - See Design Considerations www.saginawcontrol.com/instman/considerations.pdf

#4 brushed finish on all exterior surfaces. Optional sub-panels are powder coated white.

- Industry Standards (IS6)

 NEMA Type 3R, 4, 4X, 12 and Type 13

 UL Listed Type 3R, 4, 4X and 12
- CSA Type 4, 4X and 12
- IEC 60529
- IP 66

Notes

Special Instructions apply for IS3, IS4 and IS6 to maintain the environmental rating of Type 3R for these parts. Instructions are located on the enclosure door. Drip shield is required on IS3, drip shield is recommended on IS4 and IS6. Drain holes are required on all.

Optional Accessories

SCE-12P10 Subpanel, Flat SCE-12P10AL Subpanel, Flat Aluminum SCE-12P10GALV Subpanel, Flat Galvannealed SCE-12P10SS Subpanel, Type 316 SS SCE-BVK Breather Vent SCE-CHCLAMP Assembly, CH Clamp & Base SCE-DFJ1210 Panel, Dead Front (ELJ & CH) SCE-PLKJIC Padlock Kit

Similar Part Numbers

SCE-10086CHNFSS6S.S. CHNF Enclosure SCE-1008CHNFSS6S.S. CHNF Enclosure SCE-12106CHNFSS6S.S. CHNF Enclosure SCE-1212CHNFSS6S.S. CHNF Enclosure SCE-1412CHNFSS6S.S. CHNF Enclosure SCE-16148CHNFSS6S.S. CHNF Enclosure SCE-1614CHNFSS6S.S. CHNF Enclosure SCE-6044CHNFSS6S.S. CHNF Enclosure SCE-606CHNFSS6S.S. CHNF Enclosure SCE-8064CHNFSS6S.S. CHNF Enclosure

Installation Information

- Dead Front CH & ELJ Style Installation Instructions
- Padlock Kit For Junction Boxes
- Continuous Hinge Junction Enclosure

CONTINUOUS HINGE JUNCTION ENCLOSURES SERVICE PARTS





Your Enclosure Source ®

Saginaw Control and Engineering 95 Midland Road Saginaw, MI 48638-5770 (800) 234-6871 - Fax: (989) 799-4524 SCE@SaginawControl.com

SCE-PLKJIC

Product Specifications:



Part Number: SCE-PLKJIC Description: Padlock Kit Description: Padlock Kit Height: 3.00" Width: 2.00" Depth: 1.00" Price Code: P2 List Price: \$11.47 Catalog Page: 407 Est. Ship Weight: 1.00 lbs

ApplicationDesigned for CH, and CHNF enclosures. Maintains water-tight and dusttight seal. Made from stainless steel.


Industry Standards - (IS17) NEMA Not Applicable

- UL Not Applicable
- CSA N/A

Installation Information

Padlock Kit For Junction Boxes

SCE-PLKJIC INSTALLATION



- A. Pre-drill two 5/32 diameter holes in the door. Shown in "Enclosure Door Drill Detail"
- B. Pre-drill two 5/32 diameter holes in body. Shown in "Enclosure Body Drill Detail"


1.

Nut Plate Door Staple **Body Staple**


Screw (x2)


Keps Nut (x2)

- C. Align and place nut plate (Item 1) on exterior and door staple (Item 2) on interior of the door with the pre-drilled holes from step A.
- D. Fasten together the door staple and nut plate with Two 6-32 flat head screws (Item 4) onto the door.
- E. Place the body staple (Item 3) into the pre-drilled in the enclosure from step B.
- F. Fasten the body staple to the body with two 6-32 keps nut (Item 5) on the interior of the body.



ENCLOSURE DOOR DRILL DETAIL







Your Enclosure Source ®



SCE-12P10

Product Specifications:

Part Number: SCE-12P10 Description: Subpanel, Flat Height: 11.00" Width: 9.00" Depth: 0.08" Price Code: P3 List Price: \$8.59 Catalog Page: 440 Est. Ship Weight: 2.00 lbs

Finish

Powder Coated White.

Industry Standards - (IS17) NEMA Not Applicable UL Not Applicable

- CSA N/A

Similar Part Numbers

SCE-10P10Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P6Subpanel, Flat SCE-10P8Subpanel, Flat SCE-12DLP12Subpanel, Flat SCE-12P12Subpanel, Flat SCE-12P12CSubpanel, Flat SCE-12P16CSubpanel, Flat SCE-12P20CSubpanel, Flat SCE-12P24Subpanel, Bent SCE-12P6Subpanel, Flat

Installation Information

Sub-Plate Layout & Grounding for 3/8-16

30.5 mm Corrosion Resistant Watertight/Oiltight—E34



Product Description

Eaton's E34 Series 30.5 mm pushbutton line features the same rugged die cast construction of our 10250T line with an additional two-layer 100% solid thermosetting cathodic epoxy coating. This coating provides a flat black smooth, consistent, corrosion resistant surface that has passed a demanding 600 hour salt spray test. (The industry standard for this 4X test requires only 200 hours.)

Features

- Epoxy-coated metal operators
- Corrosion resistant
- Integral ground screw terminal on operators
- FDA approved for sanitary chemical resistance requirements

Contents

Description	Page
30.5 mm Corrosion Resistant Watertight/Oiltight—E	34
Product Overview	V7-T1-285
Product Identification	V7-T1-286
Catalog Number Selection	V7-T1-287
Ordering Complete Devices	V7-T1-289
Product Selection	
Non-Illuminated Momentary	
Pushbutton Units	V7-T1-290
Plastic Lens Indicating Light Units	V7-T1-290
Pushbuttons	V7-T1-291
Illuminated Pushbuttons and	
Indicating Lights	V7-T1-292
Push-Pull Units	V7-T1-294
Illuminated Push-Pull Units	V7-T1-295
Potentiometers	V7-T1-297
Push-Pull Operators	V7-T1-298
Selector Switch Units	V7-T1-302
Selector Switch Selection	V7-T1-303
Selector Switch Operators	V7-T1-306
Key Operators	V7-T1-306
Illuminated Selector Switch Operators	V7-T1-308
Accessories	V7-T1-309
Options	V7-T1-311
Replacement Parts	V7-T1-317
Technical Data and Specifications	V7-T1-319
Dimensions	V7-T1-322

Standards and Certifications

- CE EN60947-5-1 and 60947-5-5
- UL 508—File No. E131568
- CSA C22.2 No. 14—File No. LR68551
- FDA 3-A Sanitary Standards







Ingress Protection

When mounted in similarly rated enclosure—

- Standard indicating lights
 - UL (NEMA) Type 1, 2, 3, 3R, 3S, 4, 4X, 12, 13
 - IEC IP65
- All other operators
 - UL (NEMA) Type 1, 2, 3, 3R, 4, 4X, 12, 13
 - IEC IP65

Product Overview


Ultraviolet Light

E34 cathodic coating is not recommended for use in applications where exposure to ultraviolet light exists—use NEMA 4X 10250T operators.

Reliability Nibs

Eaton's contact blocks feature enclosed silver contacts with pointed "reliability nibs" for reliable performance from logic level up to 600V. To ensure reliable switching, nibs bite through oxide which can form on silver contacts, eliminating the need for expensive logic level blocks for most applications.

Reliability Nibs




Diaphragm Seal with Drainage Holes

Liquid Drainage


Eaton's pushbutton operators offer front of panel drainage via holes in the operator bushing. Hidden from view by the mounting nut, these holes prevent buildup of liquid inside the operator, which can prevent operation in freezing environments. The holes also provide a route for escaping liquid in high pressure washdowns, effectively relieving pressure from the internal diaphragm seal, ensuring reliable sealing in applications even beyond NEMA 4.

Diaphragm Seal




Product Identification

30.5 mm Corrosion Resistant Watertight/Oiltight-E34 Series



Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Standard Indicating Lights, PresTest and Master Test



Note

① Add X at end of catalog number to receive parts assembled from factory.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Catalog Number Selection is for illustrative purposes only and not to be used to create new catalog numbers.

Ordering Complete Devices

Complete E34 pushbuttons, indicating lights and/or selector switch operators including contact block(s) and legend plate can be ordered using a single composite catalog number. The


individually packaged components will be shipped unassembled in a single overpack carton marked with the composite catalog number.

Ordering Example

Illuminated Pushbutton Device—Catalog Number E34XB120V2-153SP90

For a complete Catalog Number breakdown, see **Pages V7-T1-287** to **V7-T1-288.**

For Complete E34 Device Ordering



Product Selection

Plastic Lens Indicating Light Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

24V Full Voltage Indicating Light

Indicating Light Units



Туре	Voltage	Color	LED/Lamp Number	Indicating Light ^① Catalog Number
LED Lamp				
Full voltage	24 Vac/Vdc	Red	Bayonet base	E34FB197LRP24
		Green		E34FB197LGP24
		Amber		E34FB197LAP24
	120 Vac	Red		E34FB197LRP2A
		Green		E34FB197LGP2A
		Amber		E34FB197LAP2A
Incandescent	Lamp			
Full voltage	24 Vac/Vdc	Red	#757	E34FB24H2X
		Green		E34FB24H3X
		Amber		E34FB24H9X
Resistor	120 Vac/Vdc	Red	120MB	E34RB120H2X
		Green		E34RB120H3X
		Amber		E34RB120H9X
Transformer	120 Vac	Red	#755	E34TB120H2X
	50/60 Hz	Green		E34TB120H3X
		Amber		E34TB120H9X

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see $\bf Pages~V7-T1-213~to~V7-T1-283$.

 $^{\scriptsize \textcircled{\tiny 1}}$ Anodized aluminum head—may not be suitable for some corrosive environments.

Illuminated Pushbuttons and Indicating Lights

Illuminated Pushbutton Operators without Lens



Indicating Light





Туре	Voltage	Lamp Number	Illuminated Pushbutton Catalog Number	Indicating Light Catalog Number	PresTest Catalog Number
LED Lamp (LEDs not	t included) ①				
Full voltage	_	Bayonet	E34CB497L	E34FB197L	E34FPB297L
Transformer AC only	24	base	E34XB024L	_	_
	120		E34XB120L	E34TB120L	E34TPB120L
	240		E34XB240L	E34TB240L	E34TPB240L
	277		E34XB277L	E34TB277L	_
	380		E34XB380L	E34TB380L	E34TPB380L
	480		E34XB480L	E34TB480L	E34TPB480L
	600		E34XB600L	E34TB600L	E34TPB600L
Incandescent Lamp					
Full voltage AC/DC	6	#755	E34CB06	E34FB06	E34FPB06
	12	#756	E34CB12	E34FB12	E34FPB12
	24	#757	E34CB24	E34FB24	E34FPB24
	32	#1828	E34CB32	E34FB32	E34FPB32
	48	#1835	E34CB48	E34FB48	E34FPB48
Resistor AC/DC ②	120	120MB	E34SB120	E34RB120	E34RPB120
	240		E34SB240	E34RB240	E34RPB240
Transformer AC only	24	#755	E34XB024	_	_
	120		E34XB120	E34TB120	E34TPB120
	240		E34XB240	E34TB240	E34TPB240
	277		E34XB277	E34TB277	_
	380		E34XB380	E34TB380	E34TPB380
	480		E34XB480	E34TB480	E34TPB480
	600		E34XB600	E34TB600	E34TPB600
Neon AC/DC	120	NE51H-R-22	_	E34NB120	_
	240	NE51H-4-68	_	E34NB240	_

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

① These units do not include lamps. Order LED separately to match lens color, see Page V7-T1-269 for LED Selection and Pages V7-T1-287 to V7-T1-288 for Catalog Numbering Selection.

② Resistor units are not available for use with LEDs, choose either transformer or full voltage LED style.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Plastic

Indicating Light Lens







Color	Plastic Catalog Number	Glass (1) Catalog Number	
Red	E34H2	E34G2	
Green	E34H3	E34G3	
Yellow	E34H4	E34G4	
White	E34H5	E34G5	
Blue	E34H6	E34G6	
Ambler	E34H9	E34G9	<u> </u>
Clear	E34H0	E34G0	

E34V_

Illuminated Pushbutton Lens



Color	Catalog Number
Red	E34V2
Green	E34V3
Yellow	E34V4
White	E34V5
Blue	E34V6
Ambler	E34V9
Clear	E34V0

Plastic

PresTest Lens







Red E34V2 E34P2 Green E34V3 E34P3	og Number
Green E34V3 E34P3	
Yellow E34V4 E34P4	
White E34V5 E34P5	i
Blue E34V6 E34P6	 i
Ambler E34V9 E34P9	
Clear E34V0 E34P0	

Note

 $^{\scriptsize \textcircled{\tiny 1}}$ Glass lens has black anodized aluminum bezel.

Vertical or Horizontal One-Hole Mounting ³

Potentiometers

Potentiometer

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13



Potentiometer with Knob and Standard Dial Plate—Linear Type $\pm 10\%$

Catalog Number				
2 Watt (60V Max.) Single Potentiometer with Standard Aluminum Dial Plate @®				
E34PDB1F1				
E34PDB1F2				
E34PDB1F5				
E34PDB1F10				
E34PDB1F25				
E34PDB1F50				
E34PDB1A0				
E34LP99				

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- ① X = closed circuit, 0 = open circuit.
- ② To order different type or color lens, substitute the underlined characters with appropriate suffix code from table on the bottom of Page V7-T1-295.
 - Example: E34GFB79M3-3X. For LEDs with different voltages see ordering example on Page V7-T1-301.
- 3 Shown with standard aluminum dial plate.
- Large dial plate with space for legend is available at no charge. To order, add suffix 36 to catalog number. Example: E34PDB1F136. To order separately, see footnote
 below.
- ⑤ Large dial plate has space at top for 15 letters. 3/32 in high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.
- 6 For use with commercially purchased potentiometers having shaft dimensions per dimension drawing on Page V7-T1-274.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Standard LED Lamp

24 V

LED Selection

Voltage	Color	Catalog Number	Voltage	Color	Catalog Number
6 Vac/Vdc	Red	E22LED006RN	60 Vac/Vdc	Red	E22LED060RN
suitable for use with	Orange	E22LED006ON		Orange	E22LED0600N
transformers	Yellow	E22LED006YN		Yellow	E22LED060YN
	Green	E22LED006GN		Green	E22LED060GN
	Blue	E22LED006BN		Blue	E22LED060BN
	White	E22LED006WN		White	E22LED060WN
12 Vac/Vdc	Red	E22LED012RN	120 Vac	Red	E22LED120RA
	Orange	E22LED012ON		Orange	E22LED1200A
	Yellow	E22LED012YN		Yellow	E22LED120YA
	Green	E22LED012GN		Green	E22LED120GA
	Blue	E22LED012BN		Blue	E22LED120BA
	White	E22LED012WN		White	E22LED120WA
24 Vac/Vdc	Red	E22LED024RN	120 Vdc	Red	E22LED120RD
	Orange	E22LED0240N		Orange	E22LED1200D
	Yellow	E22LED024YN		Yellow	E22LED120YD
	Green	E22LED024GN		Green	E22LED120GD
	Blue	E22LED024BN		Blue	E22LED120BD
	White	E22LED024WN	 ;	White	E22LED120WD
48 Vac/Vdc	Red	E22LED048RN			
	Orange	E22LED048ON			
	Yellow	E22LED048YN	 ;		
	Green	E22LED048GN			

E22LED048BN

E22LED048WN

Blue White

Selector Switch Units

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

- Two-, three- and four-position—maintained
- · Non-illuminated and illuminated

Two-Position Maint. Switch Knob

Two-Position Selector Switch



Operator Position ①							Non-Illuminated		Illuminated—120V Transformer	
			Operator Action ^②	Contact Type	Mounting Location A B	Cam Code	Black Knob Catalog Number ^③	Black Lever Catalog Number ³	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
	X	0	M\/M	1NC	ماه	1	E34VFBK <u>1</u> -1X	E34VFBL <u>1</u> -1X	E34VFB120ER-1X	E34VFB120FR-1X
	U	Х	IVI VIVI	1N0						

Three-Position Maint.

Three-Position Selector Switch



Opera	tor Pos	sition (1)					Non-Illuminated		Illuminated—120V Transformer	
			Operator Action ^②	Contact Type	Mounting A	Location B	Cam Code	Black Knob	Black Lever Catalog Number ^③	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
X 0	0 0	0 X	M	1N0	 		3	E34VHBK1-2X	E34VHBL1-2X	E34VHB120TER-2X	E34VHB120TFR-2X
			_	1N0		0 0					
Χ	0	0		1N0			3	E34VHBK <u>1</u> -23X	E34VHBL <u>1</u> -23X	E34VHB120TER-23X	E34VHB120TFR-23X
0	Χ	0			0 0						
0	0	X		2NC (Series)	-مىن	—aro					
				1N0		00					

Four-Position Maint. Switch Lever

Four-Position Selector Switch



	Operator Position ①								Non-Illuminated		Illuminated—120V Transformer		
					Operator Action ②	Contact Type	Mounting A	Location B	Cam Code	Black Knob Catalog Number ®	Black Lever Catalog Number ®	Red Knob Catalog Number ^③	Red Lever Catalog Number ^③
Ì	X	0	-	0	м м	1NC	<u>م ا ه</u>		7	E34VTBK <u>1</u> -23X	E34VTBL <u>1</u> -23X	E34VRB120TER-23X	E34VRB120TFR-23X
	0 0 0	X 0 0		0 0 X	M	1N0	→						
						1N0		~ ~					
						1NC		مله					

Color Selection, Non-Illuminated

Color	Code Letter	Color	Code Letter	
Black	1	White	5	
Red	2	Blue	6	
Green	3	Gray	7	
Yellow	4	Orange	8	

Notes

For Light Unit Voltage Suffix and Knobs, Levers tables, see {\bf Page V7-T1-308}.

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize (1)}$ X = closed circuit, 0 = open circuit.
- ② M = Maintained.
- To order different type or color selector switch, substitute the underlined character with appropriate suffix code from the Color Selection table. Example: E34VFBK<u>2</u>-X1.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Selector Switch Selection




Cam and Contact Block Selection

Selector switches in their varied forms (two-position, three-position and four-position) are a big factor contributing to the great flexibility of control that a well rounded line of "pushbuttons" can achieve. Because of their flexibility, they tend to cause difficulty with product selection and application. The following systematic approach should simplify that task.

Cam and contact block selection is better understood if you:

- Work with each incoming and outgoing wire/circuit separately.
- Recognize the terms NO and NC only identify the type of contact by its mode before mounting to the operator. The "X-O" chart (Page V7-T1-305) shows how that contact will act after assembly to the operator with the selected cam shape. X = closed circuit, O = open circuit.
- Up to six NO or NC contacts may be mounted behind each plunger location for a total of twelve contacts. Single circuit contact blocks have only one plunger with the other side of the block "open." Therefore, single circuit contact blocks transmit motion to blocks behind them only for the position containing the circuit.
- Each cam has two separate lobes, each of which operates one of the two contact block plungers independently of each other. Those are identified as position A (locating nib side) and position B (opposite of locating nib). The position designations give direction in selecting and mounting of the contact blocks.

Contact Circuit Locations




Systematic Approach

Application: **HAND-OFF- AUTO** selector switch. In this circuit, one incoming line is distributed to two other outgoing circuits by the switch. The two circuits can be looked at individually.

Step 1: Elementary Diagram.

Construct on paper, or in your mind, a simple elementary diagram of the switching scheme as follows:



Step 2: "X-O" Pattern.

From the elementary diagram, you can construct an "X-O" diagram which describes when the contacts are to be closed (X) or open (O) in the various positions of the switch. The "X-O" for the **HAND** circuit looks like this:

HAND OFF AUTO

A
A
X
O
O

In this circuit, you want a contact closed on the left (HAND) but open in the center and right.

For the **AUTO** circuit, the "X-O" diagram would look like this:



Putting them together, the complete "X-O" diagram is:

X O O

Once the "X-O" diagram has been generated, the next step is to select the cam and contact block, or blocks, needed to perform the desired "X-O" functions. The selection tables on the following pages list the various types (shapes) of cams by number to choose from and the type of contact and position to achieve the function outlined in your "X-O" diagram.

Step 3: Cam Selection.

The cam you select determines the operation of all contact blocks mounted to the operator. It is selected on the basis that it provides the simplest circuitry for the desired "X-O" diagram. The selection tables show all the "X-O" combinations. For the purpose of this example, the applicable portion of those tables is shown on this page.

Now to make the cam selection, make a simple worksheet such as:

	<u>Cam 2</u>	Cam 3
X O O	(A)NO-(B)NC	(A)NO
0 O X	(B)NO	(B)NO

It becomes immediately obvious that cam 3 is the better choice for two reasons, (1) the series combination can be avoided making it simpler to wire, (2) only two contacts are required, which is less expensive than the three contacts required by cam 2.

Step 4: Contact Block Selection.

Having selected the cam, contact block selection is simply a matter of gathering the A position and B position circuits into pairs which make up the most convenient contact block arrangement. If there is an imbalance in the number of circuits under A or B, then single circuit blocks must be selected for these leftover circuits.

Back to the worksheet, having selected cam 3 do this:



Step 5: Selector Switch Operator.

Lastly, you have to choose from the many types of operators—knob and lever in various colors or keyed. Also what combinations of maintained and spring return functions are required. Selection of these operators can be found on **Page V7-T1-306**. For the example in step 4, you may want a three-position maintained black knob, cam 3—Catalog Number E34VHBK1.

The Complete Switch:

E34VHBK1 with one 10250T2 or, for one composite catalog number, E34VHBK1-Y1 found on Page V7-T1-303.

Diagrams

Circuits shown illustrate connections to obtain a selector switch circuit combination and are shown with their appropriate line diagrams. Field wiring of jumper connections required as shown.

X = Closed circuit O = Open circuit

Wiring of Jumper Connections





Parallel Connection

Four-position selector switches are limited to four contact blocks.

Contact Blocks

For selection and number of available contact blocks per operator, see **Page V7-T1-315**.

Example Selection Table

				Cam C	ode #2	Cam Cod	e #3
No.	"X-0	" Patterr	1	Top A	Bottom B	Top A	Bottom B
1	Х	0	0	- -	D 0.10-	-0 -0-	_
				NO	NC	NO	
4	0	0	Х	_	-0 -0-	_	-0 0-
					NO		NO

Two-Position Selector Switch Contact Block Selection

Desired Circuit and Operator Position

		90	Contact Blocks Required to Accomplish Circuit Function			
No.	D		Top Plunger A	Bottom Plunger B		
1	Х	0	— <u>Q⊥Q</u> NC or	<u>-о го-</u> NC		
2	0	Х	or NO	 		

Note

① Wired in series.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Three-Position Switch—Cam and Contact Block Selection

					red to Accomplish Circuit talled where indicated)	Function
	Desired C Operator	Circuit and Position		Operator with Cam Co Mounting Location	ode #2 Operator v Mounting	vith Cam Code #3 Location
No.				Top Bottom Plunger Plunger A B	Top Plunger A	Bottom Plunger B
1	Х	0	0		 	
2	Х	Х	0	− <u>O L O</u> NC	_	-O_L_O- NC
3	X	0	X	 NO		NO NO
4	0	0	Х	 O NO		
5	0	Х	Х	TO O O		
6	0	X	0	— <u>О. I. О</u> — NC	— <u>Q⊥Q</u> NC	NC

Four-Position Switch—Contact Block Selection

100	1 1 0 31 1.		reon	Jones	Contact B Required t Accomplis	locks to	•					Contact B Required t Accompli	to
No.		ed Circuit tor Positi			Function Mounting Top Plunger A	Location Bottom Plunger B	No.		ed Circui tor Posit			Function Mounting Top Plunger A	Location Bottom Plunger B
1	Χ	0	0	0	— <mark>⊙⊥⊙</mark> —		10	Х	0	Х	0		
2	0	Х	0	0								NC NO	
3	0	0	Х	0	-O O- NO		11	X	Х	Х	0	TO 0	
4	0	0	0	Х		—O_LO— NC	_					NC NO	NO
5	Χ	0	0	Х	TO LO	NC NC	12	0	Х	Х	X	70-0-	010
6	0	Х	Х	0	To o	NO NO	_					NO	NC NC
7	0	0	Х	X		NC NC	13	X	0	Х	X	To o	010
8	Χ	Х	0	0	TO LO	NO NO	_					NC NC	NC
9	0	X	0	X		NO NC	14	Х	X	0	X	NC NC	NO NC

1

Selector Switch Operators

UL (NEMA) Type 3, 3R, 4, 4X, 12, 13

Two-Position Knob Selector Switch

Operators with Knob Assembled



	Operator	Black Knob Selector Switch— Vertical Mounting ②			
Positions	Action ①	Cam Code ③	Catalog Number [®]		
Two-position—60° throw	M M	1	E34VFB <u>K1</u>		
	M	1	E34VEB <u>K1</u>		
Three-position—60° throw	M	2	E34VGB <u>K1</u>		
	$M \longrightarrow M$	3	E34VHB <u>K1</u>		
	M _	2	E34VJB <u>K1</u>		
	S M	3	E34VKB <u>K1</u>		
	y M ⋅	2	E34VLB <u>K1</u>		
	SS	3	E34VMB <u>K1</u>		
	M 👡	2	E34VNB <u>K1</u>		
	MS	3	E34VPB <u>K1</u>		
Four-position—40° throw	M M	7	E34VTB <u>K1</u>		
	MM				

Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light, see Pages V7-T1-213 to V7-T1-283.

- $^{\scriptsize \textcircled{1}}$ M = Maintained. S = Spring return in direction of arrow (R).
- ② Field convertible to horizontal mounting.
- ® For selection of the proper cam and contact block to obtain the proper circuit sequence, see selection instructions and tables on Pages V7-T1-303 to V7-T1-305.
- For other colors of either the knob or lever, replace the underlined characters of the catalog number with the appropriate suffix code from Alternate Knob and Lever table on Page V7-T1-307. Example: E34VFBL2.
- © Choose key removal position required for application from table on Page V7-T1-307. Add key removal code number to listed catalog number. Example: E34KFB2.

E34K_

E34L



F34A



Alternate Knobs and Levers for Operators ^②

	Knob		Lever		Lever Designed for Added Ingress Protection ³		
Color	Suffix Code	Catalog Number	Suffix Code	Catalog Number	Suffix Code	Catalog Number	
Black	K1	E34K1	L1	E34L1	A 1	E34A1	
Red	K2	E34K2	L2	E34L2	A2	E34A2	
Green	К3	E34K3	L3	E34L3	А3	E34A3	
Yellow	K4	E34K4	L4	E34L4	A4	E34A4	
White	K5	E34K5	L5	E34L5	A5	E34A5	
Blue	К6	E34K6	L6	E34L6	A6	E34A6	
Gray	К7	E34K7	L7	E34L7	A7	E34A7	
Orange	K8	E34K8	L8	E34L8	A8	E34A8	

Notes

- $^{\scriptsize\textcircled{\tiny{1}}}$ Key removal in "spring return from" positions not recommended.
- ② See operators on Page V7-T1-306.
- For use on maintained operators only.

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Contact Blocks

Standard Contact Blocks

- UL A600/P600 rated
- Color-coded plungers—red/ green for NC/NO circuits
- Silver contact tips with "reliability nibs"
- Black (opaque) or amber (translucent) housings
- Pressure plate or spade terminals
- Fingerproof shrouds (for pressure terminals only)

Logic Level Contact Blocks

- UL A600/P600 rated
- · Black plungers
- Inert palladium knife-blade contacts
- Black (opaque) housings
- Pressure plate or spade terminals
- Fingerproof shrouds not available

Special Function Contact Blocks

- UL A600/P600 rated
- Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals
- Fingerproof shrouds not available

Special Purpose Contact Block

- Maximum 300V rated
- · Black plungers
- Silver contact tips with "reliability nibs"
- Black (opaque) housings
- Pressure plate terminals only
- Fingerproof shrouds not available

Reliability Nibs

Reliability nibs are the hallmark of Eaton's contact blocks. A pointed silver nib on the contact tip ensures reliable switching from logic level (5V) up to 600V applications. Therefore standard contact blocks can be used for most logic level applications where the contacts are not exposed to any harsh environmental conditions.

Palladium Contacts

Palladium, which is more inert than gold, is well suited for voltages and currents approaching zero and is recommended for applications where environmental conditions are a factor.

Maximum Contact Block Mounting per Operator Type

Operator	Max. Stack
Pushbuttons	6
Push-pull operators	2
Roto-push operators	4
Two- or three-position selector switches	6
Four-position selector switches	4
Joysticks	4

10250T1

Contact Blocks



Symbol	Circuit	Description ①	Standard Pressure Terminal Catalog Number	Spade Terminal ② Catalog Number	Logic Level Pressure Terminal Catalog Number	Spade Terminal ^② Catalog Number
O I O Blank No Plunger	1NC	Stack up to six blocks (six circuits) unless otherwise noted.	10250T51	10250T59	10250T51E	10250T59E
O O Blank No Plunger	1N0	Stack up to six blocks six circuits) unless otherwise noted.	10250T53	10250T60	10250T53E	10250T60E
0 0 0 1 0	NO-NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T1	10250T40	10250T1E	10250T40E
010010	2NC	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T3	10250T42	10250T3E	10250T42E
0 0 0 0	2N0	Stack up to six blocks (12 circuits) unless otherwise noted.	10250T2	10250T41	10250T2E	10250T41E
Special Funct	tion Block	(S ^③				
Blank No Plunger	LONC	Late opening NC. Stack up to six blocks (six circuits) unless otherwise noted.	10250T71 ^③	-	10250T71E 3	_
	ECNO- NC	Early closing NO and standard NC. Stack up to six blocks unless otherwise noted.	10250T47 3·4	_	10250T47E ③	_
7-000	ECNO- NO	Early closing NO and standard NO. Stack up to four blocks unless otherwise noted.	10250T57 3·4	-	10250T57E ③	_
<u>a.p</u> a.p	2LONC	Two late opening NC contacts. Stack up to six blocks unless otherwise noted.	10250T45 ^③	-	10250T45E ③	_
d 10	LONC- ECNO	Overlapping contacts. Stack up to four blocks unless otherwise noted.	10250T55 34	_	10250T55E ³	_
Special Purpo	ose Block	S ⁽⁵⁾				
	2NO- 2NC	Four circuits in single block depth. Rated 300V max. Stack up to four blocks unless otherwise noted.	10250T44 ®	_		

Notes


- ① All 10250T contact blocks shown are suitable for use on standard 10250T and E34 operators. These contact blocks are not suitable for Class I Division 2 type 10250T or E34 devices.
- ② Contact blocks with spade terminals are limited to a maximum of one contact block per operator and minimum spacing between devices is 2.5 in (63.5 mm). Not suitable for use in 10250T or E34 enclosures. Also available in amber housing. Not available with fingerproof shrouds.
- Special function contact blocks are not suitable for use with roto-push operators, three-position push-pull operators, or four-position selector switches.
- ECNO contact blocks are not suitable for use with two-position joysticks or when operators are used with padlock attachments.
- Special purpose 10250T44 contact blocks are not suitable on selector switches or roto-push operators. Okay to use with three-position push-pull operators only on low voltage (30V or less) circuits.




Flush Head Pushbutton Operator



Mushroom Head Pushbutton Operator



Jumbo Mushroom Head Operator



Potentiometers



Illuminated Pushbutton Operator



Transformer Type Indicating Light



Knob-Operated Selector Switch Operator



Dart

Full Voltage, Resistor and Transformer Type Illuminated Selector Switch

E34 Style Operator Replacement Parts

No.	Description	No. Req.	Part Number
1	Gasket	1	16-1548
2	Mounting nut	1	15-1530-4
3	Set screw (#6-32 x 0.250 in long hollow hex)	2	11-2014
4	Mushroom head button (includes [2] item 5)	1	As Req. Below
	Black	_	53-1317
	Red	_	53-1317-2
	Yellow	_	53-1317-3
	Green	_	53-1317-4
	Blue	_	53-1317-22
5	Set screw (#10-32 x 0.250 in long hollow hex)	2	11-544
6	Jumbo mushroom head button (aluminum—includes [2] item 5)	1	As Req. Below
	Red	_	53-1317-9
	Black	_	53-1317-10
	Yellow	_	53-1317-11
	Green	_	53-1317-12
7	Jumbo mushroom head button (aluminum—red EMERG. STOP) does not include item 5	1	53-1349-18
8	Mounting screw (#6-32 x 0.710 in long)	2	10250TA79
	Washer	2	16-2038
9	Terminal screw and lug (captive)	Req.	80-5502
10	Gasket (supplied with basic unit)	1	32-803
11	Round head screw (#4-40 x 0.344 in long) (supplied with basic unit)	2	11-4553

Item No.	Description	No. Req.	Part Number
12	Mounting screw	2	11-1632
13	Simple potentiometer (does not include items 18, 28 or 29)	1	As Req. Below
	1,000 ohms	_	41-782-2
	2,500 ohms	_	41-782-3
	5,000 ohms	_	41-782-10
	10,000 ohms	_	41-782-4
	25,000 ohms	_	41-782-5
	50,000 ohms	_	41-782-6
14	Connector (includes screw and lug)	2	25-1851
15	Indicating plate	1	As Req. Above
	Standard size (without legend)	_	30-4460
	Large size (specify legend)	_	10250TR30
16	Retaining nut	1	15-1547-3
17	Knob	1	53-1314
	Socket set screw (#6-32 x 0.250 in long)	1	11-2014
18	Coupling	1	11-2014
			29-3749-2
19	Set screw (#6-32 x 0.188 in long)	1	11-1199
20	Spacer	2	56-1066-18
21	Connector (includes screw and lug)	1	25-1851-2
22	Mounting nut	1	15-1938-2

30.5 mm Corrosion Resistant Watertight/Oiltight—E34

Technical Data and Specifications

Mechanical Ratings

Description	Specification		
Frequency of Operation			
All pushbuttons	6000 operations/hr.		
Key and lever selector switches	3000 operations/hr.		
Auto-latch devices	1200 operations/hr.		
Life			
Pushbuttons	10 x 10 ⁶ operations		
Contact blocks	10 x 10 ⁶ operations		
PresTest units	10 x 10 ⁶ operations		
Lever and key selector switches	0.25 x 10 ⁶ operations		
Twist to release pushbuttons	0.3 x 10 ⁶ operations		
Shock Resistance			
Duration	210 ms ≥5g		

General Specifications

Description	Specification				
Climate Conditions					
Operating temperature	1° to 150°F (-17° to 66°C)				
Storage temperature	-40° to 176°F (−40° to 80°C)				
Altitude	6,562 ft (2,000m)				
Humidity	Max. 95% RH at 60°C				
Terminals					
Marking	NC-NO on the contact block to meet the NEMA requirements. Dual marking system 1–2 for normally closed, 3–4 for normally open to meet BS5472 (Cenelec EN50 005).				
Clamps	Terminals are saddle clamp type for 1 x 22 AWG (0.34 mm 2) to 2 x 14 AWG (2.5 mm 2) conductors				
Torque	7 lb-in (0.8 Nm)				
Degree of protection against direct electrical contact	IP2X with fingerproof shroud				
Light Units					
Transformers	Will withstand short-circuit for 1 hour per IEC 60947-5-1				
Bulbs—average life:					
Transformer type	20,000 hrs.				
Resistor/direct voltage type	2500 hrs. minimum at rated V				
LED	60,000 to 100,000 hrs.				

Electrical Ratings

Description	Specification				
Insulation	U _i = 660 Vac or Vdc				
Thermal	$I_{th} = 10A$				
Short Circuit Coordination to IEC/EN 609	47-5-1				
Rated conditional short circuit current	1 kA				
Fuse type	GE power controls TIA 10, red spot type gG, 10A, 660 Vac, 460 Vdc, BS88-2, IEC 60269-2-1				
UL rating	A600, P600				
AC load life duty cycle 1200 operations/hour					
10A	110V pf 0.4—1 x 10 ⁶ operations				
5A	250V pf 0.4—1 x 10 ⁶ operations				
2A	600V pf 0.4—1 x 10 ⁶ operations				
Switching capacity					
AC 15 rated make/break (11 x I _e at 1.1 x U _e)					
6A	120V pf 0.3				
4A	240V pf 0.3				
2A	660V pf 0.3				
DC13 rated make/break (1.1 x I _e at 1.1 x U _e)					
1.0A	125V L/R ≥0.95 at 300 ms				
0.55A	250V L/R ≥0.95 at 300 ms				
0.1A	660V L/R ≥0.95 at 300 ms				
10A	110V pure resistive				
Maximum ratings for logic level and hostile atmosphere application					
Maximum amperes	0.5A				
Maximum volts	120 Vac/Vdc				
Low voltage switching	Conical shaped points or "reliability nibs" improve performance in dry circuit, corrosive, fine dust and other contaminated atmospheres. Under normal environmental conditions, the minimum operational voltage is 5V and the minimum operational current is 1 mA, Vac/Vdc.				
Contact operation	Slow make and break. All normally closed contacts have positive opening operation, i.e., normally closed contacts are forced open in the event of contact weld or spring breakage.				

Electrical Ratings—Contact Block

Meet or Exceed NEMA Rating Designations A600, A300 and B300 for AC and P600 for DC $\,$

	50 Vac or 60 H				Vdc		
Description	120	240	480	600	24/28	125	250
Meet or Exceed NEMA Rating Designations A600,	A300 and B300 f	or AC and	P600 for DC	;			
Make and emerg. interrupting capacity (amp)	60	30	15	12	5.7	1.1	0.55
Normal load break (amp)	6	3	1.5	1.2	5.7	1.1	0.55
Thermal current (amp)	10	10	10	10	5.0	5.0	5.0
Voltamperes:							
Make and emerg. interrupting capacity	7200	7200	7200	7200	138	138	138
Normal load break	720	720	720	720	138	138	138

Mounting Options

Panel Thickness

• Minimum: 0.06 in (1.6 mm)

• Maximum: 0.25 in (8 mm) including legend plate

• Maximum can be increased to 0.375 in (15.9 mm) using optional retaining nut


• Indicating light: 10250TA30

Pushbutton/selector switch: 10250TA31

Mounting Matrix

Legend	Dimensions in Inches (mm)							
Plate	A	В	C	D				
Small	1.63 (41.3)	2.25 (57.2)	2.25 (57.2)	1.63 (41.3)				
Medium	1.75 (44.5)	2.25 (57.2)	2.25 (57.2)	1.75 (44.5)				
Large	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)	2.25 (57.2)				

Mounting Options in Inches (mm)




Horizontal Mounting

Vertical Mounting

Horizontal mounting means terminals are located top and bottom of contact block. Vertical mounting means terminals are left and right of contact block. This allows close spacing of adjacent operators with easy access to terminals.

Locating nib hole or notch is 0.14 in (3.6 mm) #29 drill.

Drilling Dimensions in Inches (mm)



Eaton E34FPB297LGP2A

Catalog Number: E34FPB297LGP2A

Eaton E34 pushbutton, Green, Corrosion Resistant Assembled Indicating Light, PresTest, LED, Full voltage, NEMA 3, 3R, 4, 4X, 12, 13, 120 Vac, Bayonet base, Green, Plastic, 120 V

General specifications



Product Name Catalog Number
Eaton E34 pushbutton E34FPB297LGP2A

UPC Product Length/Depth

782114718933 0.01 in

Product Height Product Width 0.01 in 0.01 in

Product Weight Warranty 0.01 lb 1 year

Compliances Certifications
FDA 3-A UL Listed
CE Marked CSA Certified

Catalog Notes

Use NEMA 4X 10250T operators where exposed to ultraviolet light



Product specifications

LED lamp number

Bayonet base

Supply voltage

120 Vac

Light unit type

LED, full voltage

Series

E34

Туре

30.5 mm, Corrosion Resistant Watertight/Oiltight

Lamp voltage

120 Vac

Rating

NEMA 4

NEMA 3

NEMA 12

NEMA 4X

NEMA 13

NEMA 3R

Lens material

Plastic

Lens color

Green

Actuator

PresTest

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34FPB297LGP2A

Cam selection for pushbutton selectors

Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.







Eaton E34PDB1F1

Catalog Number: E34PDB1F1

Eaton E34 Potentiometer, 30.5 mm, Corrosion Resistant, 60 Vac/dc, 2W DC coil power, NEMA 3, 3R, 4, 4X, 12, 13, 1000 Ohms

General specifications



Product Name Catalog Number
Eaton E34 potentiometer E34PDB1F1

UPC Product Length/Depth

2.4 in

Product Height Product Width

3. in 2 in

Product Weight Warranty
0.35 lb 1 year

Compliances Certifications
CE Marked UL Listed
FDA 3-A CSA Certified

Catalog Notes

Large dial plate with space for legend is available at no charge. Large dial plate has space at top for 15 letters, 3/32 inch high. For custom stamped legend plates, order legend plate as separate item 10250TR30 and specify stamping.



Product specifications

Product Category

Potentiometer

Resistance

 1000Ω

Special features

2W DC coil power

Series

E34

Type

30.5 mm, Corrosion Resistant

Rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Voltage rating

60 Vac/dc

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity

Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Eaton Specification Sheet - E34PDB1F1

Cam selection for pushbutton selectors



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

Eaton E34VHBL1-2X

Catalog Number: E34VHBL1-2X

Eaton E34 pushbutton selector switch, Corrosion Resistant Watertight/Oiltight, 30.5 mm, Selector switch, Knob, 1/4 in, Three-position, Cam 3, Maintained, NEMA 3, 3R, 4, 4X, 12, 13

General specifications



Product Name Catalog Number
Eaton E34 pushbutton selector switch E34VHBL1-2X

UPC Product Length/Depth 782113027753 2 in

Product Height Product Width 3.5 in 2.5 in

Product Weight Warranty 0.3 lb 1 year

Compliances
CE Marked



Product specifications

Product Category

Selector switch

Number of positions

3

Series

E34

Type

Knob

Operating mode

Maintained

NEMA rating

NEMA 3, NEMA 3R, NEMA 4, NEMA 4X, NEMA 12, NEMA 13

Size

1/4 in

Cam code

Cam 3

Resources

Brochures

10250T and E34 Class I Division 2

Catalogs

Eaton's Volume 7—Logic Control, Operator Interface and Connectivity Solutions

Multimedia

How to size and select a Power Supply

Specifications and datasheets

Cam selection for pushbutton selectors

Eaton Specification Sheet - E34VHBL1-2X



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2023 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia

FC-R1 Cut Sheet





AutomationDirect temperature transmitter, isolated, Input: 1-channel, RTD, deg F or deg C, Output: 1-channel, current, 24 VDC operating voltage, 35mm DIN rail or panel mount, removable screw terminal plugs.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/FC-R1

Technical Specifications

Brand	AutomationDirect
Item	Temperature transmitter
Isolation	Isolated
Field Configurable	Yes
Number Of Input Channels	1
Input	RTD
Input RTD Signal Types	Pt100, Pt1000 and Cu10
Programmable Temperature Range	Deg F or deg C

Number Of Output Channels	1
Output	Current
Output Current Signal Range	4-20 mA
Operating Voltage	24 VDC
Housing Material	Plastic
Mounting	35mm DIN rail or panel
Electrical Connection	Removable screw terminal plugs

Agency Approvals

UL Listed File #	None
UL Recognized File #	None
UL Hazardous File #	E200031
CE	View CE declarations
CSA File #	None
RoHS Status	Yes (See CE Doc)
EU REACH	View EU REACH document

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/FC-R1.pdf See store item page for other formats. THIS PAGE LEFT BLANK

FC-R1 RTD Input Loop Powered Signal Conditioner



Overview

The <u>FC-R1</u> is a DIN-rail or side-mount Resistive Temperature Detector signal conditioner. It is a non-isolated signal conditioner which converts a 3-wire RTD to a linearized 4-20 mA current loop signal.


The <u>FC-R1</u> has a user selectable CU10 (10 Ohm copper), PT100 (100 Ohm platinum) or PT1000 (1000 Ohm platinum) RTD input, and also offers OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET has an adjustment range of 0 to 25% of full scale output and the SPAN has an adjustment of 80% to 102%.




Click on the thumbnail or go to https://www.automationdirect.com/ VID-TE-0006 for a short video on Remote Temperature Sensing

Application


The <u>FC-R1</u> field configurable input signal conditioner is useful for interfacing RTD sensors to PLC analog current input modules. It is recommended that shielded RTDs be used whenever possible to minimize noise on the input signal.





Specifications							
	CU10	-200°C to 260°C	-328°F to 500°F				
Input Ranges	PT100	-328°F to 1562°F					
	PT1000	-200°C to 595°C	-328°F to 1103°F				
RTD Excitation Current	CU10, РТ100 500 µA ±50 µA РТ1000 80 µA ±20 µA						
Common Mode Range		0 - 3.5 VD	С				
Output Range		4-20 mA (linea	rized)				
Maximum Inaccuracy	0.35% FSO / CU10 0.2% FSO @ 25°C / PT100 & PT1000 0.26% FSO @ 60°C / PT100 & PT1000						
Maximum Loop Supply	30VDC						
Load Impedance	0Ω minimum						
Maximum Load/Power Supply	203Ω / 12V, 745Ω / 24V						
Linearity Error	0.35% FSO / CU10 0.2% FSO / PT10 & PT1000						
Output Slew Rate	1% @ 20 mS						
Filter Characteristics	105 dB @ DC, 60 dB @ 10 Hz, 40 dB @ 60Hz						
Stability		0.05% FSO ma	ximum				
Operating Temperature		0 to 60°C (32 to	140°F)				
Storage Temperature		-20 to 70°C (-4 to	158°F)				
Relative Humidity	5 to 90% (non-condensing)						
Environmental Air	No corrosive gases permitted						
Vibration		ML STD 810C	514.2				
Shock	ML STD 810C 516.2						
Noise Immunity		NEMA ICS3-	304				

Typical User Wiring



RTD Signal Conditioner to 4-20 mA DL05/06 analog module Only use three wire and four wire RTDs.

FC Series Accessories





FC-35MM

Description

Universal terminal block replacements for the FC Series signal conditioners. Each packcage includes enough terminal blocks to replace all the terminal blocks on any FC Series signal conditioner according to the following table:

	FC Series Terminal Blocks							
FC Series Model	Terminal Block Replacement Part Number	Package Includes						
FC-11								
FC-33	EO EMM	(2) 2-pole blocks						
FC-R1	FC-5MM	(2) 3-pole blocks (1) 4-pole blocks						
FC-T1		(1) 1 polo blooks						
FC-ISO-C								
FC-ISO-D		(6) 2-pole blocks						
FC-B34		(2) 3-pole blocks						
FC-35B	FC-35MM	(2) 4-pole blocks (1) 5-pole blocks						
FC-P3		(1) 6-pole blocks						
FC-3RLY2		(2) 8-pole blocks						
FC-3RLY4								

Note: Depending on the model, some terminal blocks in the package may be unused.


Universal Signal Conditioners									
Part No.		Rated Torque (N·m)	Weight (Lbs)	Price					
<u>FC-5MM</u>	Terminal block, replacement, 5mm. Package of 5. For use with FC Series signal conditioners.	0.5	0.1	\$18.00					
<u>FC-35MM</u>	Terminal block, replacement, 3.5mm. Package of 14. For use with FC Series signal conditioners.	0.2	0.1	\$33.00					

www.automationdirect.com Signal Conditioners tPSC-26

FC-R1 RTD INPUT LOOP POWERED SIGNAL CONDITIONER

Product Guide

3505 HUTCHINSON ROAD CUMMING, GA 30040-5860



Description:

The FC-R1 is a DIN rail mount, Resistive Temperature Detector, signal conditioner. FC-R1 is non-isolated, 3-wire RTD which converts to linearized 4-20 mA current loop.


The FC-R1 has user selectable, CU10 (10 Ohm Copper), PT100 (100 Ohm Platinum), PT1000 (1000 Ohm Platinum) RTD Input, but also has OFFSET (zero) and SPAN (full scale) adjustments of the output signal. The OFFSET (zero) has an adjustment range of 0 to 25% of full scale output, the SPAN (full scale) has an adjustment of 80 to 102%.

Application

The FC-R1 field configurable input signal conditioner is useful for interfacing RTD sensors to our PLC analog current input modules. Use shielded RTD's whenever possible to minimize noise on the input signal. Ground the shield wire at one end only. The suggested 3-lead configuration shown provides one lead to (+) terminal, one lead to the (-) terminal and one lead to the (COM) terminal. Compensation circuitry nulls out the lead length for accurate temperature measurements. Some sensors have 4-leads, when making connections, do not connect the second lead to the (+) terminal, leave that lead unconnected.

Input Selection

The signal conditioner can be configured for either CU10, PT100, PT1000 Input and Output signal type of 4 - 20mA.



EXAMPLE:
PT100 INPUT
4 - 20 mA OUTPUT

Input Ranges		Switch Position						
IIIµut naliyes	1	2	3	4	5	6	7	8
CU10	0	0	1	0	1	0	1	1
PT100	1	0	0	0	1	1	0	1
PT1000	0	1	0	0	0	0	0	0

Specifications

Input Ranges	Ranges					
	CU10	-200°C to 260°C	-328°F to 500°F			
	PT100	-200°C to 850°C	-328°F to 1562°F			
	PT1000	-200°C to 595°C	-328°F to 1103°F			
RTD Excitation Current	CU10 & PT100	500μA :	± 50μA			
TITO EXCITATION GUITGIN	PT1000	80μA ± 20μA				
Common Mode Range	0-3.5 VDC					
Maximum Inggayyayı	CU10	0.35% FS0				
Maximum Inaccuracy (Includes Offset, Span, Linearity)	PT100 & PT1000	0.2% FSO @ 25°C				
(moradoo onoot, opan, Emourty)	PT100 & PT1000 0.26% FS0					
Maximum Loop Supply	30VDC					
Load Impedance	0Ω Minimum					
Maximum Load	12V Power Supply	203Ω				
maximum Luau	24V Power Supply	745Ω				
Linearity Error	CU10	0.35% FSO				
Lilicality Lilui	PT100 & PT1000	0.2%FSO Maximum				
Output Slew Rate	1% @ 20mS					
Filter Characteristics	105dB @ DC, 60dB @ 10Hz, 40dB @ 60Hz					
Stability	0.05% FSO Maximum					

NOTE: All data 0-60°C except where specified.

Input Setting Explanation


The default setting from the factory is PT100. This selects the DIN (Deutsche Institute for Normung) requirements for accuracy of the RTD element. The temperature vs. resistance curve, RTD's are calibrated to DIN 43760, BS1995, or IEC751 specifications which is $0.00385\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=138.50\Omega$).

The PT1000 utilizes the same type curve except it is ($100^{\circ}C = 1385\Omega$).

The CU10 utilizes temperature coefficient of $0.0042\Omega/\Omega/^{\circ}C$ ($100^{\circ}C=12.89683\Omega$)


Precision excitation currents are used to generate voltage drop across the RTD element. To maintain accuracy it is important that all 3 RTD wires are the same length.


It is suggested if your application does not need modified OFFSET or SPAN - DO NOT ADJUST potentiometers since this loses the factory calibration.



Operating Specifications

Operating Temperature	0 to 60°C (32 to 140°F)
Storage Temperature	-20 to 70°C (-4 to 158°F)
Relative Humidity	5 to 90% (non-condensing)
Environmental Air	No Corrosive Gases Permitted
Vibration	MIL STD 810C 514.2
Shock	MIL STD 810C 516.2
Noise Immunity	NEMA ICS3-304





Input Temperature - PT100 Type RTD

 Max_{temp} - Min_{temp} = $Total_{temp}$ / Counts = resolution 850° - (-200°) = 1050° / $4095 = 0.256^\circ$ C / count - resolution

Actual $_{temp}$ - Min_{temp} = $Total_{temp}$ / Resolution = Counts 325° - (-200°) = 525° / 0.256° = 2050 Counts

Counts X Resolution = $Total_{temp}$ + Min_{temp} = $Actual_{temp}$ 2048 X 0.256° = 524.3° + -200° = 324.3°C

UL Information

A. THIS EQUIPMENT IS SUITABLE FOR USE IN CLASS I, DIVISION 2, GROUPS A, B, C AND D OR NON-HAZARDOUS LOCATIONS ONLY.

Cet équipement est conçu pour être utilisé dans des environnements de Classe I, Division 2, Groupes A, B, C, D ou non dangereux.

B. WARNING - EXPLOSION HAZARD - SUBTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2/ZONE 2.

AVERTISSEMENT: Risque d'explosion: la substitution de composants peut compromettre la convenance pour la Classe I, Division 2/Zone 2.

C. WARNING - EXPLOSION HAZARD - DO NOT DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NON-HAZARDOUS.

AVERTISSEMENT: Risque d'explosion: Ne pas déconnecter l'équipement à moins que l'alimentation soit coupée ou que la zone soit reconnue non dangereuse.



MANUFACTURER'S CERTIFICATE OF PROPER INSTALLATION

OWNER	_ EQPT SERIAL NO:
EQPT TAG NO:	EQPT/SYSTEM:
PROJECT NO:	SPEC. SECTION:
I hereby certify that the above-referenced ed	quipment/system has been:
(Check Applicable)	
☐ Installed in accordance with Manufa	acturer's recommendations.
☐ Inspected, checked, and adjusted.	
Serviced with proper initial lubrican	ts.
☐ Electrical and mechanical connection	ns meet quality and safety standards.
☐ All applicable safety equipment has	been properly installed.
☐ Functional tests.	
System has been performance tested requirements. (When complete system of	l, and meets or exceeds specified performance of one manufacturer)
Note: Attach any performance test docu	mentation from manufacturer.
Comments:	
I, the undersigned Manufacturer's Represent authorized representative of the manufactur inspect, approve, and operate their equipme recommendations required to ensure equipme and operational, except as may be otherwise information contained herein is true and accommendations.	er, (ii) empowered by the manufacturer to nt and (iii) authorized to make nent furnished by the manufacturer is complete e indicated herein. I further certify that all
Date:	, 20
Manufacturer:	
By Manufacturer's Authorized Representati	
	(Authorized Signature)

THIS PAGE LEFT BLANK



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

MAINTENANCE SUMMARY FORM

PROJECT:		CONTRACT NO.:					
1. EQUIPME	NT ITEM						
2. MANUFA	CTURER						
3. EQUIPME	3. EQUIPMENT/TAG NUMBER(S)						
4. WEIGHT	4. WEIGHT OF INDIVIDUAL COMPONENTS (OVER 100 POUNDS)						
5. NAMEPLA	ATE DATA (hp, voltage, speed, etc.) _						
6. MANUFA	CTURER'S LOCAL REPRESENTAT	IVE					
a.	Name_	Telephone No.					
	Address	-					

7. MAINTENANCE REQUIREMENTS

Maintenance Operation Comments	Frequency	Lubricant (If Applicable)
List briefly each maintenance operation required and refer to specific information in manufacturer's standard maintenance manual, if applicable. (Reference to manufacturer's catalog or sales literature is not acceptable.)	List required frequency of each maintenance operation.	Refer by symbol to lubricant required.



COOS BAY WWTP 1 PHASE 1A FINAL DESIGN

8. LUBRICANT LIST

Reference Symbol	Shell	Exxon Mobile	Chevron Texaco	BP Amoco	Or Equal	
List symbols used in No. 7 above.	List equivalent lubricants, as distributed by each manufacturer for the specific use recommended.					

9. RECOMMENDED SPARE PARTS FOR OWNER'S INVENTORY.

Part No.	Description	Unit	Quantity	Unit Cost		
Note: Identify parts provided by this Contract with two asterisks.						

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements

Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods

Date: September 2025



Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	1	C92ZS9401	Limit Switch, Pre-Wired Factory Sealed, Corrosion Resistant, Lever Type, Spring Return Operating Lever, Corrosion Resistant Roller Lever, Adjustable, Type 316 Stainless Steel	Allen-Bradley	802MC-AY5	_	09-1-009
002	1	C92ZS9401	Operating Lever, Corrosion Resistant Roller Lever, Adjustable, Type 316 Stainless Steel	Allen-Bradley	802MC-W2B	_	09-1-009
003							
004							
005							
006							
007							
008							
009							
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
030							
038							
039							
040							

THIS PAGE LEFT BLANK

802MC Corrosion-resistant Prewired — Factory Sealed Switches

802MC corrosion-resistant switches have the following features:

- · Prewired and factory sealed
- Corrosion resistant
- Submersible



Specifications

Attribute	Value
Certifications	UL Listed, CSA Certified, and CE Marked for applicable directives
Enclosure type rating	NEMA 1, 4X, 6P, 13; and IP66/67 (IEC 529)
Pollution degree	3
Ambient temperature (1)	080 °C (32180 °F)

⁽¹⁾ Minimum temperature is based on the absence of freezing moisture or water.


Table 13 - AC Contact Rating (Max per Pole, 50 or 60 Hz, Two Circuits Same Polarity)

NEMA Rating	Max Voltage	Voltage A		Continuous	VA	
Designation	[AC]	Make	Break	Carrying Current [A]	Make	Break
	120	60	6.00		10 7200	
A600	240	30	3.00	10		720
AC-15	480	15	1.50			
	600	12	1.20			

Table 14 - DC Contact Rating (Max per Pole, Two Circuits Same Polarity)

Nominal Voltage	A	Continuous Carrying Current [A]
24	1.1	5

Factory Sealed









Adjustable Top Push Rod

Side Push Rod

Top Push Roller

Product Selection


	IMDECOT Lover Movement ve Contact Operation		Torque/Force	Travel to	Max Travel	Travel to Reset Contacts, Max	Cat. No.		
Number of Circuits			to Operate,	Operate Contacts, Max			Switch without Lever ⁽¹⁾	Operator Head Only	Switch Body Only ⁽¹⁾
	Clockwise or Counterclockwise	10 02 10 02 10 02 30 04 30 04 30 04					802MC-AY5	802MC-AX	
2	Clockwise	10 02 10 02 10 02 30 04 30 04 30 04	0.34 N•m (3 lb•in)	15°	86°	6°	802MC-A1Y5	802MC-A1X	802MC-XY5
	Counterclockwise	10 02 10 02 10 02 30 04 30 04 30 04					802MC-A2Y5	802MC-A2X	

⁽¹⁾ The standard length of STO cable is 1.52 m (5 ft). For other lengths, see Table 16 on page 27.

Approximate Dimensions

Dimensions are shown in mm (in.). Dimensions are not intended to be used for installation purposes.

IMPORTANT For operating head and lever assembly dimensions that are not shown, see <u>Approximate Dimensions on page 132</u>. Conduit pipe opening 1/2 in. NPT.




Wiring Diagrams

IMPORTANT See applicable codes and laws.

Cable Models Cable Models with Status Indicator 5-pin Mini Receptacle Black White Black White 1 \bigcirc \bigcirc Same Polarity Same Polarity Black White Same Polarity Same Polarity 4 1 Same Polarity Orange Red Orange Red Orange No Connection No Connection Status Indicator Wired J9 Wiring Status Indicator Wired J1 Wiring to N.O. (White) Wire to N.C. (Orange) Wire

5-pin Mini-type Receptacle Status Indicator



Modifications for 802MC Limit Switches

Status Indicators

Bulletin 802MC prewired limit switches can be supplied with a status indicator that is wired to one side of either the N.O. or N.C. contact. The second lead of the status indicator is available as a fifth conductor for wiring flexibility.



Neon Status

To order, add the appropriate suffix that is listed in Indicator Table 15 to the Cat. No. Example: Cat. No. 802MC-AY5 with a 120V AC LED status indicator that is wired across the N.O. contact would be Cat. No. 802MC-AY5L1F.

Table 15 - Status Indicators

Voltage	Voltage Wired to:		
LED			
24V DC ⁽¹⁾	N.O. contact	LF	
24V DC ***	N.C. contact	LC	
120V AC 5060 Hz	N.O. contact	L1F	
	N.C. contact	L1C	
Neon			
120V AC	N.O. contact	NF	
5060 Hz	N.C. contact	NC	
240V AC 5060 Hz	N.O. contact	N5F	
	N.C. contact	N5C	


⁽¹⁾ Requires switch to be rated for 24V DC operation.

5-pin Mini-type Receptacle — Two-circuit Contact Block



A 5-pin mini-type receptacle is supplied to facilitate retrofitting existing installations. The normal ground wire pin is not required and is not connected inside the switch.

To order a Bulletin 802MC pre-wired limit switch with a 5-pin mini connector in place of the 1.52 m (5 ft) of STO ^(a) cable, replace the Y5 in the Cat. No. with the suffix J1 or J9 depending upon the wiring configuration required. Maximum voltage rating for this receptacle is 250V AC.



An appropriate female connector with cable (Cat. No. 889N-F5AFC-6F) is available.

Cable Lengths

The factory-installed, prewired, type STO cable is normally supplied in 1.52 m (5 ft) lengths. Extended cable lengths are available in multiples of 4 feet. To order, replace the suffix Y5 in the Cat. No. with the appropriate suffix from Table 16. Example: A lever-type spring return switch with 1.83 m (8 ft) of STO cable is Cat. No. 802MC-AY8. Cable lengths up to 96 feet are available as a special order.

Table 16 - Additional Cable Lengths

Modifications	Cat. No. Suffix
1.83 m (8 ft) cable	Y8
3.66 m (12 ft) cable	Y12
4.78 m (16 ft) cable	Y16

Two-circuit 24V DC Switches

All two-circuit Bulletin 802MC limit switches are available with silver-nickel contacts and rated for 24V DC applications. To order a switch rated for 24V DC use, insert the letter Z before the cable or connection designation. Example: Cat. No. 802MC-AZY5 is a 24V DC version of Cat. No. 802MC-AY5. The use of the 24V DC status indicator option requires the switch be rated for 24V DC operation.

a) STO is a common identification of this cable. The complete identification of the cable that is used on the Bulletin 802M is STOOW-A, which incorporates an oil-resistant jacket and conductor insulation, for indoor and outdoor use.

Bulletin 802

IMPORTANT For use with 802M, 802MC, 802R, 802T, 802X, and 802XR

Roller Levers

	Roller				
Туре	Material	Dia. [in.]	Width [in.]	Cat. No.	
Non-adjustable Cast Lever 0.75 in. Radius	Metal	0.75	0.27	802T-W9A	
	Nylon	0.75	0.28	802T-W1	
	Nylon	0.75	1	802T-W1H	
-	Dual nylon	0.75	1(each)	802T-W1HH	
	Steel	0.75	0.25	802T-W1A	
Non-adjustable Cast	Steel	0.75	0.75	802T-W1N	
Lever 1.5 in. Radius Roller on Front	Ball bearing	0.75	0.23	802T-W1B	
Koller off Front	Beryllium copper (nonsparking)	0.75	0.28	802T-W1J	
	Nylon	0.75	0.75	802T-W1L	
	Nylon	0.75	0.28	802T-W1E	
	Nylon	0.75	1	802T-W1D	
60 O	Nylon	1.5	0.28	802T-W1G	
Non-adjustable Cast Lever 1.5 in. Radius	Steel	0.75	0.25	802T-W1F	
Roller on Rear	Steel	0.75	0.75	802T-W1C	
	Nylon	0.75	0.75	802T-W1M	
	Nylon	0.75	0.28	802T-W20	
	Nylon	0.75	1	802T-W20D	
	Steel	0.75	0.25	802T-W20A	
Non-adjustable Steel Lever 2.0 in. Radius	Steel	0.75	0.75	802T-W20B	
Roller on Front	Ball bearing	0.75	0.23	802T-W20C	
	Beryllium copper	0.75	0.28	802T-W20E	
	Nylon	0.75	0.28	802T-W20J	
THE COLUMN	Nylon	0.75	1	802T-W20K	
	Steel	0.75	0.25	802T-W20L	
Non-adjustable Steel Lever 2.0 in. Radius	Steel	0.75	0.75	802T-W20M	
Roller on Rear	Ball bearing	0.75	0.23	802T-W20N	
	Beryllium copper	0.75	0.28	802T-W20P	
	Nylon	0.75	0.75	802T-W18	
Non-adjustable Steel Lever 2-1/8 in. Radius Roller on Front	Nylon	0.75	1	802T-W18A	

Roller Levers, continued

	ı			
Туре	Material	Dia. [in.]	Width [in.]	Cat. No.
	Nylon	0.75	0.28	802T-W25
	Nylon	0.75	1	802T-W25D
	Steel	0.75	0.25	802T-W25A
Non-adjustable Steel Lever 2.5 in. Radius	Steel	0.75	0.75	802T-W25B
Roller on Front	Ball bearing	0.75	0.23	802T-W25C
	Beryllium copper	0.75	0.28	802T-W25E
	Nylon	0.75	0.28	802T-W25J
9	Nylon	0.75	1	802T-W25K
() () () () () () () () () ()	Steel	0.75	0.25	802T-W25L
Non-adjustable Steel Lever 2.5 in. Radius	Steel	0.75	0.75	802T-W25M
Roller on Rear	Ball bearing	0.75	0.23	802T-W25N
	Beryllium copper	0.75	0.28	802T-W25P
	Nylon	0.75	0.28	802T-W30
	Nylon	0.75	1	802T-W30D
6	Steel	0.75	0.25	802T-W30A
Non-adjustable Steel Lever 3.0 in. Radius	Steel	0.75	0.75	802T-W30B
Roller on Front	Ball bearing	0.75	0.23	802T-W30C
	Beryllium copper	0.75	0.28	802T-W30E
	Nylon	0.75	0.28	802T-W30J
- est	Nylon	0.75	1	802T-W30K
() () () () () () () () () ()	Steel	0.75	0.25	802T-W30L
Non-adjustable Steel Lever 3.0 in, Radius	Steel	0.75	0.75	802T-W30M
Roller on Rear	Ball bearing	0.75	0.23	802T-W30N
	Beryllium copper	0.75	0.28	802T-W30P
	Nylon	0.75	0.28	802T-W2
	Nylon	0.75	1	802T-W2D
	Nylon	1.5	0.28	802T-W2A
Institute Officers	Steel	0.75	0.25	802T-W2B
Adjustable Lever 1.193	Ball bearing	0.75	0.23	802T-W2C
in. Radius	Steel	1.4	0.27	802T-W2E
	Rubber	1.5	0.5	802T-W2R
	Beryllium copper	0.75	0.28	802T-NX94
The state of the s	Nylon	0.75		802T-W17
	Metal	0./0	0.28	802T-W17B
Adjustable Lever 1.193.5 in. Radius	Nylon	1.5		802T-W17A

Roller Levers, continued

	Roller				
Туре	Material	Dia. Width [in.]		Cat. No.	
	Nylon (L.H. roller on front; R.H. roller on back)	0.75	0.28	802T-W4	
	Steel (L.H. roller on front; R.H. roller on back)	0.75	0.25	802T-W4B	
	Nylon (both rollers on front)	0.75	0.28	802T-W4A	
	Nylon (both rollers on rear)	0.75	0.28	802T-NX115	
Fork Lever 1.5 in. Radius	Nylon (both rollers on front)	0.75	1	802T-W4F	
	Steel (both rollers on front)	0.75	0.25	802T-W4C	
	Nylon (L.H. roller on back; R.H. roller on front)	0.75	0.28	802T-W4D	
	Nylon (R.H. adj.)	0.75	0.28	802T-W6	
	Steel (R.H. adj.)	0.75	0.25	802T-W6A	
	Ball bearing (R.H. adj.)	0.75	0.23	802T-W6B	
Micrometer Adjustment	Nylon (L.H. adj.)	0.75	0.28	802T-W6C	
Lever 1.5 in. Radius ⁽¹⁾	Steel (L.H. adj.)	0.75	0.25	802T-W6D	
	Ball bearing (L.H. adj.)	0.75	0.23	802T-W6E	
	Nylon (R.H. adj.)	0.75	1	802T-W6F	
	Nylon	0.75	0.28	802T-W7 ⁽²⁾	
NI A II O M	Steel	0.75	0.25	802T-W7A ⁽²⁾	
Non-Adj. One-Way Lever 1.5 in. Radius	Ball bearing	0.75	0.23	802T-W7B ⁽²⁾	
	Nylon	0.75	0.28	802T-W12 ⁽³⁾	
New Adj. Office to	Steel	0.75	0.25	802T-W12A ⁽³⁾	
Non-Adj. Offset Lever 1.44 in. Radius Roller on Front	Bearing roller	0.75	0.23	802T-W12B	
	Nylon	0.75	0.28	802T-W12E	
Non-Adj. Offset Lever 1.44 in. Radius Roller on Rear	Steel	0.75	0.25	802T-W12F	

The micrometer adjustment roller lever is designed especially for installations where the position of the roller is a critical factor. This lever has a pivoted roller that can be turned laterally. After clamping the lever to the switch shaft, the position of the roller can be precisely adjusted through an arc of 7.5° on either side of the center or straightline position. line position.

Roller Levers - Corrosion-resistant

	Roller				
Туре			Width [in.]	Cat. No.	
1.5 in. Radius Roller on Front	Type 316 stainless steel roller, roller pin, and clamp pin One-piece cast aluminum arm is protected with TUFRAM® (1)	0.75	0.25	802MC-W1A	
1.5 in. Radius Roller on Rear	Nylon Roller One-piece cast aluminum arm is protected with TUFRAM	1.5	0.28	802MC-W1G	
Non-Adj. Offset Lever 1.44 in. Radius Roller on Front	Nylon Roller One-piece cast aluminum arm is protected with TUFRAM ⁽¹⁾	0.75	0.28	802MC-W12	
Adjustable 1.193 in. Radius	Type 316 stainless steel roller, roller pin, clamp pin, and adjustable lever arm Block is cast aluminum protected with TUFRAM (1)	0.75	0.25	802MC-W2B	

TUFRAM is a synergistic coating that combines the advantages of anodizing with a controlled infusion of PTFE for added corrosion resistance.

Rod Levers

Туре	Material	Dia. [in.]	Cat. No.	
	Stainless steel rod 5 in. long	0.13	802T-W3 ⁽¹⁾	
	Stainless steel rod 8.5 in. long	0.13	802T-W3B ⁽¹⁾	
	Stainless steel rod 12 in. long	0.13	802T-NX50	
	Ctainless steel red 11 F in Jana	0.13	802T-W3A	
	Stainless steel rod 11.5 in. long	0.08	802T-W3F ⁽²⁾	
	Stainless steel rod 14 in. long	0.13	802T-NX159	
	Nylon rod 12 in. long	0.25	802T-W3C 802T-NX142 ⁽³⁾	
	Stainless steel rod 5 in. long	0.06	802T-W5 ⁽¹⁾	
9	Stainless steel rod 5 in. long one way	0.06	802T-W8 ⁽⁴⁾	
	Nylatron looped rod 6 in. long, 2 in. wide loop	0.18	802T-W14	
	Nylatron looped rod 9 in. long, 2 in. wide loop	0.10	802T-NX119	
6	Steel rod 9 in. long	0.25	802T-W16	
	Nylon rod 9 in. long	0.23	802T-W16A	

Recommended for use with low operating torque switches.
 Not for use with 802M-NPY5 or 802M-ASY5 type switches.
 Recommended for high impact applications.
 Do not use on maintained contact limit switches.

Do not use on maintained contact limit switches.

When mounted on plug-in devices, the offset lever provides equivalent cam tracking to the NonPlug-In devices using catalog number 802T-W1 levers.

Rod Levers — Corrosion-resistant


Туре	Material	Dia. [in.]	Cat. No.
<u> </u>	Type 316 stainless steel rod 5 in. long Block is cast aluminum protected with TUFRAM ⁽¹⁾	0.13	802MC-W3
<u> </u>	Type 316 stainless steel rod 11.5 in. long Block is cast aluminum protected with TUFRAM ⁽¹⁾	0.08	802MC-W3A
<u> </u>	Nylon rod 12 in. long Block is cast aluminum protected with TUFRAM ⁽¹⁾	0.25	802MC-W3C
	Nylon rod only	0.25	WF25507

⁽¹⁾ TUFRAM is a synergistic coating that combines the advantages of anodizing with a controlled infusion of PTFE for added corrosion resistance.

Approximate Dimensions

Dimensions are shown in mm (in.). Dimensions are not intended to be used for installation purposes.

802 Levers




Cat. No. 802T-W3C

Shipping Wt. 57 g (2 oz)

Shipping Wt. 57 g (2 oz)

Dimensions are shown in mm (in.). Dimensions are not intended to be used for installation purposes.



THIS PAGE LEFT BLANK



802MC Pre-Wired Factory Sealed Corrosion Resistant

802MC-AY5



Representative Rendering, Not The Actual Product

Limit Switch, Pre-Wired Factory Sealed, Corrosion Resistant, Complete Switch, Lever Type, Spring Return, Standard Operating Torque, 2-Circuit, CW and CCW operation, 1.52m (5ft) length STO cable

Product Details

SWITCH DATA	
Switch Components	Complete Switch
Actuation Type	Lever Type, Spring Return, Standard Operating Torque
Number of Circuits	2-Circuit
Mode of Operation	CW and CCW operation
Travel to Operate Contacts (Max)	15°
Torque to Operate Contacts (Max.)	0.34N.m (3lb in)
Travel to Reset Contacts (Max.)	6°
Maximum Travel	86°
MODIFICATIONS	
24V DC Switch	AC Model
Indicating Lights	No Indicating Light(s)
Connection Options	1.52m (5ft) length STO cable (standard)
NOTE	Build to Order Cable Length
OPERATING LEVER DATA	
Operating Lever	Operating Lever Not Selected

Supporting Documentation and Downloads

• Photo

THIS PAGE LEFT BLANK



NEMA Style Operating Levers

802MC-W2B



Representative Rendering, Not The Actual Product

Operating Lever, Corrosion Resistant Roller Lever, Adjustable, 1.19 to 3.0 In, Roller On Front, Type 316 Stainless Steel, 0.75 In, 0.25 In

Product Details

OPERATING LEVER DATA	
Lever Type	Corrosion Resistant Roller Lever
Adjustable or Non-Adjustable	Adjustable
Radius	1.19 to 3.0 ln
Roller Material	Type 316 Stainless Steel
Roller Diameter	0.75 In
Roller Width	0.25 In
Roller Position	Roller On Front
ADDITIONAL INFORMATION	
Message	Operating Lever 802T-W3F Should Not Be Used With 802M-NPY5 or 802M-ASY5 Switches.
Message	Do Not Use 802T-W7, 802T-W7A, 802T-W7B On Maintained Contact Limit Switches.

Supporting Documentation and Downloads

• Photo

THIS PAGE LEFT BLANK

Bill of Materials

Project: Coos Bay Wastewater Treatment Plant 1 Phase 1A Improvements

Specification Section(s): Section 26 05 04 – Basic Electrical Materials and Methods

Date: September 2025



Item No.	Qty.	Control Station	Description	Manufacturer	Manufacturer Part Number	Specification Section	Drawing
001	10	SPARE PARTS	Replacement Lamp, LED, 120V AC/DC	Eaton	E22LED120WN	_	_
002	2	SPARE PARTS	Indicating Light, PresTest, LED, Full Voltage, Amber	Eaton	E34FPB297LAP2A	_	_
003	2	SPARE PARTS	Indicating Light, PresTest, LED, Full Voltage, Green	Eaton	E34FPB297LGP2A	_	_
004	2	SPARE PARTS	Pushbutton, Flush, Black, 1NO	Eaton	E34PB1-53	_	_
005	2	SPARE PARTS	Potentiometer, 1k Ohms	Eaton	E34PDB1F1	_	_
006	2	SPARE PARTS	Selector Switch, 2-Position, Black Lever, 1NC/1NO	Eaton	E34VFBL1-1X	_	_
007	2	SPARE PARTS	Selector Switch, 3-Position, Black Lever, 2NO	Eaton	E34VHBL1-2X	_	_
008							
009							
010							
011							
012							
013							
014							
015							
016							
017							
018							
019							
020							
021							
022							
023							
024							
025							
026							
027							
028							
029							
030							
031							
032							
033							
034							
035							
036							
037							
038							
039							
040							

THIS PAGE LEFT BLANK